UNITED STATES

DEPARTMENT OF INTERIOR GEOLOGICAL SURVEY

COLLECTION, REDUCTION and INTERPRETATION of MARINE SEISMIC SONOBUOY DATA

by

Jonathan R. Childs and Alan K. Cooper

OPEN FILE REPORT

78-442

U.S. Geological Survey
OPEN FILE REPORT

This report is preliminary and has not been edited or reviewed for conformity with Geological Survey standards.

Any use of trade names and trademarks in this publication is for descriptive purposes only and does not constitute endorsement by the U.S. Geological Survey.

TABLE OF CONTENTS

I.	INTRODUCTION	1
II.	THE SONOBUOY METHOD A. General Technique B. Methods of Analysis	3 3 5
III.	FIELD OPERATIONS A. General Information B. Equipment Description 1. Sonobuoys 2. Receivers 3. Analog tape recorder 4. Graphic recorders and recording techniques C. Sonobuoy Preparation and Launch D. Underway Operations E. Replaying Analog Tapes	15 15 17 17 18 20 23 26 36 38
IV.	REDUCTION AND INTERPRETATION OF FIELD RECORDS A. Shipboard Interpretation B. Office Procedures 1. Preparing the records 2. Choosing and tracing seismic horizons 3. Digitizing and editing seismic horizons a. General notes on the Tektronix system b. Digitizing programs c. Digitizing refractions d. Digitizing reflections e. Editing reflection data 4. Processing the digitized data on MULTICS 5. Interpretation programs	40 40 40 41 42 44 46 50 51 60 66
٧.	References	69

Appendices

A.		and penetration of sonobuoys	71							
В.		ty of sound in sea water	74							
C.		ard interpretation of refractions and	-0							
_	reflec		78 2=							
D.		tion ray tracing theory	85							
Ε.		ure outline for digitizing and processing								
		oy records	96							
F.		tions to reduction results	100							
	1.	Corrections for hydrophone lower	101							
	2.	Corrections for dipping interfaces	102							
G.	Exampl	es of digitizing programs	106							
H.	Exampl	es of reduction programs	154							
I.	Examples of interpretation programs									
		SONOMODEL example	165							
		Calculating sediment thickness versus								
		travel time curves	169							
J.		gs of digitizing programs	172							
K.		gs of reduction programs	192							
L.		g of interpretation program	214							
	Lis	t of Illustrations								
Figure	1	Schematic illustration of sonobuoy								
		data collection	4							
Figure	2	Sonobuoy record in shallow water	6							
Figure	3	Sonobuoy record in deep water	7							
Figure	4	Schematic illustration of wide angle								
•		reflection and refraction geometry								
		with sonobuoy recording.	10							
Figure	5	Model of shallow water sonobuoy	13							
Figure		Model of deep water sonobuoy	14							
Figure		Schematic layout of sonobuoy equipment	16							
Figure		Diagram of receiver circuitry	19							
Figure		Example log forms	29-32							
Figure		Picking wide angle reflections	52							
Figure		Overlays for user definable keys	56							
Figure		Range and penetration of sonobuoys with	,,,							
1 15 u i 0	, _	relation to geologic province	73							
Figure	13	Variation of velocity of sound in	1 2'							
1 1000 0	• 5	sea water with depth for the Southern								
		Bering Sea, summer months	75							
Figure	111	Convention for determining slopes	10							
: 15 m e	17	of horizons	105							
Figure	15	Plot output from program SONOMODEL.	לטו							
r TRUILE	1)		168							
Figure	16	This example is also used in Figure 6.	171							
		- crevenanta reversaren Wild Scholad Ulia								

List of Tables

Table 1	Checklist for sonobuoy preparation	
	and launch	27
Table 2	Functions of user definable keys	
	for SLODIGIT	53
Table 3	Procedure for digitizing and editing	
_	wide angle reflections	59

I. INTRODUCTION

Over the past three years the U.S. Geological Survey has been developing a program for the collection of sonobuoy seismic data aboard the U.S.G.S. research vessel S.P. LEE, and for the subsequent reduction and analysis of those data. The sonobuoy seismic studies have been conducted primarily over the Alaskan continental shelf and the contiguous deep water basins, often in conjunction with multichannel seismic reflection surveys. In this report, we wish to describe in detail the present sonobuoy program, covering both the collection of data at sea and the reduction and interpretation of data back in the office.

The report is divided into three sections. The first is a review of the main principles of seismic refraction and wide angle reflection theory, including background information for the specific techniques referred to in the report. The second section describes the equipment currently available on the S.P. LEE and contains an outline of the procedures that have been developed for data collection. In the last section, the procedures and computer program for digitizing, editing, reducing and interpreting the sonobuoy field records are described, and instructions for their use included. Following this section are numerous appendices containing program listings, derivations, examples and other useful information.

In designing the current sonobuoy program, we are indebted to investigators at Lamont-Doherty Geological Observatory and Woods Hole Oceanographic Institute who laid the groundwork in this field of study. In particular, we have adopted several procedures, especially in the area of data

reduction, from a report by S.T. Knott and Hartley Hoskins (1975). Their technical report, which describes the sonobuoy program at Woods Hole, has proved invaluable in our work.

II. THE SONOBUOY METHOD

General Technique

The routine use of sonobuoys in marine geophysical studies was developed by Lamont-Doherty Geological Observatory in the 1960's, following the initial development of the technique by Hill (1963) in the post-war years. The method proved to be an economical, dependable, and relatively quick technique to determine velocity-depth variations within the sediments of marine basins. Since that time, the sonobuoy profiling method has come into much greater use in marine geophysics for the study of velocity distribution within not only sedimentary basins, but within the oceanic crust as well. The sonobuoy method enhances other standard vertical incidence seismic profiling techniques, by providing velocity information which can be used to convert reflection time on the vertical incidence record to true depth. The methods originally developed at Lamont to record, reduce and interpret sonobuoy data are still the primary basis for more recent work. Recent improvements in equipment and technology have been responsible for increased interest in the method.

Basically, a sonobuoy is a free floating buoy that contains a battery powered radio transmitter and a hydrophone. When the sonobuoy is dropped into the water from a seismic ship, the hydrophone is released and sinks to a predetermined depth. As the ship moves away, the seismic energy from the ship-towed source (usually air guns or arcer) is detected by the hydrophone and is relayed back to the ship by the radio transmitter for recording and display (see Fig. 1). The sonobuoy is usually left to scuttle itself after several hours, because retrieval is unfeasible. Sonobuoys are used to increase the range over which seismic energy is normally collected (e.g. the length of a towed hydrophone), thereby producing better reflection velocity information





Figure 1 Schematic illustration of sonobuoy data collection, with various seismic travel paths indicated. Only one interface (the seafloor) is shown. Compare with subsequent figures (2-5) to see how these paths are displayed graphically

from deep sedimentary and crustal layers, as well as detecting refracted energy from these same deep layers. Before the development of sonobuoy methods, refraction studies were limited to two ship operations, involving high, often prohibitive costs. Now, these refraction surveys can be done concurrently with other geophysical studies by using the relatively inexpensive, expendable sonobuoys. Appendix A illustrates the types of research problems for which the sonobuoy technique is well suited.


The use of high energy, rapidly firing, seismic sources, initially developed for multichannel seismic reflection work, has dramatically improved the quality of sonobuoy data. These sources provide a highly consistent and coherent outgoing pulse. Consequently, the reflected and refracted arrivals from deep as well as shallow sedimentary and crustal layers can easily be identified when displayed on high density (40 shot traces per inch) graphic recorders, often out to distances exceeding 40 kilometers. Figures 2 and 3 illustrate graphically recorded sonobuoy data using a large airgun source (1326 cu in. - 5 gun array) in shallow and deep water areas respectively. At the deep water station (Fig. 3), the large source provided sufficient energy to penetrate the entire sedimentary section and refractions were observed from sub-basement (crustal) layers down to and including the mantle.

Methods of Analysis

The analysis of wide-angle reflection and refraction seismic data is normally based on standard ray tracing theory, which can be found in any text on applied geophysics (Dobrin, 1960, ch 5, 6; Telford et al., 1976, ch 3, 4; Officer, 1958, ch 2). LePichon et al. (1968) have applied the generalized theory to the specific case of wide angle reflection data from sonobuoys. Computer programs for analyzing both the sonobuoy wide angle reflection data



Example of shallow water (150 meters) sonobuoy record. (Recording 0 - 8 seconds.) Several minutes of vertical incidence seismic were recorded just prior to the launch of the sonobuoy. Observe that all refractors come in a as first arrivals. (Compare with Figure 5.)



(LePichon's method) and the sonobuoy refraction data (general method) are given by Knott and Hoskins (1975). We will summarize briefly the basis for these methods.

The ray paths and the time-distance plots for seismic waves in a simple two layer model (water overlying sediment) are shown in Figure 4. Three basic travel paths are involved; the direct, the variable angle (wide angle) reflections, and the refractions. The direct arrival is the energy that travels through the water from the sound source directly to the hydrophone. On the time-distance plot the direct arrival is a straight line; the slope of this line is the reciprocal of the horizontal velocity of sound through the water near the sea surface. The direct arrival can, therefore, be used to determine the distance from the ship to the sonobuoy (the product of the direct arrival time, T_d , and the horizontal velocity, v_H). In practice, it is assumed that the horizontal water velocity, rather than the separation distance, is known, primarily because navigational uncertainties and sonobuoy drift introduce unknown errors into the separation distance. Once the horizontal velocity is determined, through Matthew's Tables (Mathew, 1939; also in Handbook of Oceanographic Tables, 1966), or similar tables (National Ocean Data Center, 1968), or through surface temperature and salinity measurements (including expendable bathythermographs: XBT's), then careful recording of the direct arrival times obviates the requirements that both ship navigation (course and speed) and buoy position remain constant during the sonobuoy station. Small deviations in these parameters (ship course, speed, and buoy position) will cause small changes in the slope of the direct arrival trace, but these changes are irrelevant if the proper data reduction method is used. See Appendix B for a discussion of sound velocity in water.

Seismic energy travels through the earth with a velocity which is

dependent not only upon the material through which it is travelling, but also upon the manner in which it is propagating (e.g. compressional waves, shear waves, etc.). Sonobuoy data can be used to determine: rms (for root mean square) velocity from wide angle reflections and head wave (also called refraction) velocity from refractions.

The rms velocity is an "average" velocity for all the material (water and rock) lying between the sea surface and the reflecting interface. This is the same velocity that is determined through analysis of multichannel data, but sonobuoy reflection data is collected over a considerably greater distance (typically 6 km for a sonobuoy station in 300 meters of water). The theory and geometry for determining rms velocity from wide angle reflections is presented in Appendix D. Briefly, the curve on a time-distance plot(as shown in Fig. 4) that results from a flat reflecting plane (boundary) is a hyperbola:

$$T^{2} = T_{o}^{2} + \frac{1}{V_{rms}^{2}} X^{2}$$
 (1)

This equation is linear in X^2 and T^2 . Therefore, if we measure the values of X and T along an experimental reflection hyperbola and plot X^2 versus T^2 , the X^2 , T^2 points will lie along a straight line. The slope of this line, $(1/v_{rms}^2)$ is the reciprocal of the square of the rms velocity (v_{rms}) , while the intercept of the line with the T^2 axis is the square of the minimum reflection time (T_0) to the horizon. This plot is referred to as an $X^2 - T^2$ plot, and this type of analysis referred to as an $X^2 - T^2$ velocity determination. The rms velocities from two reflecting horizons can be used to determine the interval velocity (V_{int}) between those two horizons. The interval velocity, which is the seismic wave velocity over a specific depth interval, can be computed in either of two ways: the first employs an approximate method





Figure 4 Schematic diagram illustrating the relationship between the seismic travel paths as seen on the graphic record of a sonobuoy. Note that in this representation, we've shown the source as stationary and the sonobuoy position as variable. In practice just the reverse is true, but the two cases are completely symmetric.


described by Dix (1955) while the second uses a more sophisticated ray tracing technique described by Le Pichon, et al. (1968). The latter method is described in detail in Appendix D, Part III, and is the basis for the computer program SLOWI described later in this report (Section IV).

The refraction velocity is the speed at which seismic energy propagates along an acoustic interface. With homogeneous layers, as in the model of Figure 4, the refraction velocity is equivalent to the interval velocity in the layer beneath the interface. In reality, however, an interval velocity usually encompasses several discrete rock layers, and the refraction velocity represents the "fastest" of those layers near the top of the interval. Therefore, the refraction velocity tends to be higher than the associated interval velocity. Furthermore, as pointed out by Knott & Hoskins (1975, p. 6) "sediments frequently display velocity anisotropy, in which the velocity of propagation along the bedding is significantly higher than the velocity transverse to the bedding in the same material". Refractions only occur when the interval velocity in the underlying layer is greater than the overlying layer, and are not detected until the distance between the ship and the sonobuoy exceeds the "critical distance", as determined by Snell's Law. On the time-distance plot (Figure 4), refractions appear as straight lines; the slope of the refraction $(1/v_{ref})$ is the reciprocal of the refraction velocity. When an acoustic interface produces both a reflection and a refraction, the refraction appears as a tangent to the corresponding reflection on the timedistance plot, and "peels off" from the reflector as a straight line. The point of tangency is the critical point. Since the critical distance is the point beyond which total internal reflection occurs (i.e. beyond which there is no transmitted energy), the amplitude of the reflected arrival increases at this point. This amplitude increase often helps identify the point at which

the refraction arrivals should start to appear.

Figures 5 and 6 are synthetic plots of sonobuoy records in shallow and deep water respectively illustrating these travel time curves and their relationship.






III. FIELD OPERATIONS

General Information

Knott & Hoskins (1975) note that there are three possible modes for recording sonobuoys. The first is to have a free running source and a shot actuated recorder; the second is to use a continuously running recorder (controlled by a time base), which keys the source; and the third is to use triggered recorders and triggered sources controlled by an independent timer. The first system is used primarily by Lamont-Doherty (Knott & Hoskins, 1975, p. 7), while Woods Hole relies exclusively on the second method. Because much of our sonobuoy work on the S.P. LEE is concommitant with multichannel operations, we use the third method almost exclusively. (In a few instances during high resolution seismic surveys, the second method has been used.) In standard operation, the navigation system generates a trigger pulse at 50 meter intervals that simultaneously fires the air gun array and starts the graphic recorders for the sonobuoy. At normal operating speeds of 5.5 knots, the airguns fire every 17 seconds. The airgun array used for our sonobuoy and multichannel operations is a five gun tuned array with a total volume of 1326 cu. in., which is fired at a pressure of approximately 1800 psi. The individual airgun sizes are 94, 148, 195, 309, and 580 cu in.

During field recording, the sonobuoy data is displayed in real time on one or more graphic recorders and is simultaneously recorded on analog magnetic tape. Figure 7 shows a schematic diagram of the current sonobuoy system aboard the S.P. LEE and indicates the signal path for the seismic information during recording of a sonobuoy.



Equipment Description

Sonobuovs

The sonobuoys used aboard the S.P. LEE are of two basic types: those purchased from private industry and those procurred from the U.S. Navy (see Appendix A for criteria in deciding which type of sonobuoy to use). The commercial seismic sonobuoys are available from Fairfield Industries, Inc., Fairfield Select Division, of Houston, Texas, and from Refraction Technology, Inc. of Irving, Texas. Sonobuoys produced by the two companies are very similar electronically, but differ in the design of the hydrophone suspension system. Both companies provide the same options with buoys.

1. Radio frequency band

Each sonobuoy transmits on a specific channel, in either the low frequency range (74-76 MHz) or the high frequency range (170 MHz). The lower frequency range generally allows for longer broadcasting distances and requires a larger antenna.

2. Hydrophone suspension

The sonobuoys are generally equipped with variable length hydrophone suspensions ranging from 30 to 240 foot depths. The longer suspensions (i.e. deeper hydrophones) generally give better isolation from surface noise. However, the thermal density (velocity) stratification in the upper part of the water column can cause the direct arrival to be totally reflected away from a very deep hydrophone (refer to App. B).

3. Delayed hydrophone release

When sonobuoys are deployed during multichannel operations, a delay mechanism for the sonobuoy hydrophone release is used to avoid fouling the sonobuoy on the multichannel streamer. A 20 minute delayed hydrophone release timer is provided with each sonobuoy to allow sufficient time for the sonobuoy

to clear the end of the multichannel streamer. The timer may be disabled for sonobuoy deployment during single channel operations.


4. Amplifier gains

Commercial sonobuoys are available with either fixed gain or automatic gain control amplifiers. Most buoys now in use on the S.P. LEE are fixed gain type, which allow greater control of recording gains on both the graphic and tape recorders.

The Navy sonobuoys used on the LEE have been either SSQ-41A or SSQ-41B. The SSQ-41A sonobuoys have a higher frequency response and shorter antennas than the commercial seismic buoys. Consequently, the seismic range of the 41A buoys is less than the commercial buoys and low frequency seismic information from deep interfaces is lost. The SSQ-41B sonobuoy is basically a 41A that has a lower frequency response, roughly equivalent to the commercial buoy. Because both types of the Navy sonobuoys have a high frequency bandpass filter, they generally provide a strong direct arrival signal, as well as excellent resolution at shallow depths. The poor low frequency response of the SSQ-41A sonobuoys make them less suitable for studying deeper reflections and refractions. All Navy sonobuoys are equipped with standard 300 foot hydrophone lower and have no delayed hydrophone release timer. However, since the hydrophone assembly is readily accessible, if necessary it can be tied off at a shallower depth, or a "lifesaver" delayed hydrophone release can be installed. Great care should be exercised when using the Navy sonobuoys concurrently with multichannel operation, because of the risk of damaging the multichannel streamer with the sonobuoy hydrophone cable.

Receivers

The signal transmitted from the sonobuoy is received on ship by one of two Yagi antennas mounted on the aft mast; separate antennas are required for



Schematic diagram of signal splitting and filtering circuitry of the Aquatronix receiver. Large arrows indicate input, small arrows output. Compare with Figure 7 for relationship with recording apparatus.

low and high frequency sonobuoys. The high frequency signal passes directly to the receiver, while the low frequency signal is preamplified before entering the receiver.

Two Aquatronix (now Fairfield Select, Inc.) mainframe receivers, each containing two separate crystal controlled receiving modules can be used to receive either commercial or Navy sonobuoys. Since sonobuoys with different transmitting frequencies can be received simultaneously by the two modules in both receivers, four separate sonobuoys can be received simultaneously with this equipment.

Within the receiver, the unprocessed sonobuoy signal is passed through a series of filters and amplifiers. The radio signal is first passed through a 5 Hz lo-cut filter and gain amplified. The signal is then split into two components: the seismic signal, 5-62 Hz, and the waterbreak signal, 800-1200 Hz. The seismic component is passed through a variable hi-cut filter, while the waterbreak component is amplified ± 20 db with respect to the incoming signal. The two components are then recombined and output to the recorders, and are also output separately as amplified output and waterbreak output. Figure 8 shows the receiver circuit schematically.

A third receiver, made by Nems-Clarke, Inc., which can be selectively tuned to any sonobuoy transmitting frequency, is used primarily as a backup unit. The demultiplexed signal from the Nems-Clarke receiver is fed into the filter-amplifier circuitry of the Aquatronix receiver through the auxiliary RF input to take advantage of the bandpass filtering and mixing capabilities of the Aquatronix receiver (see Figure 8).

Analog Tape Recorder

All sonobuoy data is recorded both on graphic recorders and analog magnetic tape. The tape recorder used is the Hewlett-Packard 3968A, a

quarter-inch eight track instrumentation tape recorder capable of recording either FM or Direct (AM) modes. In single buoy operations, the channels are generally assigned in the following manner:

- Channel 1 (FM): vertical incidence single channel seismic, from either single channel system and Teledyne amplifier, or a monitor channel from the multisystem
- Channel 2 (FM): unfiltered sonobuoy seismic; from the seismic monitor of the sonobuoy receiver (see Fig. 8)
- Channel 3 (FM): filtered sonobuoy seismic; from the filtered output of the sonobuoy receiver (see Fig. 8)
- Channel 4 (FM): amplified sonobuoy seismic; from the amplifier output of the sonobuoy receiver (see Fig. 8)
- Channel 5 (FM): tape recorder precision drive frequency; an internally derived crystal frequency for playback control (see page 22)
- Channel 6 (FM): airgun trigger; trigger pulse from the multichannel trigger box, which also triggers the graphic recorders
- Channel 7 (Direct): waterbreak output; filtered (800-1200 Hz) output from the sonobuoy receiver (see Fig. 8)
- Channel 8 (Direct): voice channel and WWV time record

The magnetic tape used for sonobuoy recording is 1/4 inch, 1/2 mil thick instrumentation magnetic tape. The tape is intermediate band (DC-20 kHz), which is completely satisfactory for sonobuoy recording and a fraction of the cost of wide band instrumentation tape. The tape recorder requires 7 inch tape reels, which will accommodate 3500 feet of 1/2 mil tape.

The 3968A is a six speed recorder, with a range from 15/32 to 15

inches per second. We generally record all sonobuoys at 3 3/4 ips.

This, is the lowest tape speed which will allow seismic information (5-62 Hz) as well as the waterbreak signal (800-1200 Hz) to be recorded on a single FM tape channel. At this speed, a 3500 foot tape (7 inch reel) will last for about 3 hours, usually long enough for one sonobuoy station, especially in shallow water. However, longer range sonobuoys may require two tapes to record the distant refractors. The problem of switching tapes can be avoided by reducing tape speed to 1-7/8 ips. In order to preserve the direct arrival (waterbreak) at the lower tape speed (FM bandpass at 1-7/8 ips is DC-625 Hz), the waterbreak (Channel 7) must be mixed with the sonobuoy seismic (Channel 3) when the tape is replayed.

To insure accurate replay of recorded sonobuoys, it is necessary to devote one channel (FM or Direct) to record the precision drive frequency generated by the tape recorder. The precision drive frequency is used to phase lock the capstan motor during replay, thereby compensating for small deviations in tape speed that occurred during recording. A channel near the center of the tape (track 4 or 5) should be used for this purpose, and if an FM channel is used, the board must be modified slightly. Instructions for recording the precision drive frequency are found on pages 64-67 of the Operating and Service Manual.

Since the 3968A recorder can record and playback simultaneously, the data going onto tape can be monitored in real time if the seismic channel (Channel 4) and the trigger pulse channel (Channel 6) are input to a graphic recorder. The disadvantages of this procedure are that the recorded signal may be slightly inferior to the original signal, and that a malfunction in the tape recorder will result in complete loss of information. We normally make two records, one using output directly

from the receiver and the other using output from the tape recorder.

The tape recorder should be maintenanced periodically, particularly when undergoing heavy use. Routine maintenance is covered on pages 50-55 of the Operating and Service Manual. The most critical maintenance function is careful cleaning of the tape heads and drive capstan after every sonobuoy station. Oxide buildup on the record heads can seriously degrade the record quality, while oxide buildup on the capstan drive will cause tape slippage. The problem of capstan slippage may become so serious that the tape will stop completely while the capstan continues to spin. Another advisable procedure is to periodically degauss the tape heads.

Graphic Recorders and Recording Techniques

The filtered output (5-62 + 800-1200 Hz) from the sonobuoy receivers is displayed in real time on one or more Raytheon Universal Graphic Recorders (UGR's). These dry paper, fascimile recorders are capable of operating in either a continuous mode or a start/stop mode, at sweep speeds ranging from 1/4 to 8 seconds. Normally, sonobuoys are recorded in the start/stop mode with sweep speed of either 6 or 8 seconds. The recorder sweep is initiated by a trigger pulse from the navigation system, which also triggers the airguns. Because of mechanical delays in firing the airguns, there is usually a small time delay between the air gun fire and the sweep trigger.

When recording sonobuoys in deep water areas, a sweep start delay of between 0.1 and 9.9 seconds is used to eliminate recording the water path travel time. This delay option is only possible in the start/stop mode, and makes it possible to record continuously a "full page" of seismic information. Whenever the seismic data approaches the bottom of

the record, an additional delay is added and the seismic data is shifted up the record. This procedure allows us to obtain a complete and continuous record of both the seismic and direct traces which is free from having an overprinted multiple trace. Such a record is not possible in a "continuous" record mode.

There are two limitations to the start/stop recording technique. The first is that the total time (delay plus sweep) cannot exceed the fire rate, otherwise the recorder will miss every other shot and the vertical exaggeration of the record will change. For example, with an eight second sweep and a 17 second fire rate, the maximum allowable delay (for removing the water travel time) would be 8.9 seconds (.1 second must be allowed for the recorder to stop and prepare for the next trigger. The second limitation is encountered on very long sonobuoys, when the direct trace goes off the bottom of the record because an additional delay would either exceed the fire rate and cause missed shots or would shift seismic information up and off the top of the record.

The resolution and vertical exaggeration of the graphic sonobuoy record depend on three parameters: recorder sweep speed, recorder paper feed and the seismic shot interval. These factors must be optimized to obtain a record that has low vertical exaggeration, provides good resolution of reflectors, and contains all the seismic data of interest. Often, two records with different parameters must be made to satisfy this objective.

The resolution of the sonobuoy record depends on the sweep speed of the graphic recorder. Knott & Hoskins maintain (p. 18) that a sweep speed of at least 7 cm (2.7 in.) per second is necessary to obtain measurements to \pm 3 m sec required for reliable analysis. With our

digitizing system, a slightly smaller scale appears to be sufficient. The paper for the UGR recorder is 48 cm. (19 in.) wide, so a six second sweep is 8 cm/sec, while an eight second sweep is 6 cm/sec. With normal sonobuoy operations, either one of these two sweep speeds will provide adequate resolution. The eight second sweep speed is preferable in deep crustal velocity studies because of the longer recording period that is possible.

The vertical exaggeration of the sonobuoy record depends on both the recorder paper feed and the seismic shot interval. A lower vertical exaggeration makes it easier to correlate events from one sweep of the recorder to the next. During multichannel operation, the seismic shot interval is fixed by the multichannel system, usually at 50 meters. With the single channel system, however, almost any shot interval can be used subject only to the recharge capability of the air gun compressors. the start/stop mode, the optimal shot interval is the shortest time between shots that will give a complete record of the seismic section at large distances from the buoy. This interval depends on water depth, sediment thickness, anticipated sub-crustal seismic penetration, etc. the continuous record mode, the optimal shot interval is the shortest possible time between shots (see Knott & Hoskins, 1975, pp. 16-24). The paper feed on the UGR recorders, which ranges from 40 to 120 lines per inch, is coupled to the pen sweep, so that whenever the pen sweeps, the paper feeds. The maximum feed rate, 40 lines per inch, is advisable when recording sonobuoys because it gives the lowest vertical exaggeration and it will facilitate the counting of individual seismic traces during the data reduction.

Vertical exaggeration is an important consideration when dealing

with wide angle reflection records. Refractions are easily correlated at even high vertical exaggeration, but wide angle reflections become difficult to distinguish and pick when the curvature of the reflectors becomes too steep. Vertical exaggeration can be expressed as the angle that the direct arrival makes with the edge of the paper ('K', Fig. 6). For reasons relevant to their own processing technique, Knott & Hoskins (1975, p. 18) suggest that this angle be less than 45°. We have found that an angle of 18° is quite satisfactory. The 18° angle is obtained on our records using an eight second sweep speed, a feed rate of 40 lines per inch, and a 50 meter fire interval. An angle of as little as 13° is also satisfactory, but anything less make correlation of successive sweep difficult. To determine what this angle will be for different recording parameters, use the equation

$$\alpha = \arctan\left[\frac{5W}{N*r*55*0.006477}\right]$$
(2)

where

= angle of direct trace

sw = sweep speed

n = number of lines per inch

r = fire rate (in seconds)

ss = ship speed (in knots)

Sonbuoy Preparation and Launch

A number of steps must be completed in preparation for the launch of a sonobuoy. These steps are summarized in the accompanying checklist, Table 1, and it is advisable to follow such a checklist when preparing to deploy a sonobuoy.

TABLE 1

Checklist for sonobuoy preparation and launch

- 1. Prelaunch check of sonobuoy
 - a. If possible, start transmitting on deck to ensure that sonobuoy batteries are working and that the selected crystal frequency is correct.
 - b. Check the hydrophone lower depth and delayed release timer
- 2. Notify radio officer and bridge of intent to deploy buoy
- 3. Fill out log forms
- 4. Prepare analog tape recording system
 - a. Voice introduction, including date, time, identification, etc.
 - b. Set footage counter
 - c. Check input levels on each channel
- 5. Start recording vertical incidence seismic on tape and graphic recorders
- 6. Prelaunch lab check
 - a. Ensure that the correct crystal is being used in the receiver and that all recorder inputs are coming from the receiver module used
 - b. Ensure that the correct initial settings (gain, hicut filter, waterbreak gain) have been set on the receiver
 - c. Ensure that antenna preamp gain has been turned down (for low frequency sonobuoys)
 - d. Check signal paths (seismic signal and triggers) to both graphic and analog tape recorders
- 7. Proceed with countdown to launch
 - a. Radio operator on deck counts down airgun shots, and reports when the sonobuoy is in the water and adjacent to the airguns
 - b. Lab procedure:
 - 1. Record start of countdown on tape
 - 2. Set correct feed rates on recorders
 - 3. Set proper display mode on recorders
 - Switch recorder input from vertical incidence seismic to sonobuoy seismic
 - 5. Mark the first trace (when sonobuoy at airguns) on the recorders
 - 6. Record time and footage reading in log and on tape recorder
 - 7. Retune the sonobuoy on the receiver
 - 8. Adjust the graphic recorders for optimum display

(1) Prelaunch check of the sonobuoy

In preparing commercial sonobuoys for launching, it is advisable to attach the antenna securely to the sonobouy case with fiber tape and seal the base with polyvinyl chloride (PVC) glue to avoid antenna breakage or water leakage. The hydrophone release should be set to the desired depth (refer to App. B for criteria) and the timer activated or deactivated as required. If possible, the sonobuoy should be activated on the deck, to allow checking the sonobuoy batteries, receiver crystal, etc. If anything appears to be wrong with the sonobuoy, it is advisable to stop the entire operation until the problem is corrected or the sonobuoy is replaced.

(2) Notify radio officer and bridge

Both the radio officer and the bridge should be notified at least 10 minutes prior to the deployment of a sonobuoy. Some types of radio transmission will interfere drastically with the sonobuoy signal, and the notification will allow the radio officer time either to complete the transmission or to postpone it until after the sonobuoy station. Since a sonobuoy station may last for several hours, it is courteous to give the radio officer up to several hours warning of a sonobuoy station so that the transmitting schedule can be altered accordingly. The bridge should be notified before any activity on the fantail, especially deployment of equipment. In addition, the bridge should be notified prior to a station so that speed and course changes will be avoided if at all possible. In this regard, it is also helpful to notify the navigation watch so that course or speed changes will not be requested from the lab.

(3) Fill out log forms

Log forms, as shown in Figure 9, should be prepared for each sonobuoy prior to launch. These forms contain all information essential for later

Figure 9 Example of sonobuoy station log. Sonobuoy recorded on two recorders (0-6 and 4-12 seconds) with underway multichannel operations.

SONOBUOY STATION LOG

I SHIP RIV S.P. LEE	DAFE
CHIEF SCI. A. COOPCE	LOCATOR L8 77 BS
GENERAL AREA N Alcution Basin	50110 111
APPROXIMATE LATITUDE 58°5' / 58" 25'	ARCHIVE SONO 46 (Sta. No.)
LONGITUDE 176° 51' / 177° 32' 6	LINE 7 COURSE 054 NE
WATER DEPTH 5.052 sec VH 1.485 km/sec	SPEED 5.0 KTS
SURFACE WATER TEMP 10 °C METHOD Velocimetes	
WEATHER: CLEAR DRIZZLE HEAVY RAIN	WIND: VELOCITY 12 kts DIRECTION ESE
	(from)
II. ACOUSTIC SYSTEMS	
DEPTH BELOW SEA SURFACE	FIRE SEQUENCE:
A. 3.5/12 kHz TRANSDUCERft	DISTANCE BASIS TIME BASIS
B. SEISMIC SOURCE: AIRGUNS 40 ft	DISTANCE <u>50</u> TIMEsec
ARCERSft	FIRE SEQUENCE DIAGRAM
C. SINGLE CHANNEL STREAMERft	air guns only
POWER: BATHYMETRY 3.5 kHz 12 kHz	TRIGGER TIMES:
AIRGUNS 1326 cu. in.	SEISMIC(t ₀) - GRAPHIC RECORDER(t ₁)msec
ARCER kJ	SEISMIC(t _o) - MAG TAPE RECORDER(t ₂)msec
III. RECORDERS	
1. GRAPHIC RECORDER: RECORDER NO. DEE	2. MAGNETIC TAPE RECORDER
MODE: Start/Stop Continuous	TIPE H.P 3968A - BTRK - 1/4 in
SCALE:	TAPE SPEED 33/4 in/sec
SWEEP 6 8 Sec	TAPE/TACE SERVO On Off
TRIGGER: Edge 1/4 . 1/2 3/4	FOOTAGE COUNTER: 1404 start run
PAPER FEED 40 140 lines/inch	3048 end run
INITIAL RECORDER DELAY OF 4 sec	
(thumbwheel)	
	CHANNEL FM/DIR INFORMATION
SEISHIC ROLL NUMBER(S) UNIB#3 F BA35 # 2 IV. SONOBUOY GEAR	1 FM DIR vertical incidence
SEISHIC ROLL NUMBER(S) UNIB#3 F BA35 # 2	
SEISHIC ROLL NUMBER(S) UNIB#3 F BA35 # 2 IV. SONOBUOY GEAR	1 PM DIR vertical incidence scismic. Teledyne am: 2 PM DIR Right unfiltred sonobooy scismic
SEISHIC ROLL NUMBER(S) UNIB#3 F BA35 # 2 IV. SONOBUOY GEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971	1 PM DIR vertical incidence scismic. Teledyne amo 2 PM DIR Right unfilted sonobooy scismic 3 PM DIR Left filtered sonobooy scismic
SEISHIC ROLL NUMBER(S) UNIB#3 BA35#2 IV. SONOBUOY GEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971 CHANNEL 20 L AMPS: Fixed gain AGC	1 M DIR vertical incidence scismic. Teledyne ami 2 M DIR Right unfilted sonobuoy scismic 3 M DIR Left filtered
SEISMIC ROLL NUMBER(S) UNIB#3 (BA35#2 IV. SONOBUOY GEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971 CHANNEL 20 L AMPS: Fixed gain AGC PHONE DEPTH 120 ft DELAY RELEASE 20 Mich	1 PM DIR vertical incidence scismic. Teledyne ami 2 PM DIR Right unfiltered somobuoy scismic 3 PM DIR Left filtered somobuoy scismic 4 PM DIR Right filtered
SEISMIC ROLL NUMBER(S) UNIB#3 F BA35#2 IV. SONOBUOY CEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971 CHANNEL 20 L AMPS: Fixed gald AGC PHONE DEPTH 120 ft DELAY RELEASE 20 FC FREQUENCY BAND 76 MHz 171 MHz 74 MHz	1 PM DIR vertical incidence scismic. Teledyne am? 2 PM DIR Right unfiltered somobooy scismic 4 PM DIR Right filtered somobooy scismic right filtered somobooy scismic
SEISMIC ROLL NUMBER(S) UNIB#3 F BA35#2 IV. SONOBUOY CEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971 CHANNEL 20 L AMPS: Fixed gain ACC PHONE DEPTH 120 ft DELAY RELEASE 20 FREQUENCY BAND 76 MHz 171 MHz 74 MHz 2. RECEIVER (nitial)	1 PM DIR vertical incidence scismic. Teledyne amo 2 PM DIR Right unfiltered sonobuoy scismic 4 PM DIR Left filtered sonobuoy scismic Aight filtered sonobuoy scismic sonobuoy scismic frequency frequency chennel
SEISMIC ROLL NUMBER(S) UNIB#3 BA35#2 IV. SONOBUOY GEAR 1. SONOBUOY TYPE SB.76 SER. NO. 11971 CHANNEL 20 L AMPS: Fixed galar AGC PHONE DEPTH 120 ft DELAY RELEASE 20 MC FREQUENCY BAND 76 MHz 171 MHz 74 MHz 2. RECEIVER (n. f. e.) FRONT FILTERS BI OUT LOW 5	1 PM DIR vertical incidence scismic. Teledyne amo 2 PM DIR Right unfiltered sonobuoy scismic 4 PM DIR Left filtered sonobuoy scismic A CH DIR Right filtered sonobuoy scismic sonobuoy scismic frequency frequency chennel

STATION # 46

U.S.G.S. STATION OPERATIONS LOG

-	Ιυ																						
52	.22	٤	DEPTH		T															=]
58°	, (1)	STATION DATA ONLY		4 NO	3,6,9,8	1	1 1 1			1 1 1		1 1 1		-	-	1	1	-	-	67.70	^ر ر		
	w	STATIC	MECOV	Y N	* 197															2	Š	3	
LAT (ST/ED) 5'8'S'	LONG (ST/ED) 176 51		OPERATIONS, COMMENIS, OR DATA MEASUMEMENTS		* 46	see record (4-12 see)	(0.0°) picos	عند عرب	1.2 - 7.2 scc		3.0-9.0 sec		sed to 30 db		46	of on tape	pe 46A		756		radio interference	preams toolo	
	BS		AMENTS. 01		tape	eig ht	\$ ix 9	الم إحا	Scale	drop	scale	-	inerce	2	tope	4 100+	+-		fere		, 0,		1501 85 53
1	AREA CODE (COL. 79-80)		OPERATIONS, CON		Start	Start	< +c	sondonos	Change	Phones	C herale	Routine	Gain	Routine	End +	4 shots	Start	Radio	(inter		•	antenna	e e
	77 -			COUNTY COUNTY	0000	• • •		HOHI	5'2'9'1	1,7,6,1		8022		2920	3048		0000			41.84	Early	400	CRITICE I OCATOR CAMBIE ATTEMET #
	İ	X ONLY	CATION	Cont STAT END											×					36			. Or ATC
	L8	X IN ONE BOX ONLY	PLINGLO	STA	_X	×	X	X									X			36 37			ا المال
RING SEA	CRUISE LOCATOR	*	ATTEMPT NO SAM	S LET /NO COM	4,6	1,4,6	3,4,6	1, 46	5		5, 1, 1,	-		-	י אלר		V'9'h' '			28-33	3		+
AREA BERING	CRUS SO	· EQUIP.	30 00	4 LETTERS	SONO	SONO E	SONO S	SOMOS	\ \frac{\sqrt{\sqrt{\chi}}{\chi}}{\chi}	\	•, •			^	SONO	•	SONO	:	:	26-28	ر <i>د</i>		1000 TO 000 TO 00
		SPEC	30 00	3 LET.	MAG	PAP	PAP	280							MAG		MAG			21.23	E I C	6 ++ 2	;
LEE	COOPER	*	STA NO OR	SHOT POINT	-	1.1.	1	1 1	4	1 1	-	-	- - -	1	-	-	-	1	-	16.16	VEA! HEK,	くつこと	
S.P. L	ARLOW/	SITION		LINE NO	7	7	7, , ,	۲, , ,	<u></u>	7, 1	4	7	7, ,	7	7, , ,	7	7, , ,	7, 1,	7	12:15	KALION,	^	
SHIP/LEG	CHIEF SCI. MARLOW/COOPER	TIME & POSITION	GMT TIME	M. MIN	x 2,201,800	0'0'8'	1,800	9061	0,2,0,	8261	19,35	2001	7,20,2	21,0,1	2111	2,1,1,2	2,1,1,3	7,1,2,4	8'1'1'8	95	KEMAKAS: EQUIP., OPERALION, WEATHER, ETC.	ア 。 。 。	
Ŧ,	₹		JULIAN	DAY	20	~	~;	<u></u> ;	~;	~~ <u>;</u>	ير	~	~		~		~-	;		- 2	AKAS.	T	
		ראפ	1 H3		×	×	X	×		-	-										X 2] }
										२1													

STATION # 46

U.S.G.S. STATION OPERATIONS LOG

		STATION DATA ONLY	DEPTH 4 NO	*														14 67.70 71			
LAT (ST/ED)	S LONG (ST/ED)	OPERATIONS, COMMENTS. OR DATA MEASUREMENTS		a down to 30 Hz	Buoy disappearing	ξ.ξ.		ignal gone													131
ļ	AREA CODE BS (COL. 79-80)	OPERATIONS, COMMEN		High filter down	Buoy di	70 pe 046		Radis s													MET IER COURSINS
	7.7 RY		FOOTBLE COUNTY	40.7	2,0,70	X 2,0,8			•									41.64	times		TH CAMPIE ATTE
	L8 0	X'IN ONE BOX ONLY	PISCHETE VARIABLE F.G.		X	X	X	×										36 37 36	to		CBINCE INCATE
RING SEA	CRUISE LOCATOR(COL. 73.78)	SAMPLE ** XI	1 1		2,4,1	A,6,4		1										29-33	noisy		+ + CADMANT CAD CAMBLE LABEL IC COLLICE LACEATOR CAMPLE ATTEMPT #
AREA BERING	CRUIS	EQUIP	4 LETTERS	* SONO	SONDE	HAG SONO	somes											26.28	, %	i	+ COBLANT COB
SHIP/LEG S.P. LEE	~	SPEC	3167		PAP	HAG	PAP	085										21.23	ETC. Buoy		•
	/COOP EF	*	STA NO OR SHOT POINT	-	1	1	-	-			- - - - -	1	 	4		4 .	- ·	16.19	VENTHER,	•	
	ARLOW,	SITION	CINE NO	7, , ,	L	<u> </u>	-	7.					1	4				12.15	ERATION		
	CHIEF SCI. MARLOW/COOPER	TIME & POSITION	GMT TIME HR -MIN	2,2,0,2,1,4,9	0,0,5,5	2,3,1,0	7,2,27	23.30		- - - - -	 	-	4	d :	-			9.9	REMARKS: EQUIP., OPERATION, WEATHER, ETC. Con Con		
ý	Ċ	24.14	JULIAN PUNCH DAY	0'2'2	\X	\\ \\	~ <u>:</u>	>: X		32	‡ _ _	1	-	<u> </u>				<u>-</u>	REMARK		

reduction and interpretation of the sonobuoy. In addition, the logs serve the very important function of verifying claims in the event of a sonobuoy failure. The entries on the log forms are all straightforward. Two entries worth mentioning are the water depth, which should be noted in two way time from the bathymetry record, and the horizontal velocity of sound in water, $v_{\rm H}$, which appears on the satellite navigation terminal output.

(4) Prepare analog tape recording system

First, tape heads and drive capston should be cleaned, if necessary (see p. 23). Then, a new, properly labeled tape should be mounted on the recorder to record vertical incidence seismic prior to the launch of a sonobuoy. It is advisable to record pertinent information on the voice channel, i.e. information such as cruise identification, sonobuoy station number, time, tape recorder channel designations and area. The footage counter on the recorder should also be set to zero and noted on the tape. Finally, the tape speed should be checked, usually 3 3/4 ips.

When vertical incidence seismic recording is underway, the input levels for each tape recorder channel should be measured with an oscilloscope and reset if necessary. Most important are the seismic channels and the trigger channel. The seismic channels should be adjusted for maximum gain without clipping the signal, while the trigger pulse should be adjusted so that at least a 2 volt signal is recorded. The Raytheon recorders require a two volt trigger. Having set the input gains, you should then look at the output signals (the recorder can record and playback simultaneously). This will insure that the signal being recorded will be useable for playback at a later date.

(5) Preparation of Graphic recorders

In most operations, when not recording sonobuoys, the graphic recorders are being utilized for display of other seismic data. Therefore, prior to a sonobuoy station, the seismic data being recorded should be interrupted, the paper advanced several inches, and the start of the sonobuoy station clearly marked, along with time, scale, and filters or source, if necessary. The recorder should then be set up to record vertical incidence seismic, preferrably using the same initial delay and sweep rate that will be used to record the sonobuoy.

The input for the UGR will come either directly from the sonobuoy receiver, or will come from the output of the tape recorder. Make certain that the trigger pulse to initiate the recorder sweep is consistent with the signal, i.e. if the signal is coming from the tape recorder, then the trigger input to the UGR should also be the output from the trigger channel of the tape recorder. Failure to match the signal and trigger pulse will create a recording offset because of the finite distance between the write and read heads of the tape recorder.

In shallow water, one graphic record is sufficient to record all data. If one recorder is being used to display the tape recorder output, it is advisable to make two graphic records, to protect against complete loss of data in the event of tape recorder malfunction. In deep water areas, it is usually necessary to record the sonobuoy on two separate graphic recorders. This is due to the long water path. In 5 seconds of water, even an 8 second record will provide only 3 seconds sub-seafloor. This problem can be circumvented by introducing a deep water delay, and recording from 4-12 seconds. Therefore, two recorders are necessary: one to record the direct arrival and seafloor (0-8 sec or 0-6 sec) and a second to record the complete sedimentary section.

Generally, we make a 0-6 second record and a 4-12 second record in deep water areas. Both records are used in subsequent digitizing of the wide angle reflections, so it is essential that both are correctly marked, particularly that the zero trace (the closest approach of the sonobuoy to the airguns) is marked on both records. It is also helpful to periodically make simultaneous marks on both records to insure correct correlation of seismic traces during the data reduction.

(6) Lab prelaunch and launch

Proper preparation of all equipment prior to the actual launch of a sonobuoy is the key to success! While the sonobuoy is on the deck the receiver in the lab should be tuned to the transmitting frequency of the sonobuoy to verify that the buoy is transmitting properly at the crystal frequency or channel marked on the sonobuoy (the channel markings are occasionally incorrect). The controls on the front panel of the receiver (gain and filter settings) should be initialized (see Log form, Figure 9, for example) and the antenna preamp (if using a low frequency sonobuoy) should be adjusted to a low gain setting. It is advisable also to check all signal paths, to ensure that the correct receiver and module are being recorded, and that the trigger pulse is correct. All input signals going onto tape should be checked with an oscilloscope. This ensures that the recording levels are in the proper range (maximum gain without clipping of the signal) and that the proper signals are actually being recorded.

If possible, launching the sonobuoy should be a three person operation; two people on the fantail and one person in the lab. Radio contact is desirable, but careful planning and coordination may suffice. The two people on the fantail should wear survival gear, and the person who actually launches the sonobuoy should be secured by a safety harness. The second person on the

fantail coordinates the launch by radio. Once everyone in the lab and on the fantail are ready, a countdown of airgun shots can commence. This countdown enables the person in the lab to prepare for and determine the precise time that the sonobuoy will be in the water and adjacent to the airguns.

During the countdown period. several actions must be completed by the lab person. A countdown of the shots on the voice channel of the tape during this time will prove invaluable upon later replay of the tape. Two airgun shots before the launch, the feed rate on the recorders should be increased (to 40 lines per inch) and the input signal to the graphic recorders switched to display the sonobuoy seismic rather than the vertical incidence seismic. When the sonobuoy is in the water and at the airguns, event marks should be placed on the graphic recorders and simultaneously a voice annotation made on the voice channel of the tape recorder that "the sonobuoy is at the guns". As soon as possible thereafter, the reading of the footage counter on the tape recorder and the launch time should be noted in the logs. Next, the graphic recorders should be adjusted for the sonobuoy signal; the receiver should be checked to ensure that the sonobuoy is properly tuned and that the AFT is tracking the radio signal; and the tape recorder output signals again checked with the oscilloscope to guarantee that all signals are being recorded properly (without clipping) on the tape recorder.

Underway operations

While the sonobuoy station is underway, there are several items that require monitoring. Initially, one must watch the RF signal strength carefully and keep the antenna preamplifier as high as possible without overdriving the receiver (for low frequency sonobuoy only). The signal levels being recorded on tape should also be rechecked periodically and adjusted if

necessary. As the station progresses, the gain on the receiver should be increased as the signal strength diminishes, and the hicut filter can be lowered to enhance the lower frequencies in the seismic signal. All changes should be noted on the log sheet as well as on the voice channel of the tape. If more than one recorder is being used, it is important to periodically (every 10 or 15 minutes) mark the same trace on all records with the event mark.

After 20-30 minutes, it may be necessary to introduce a sweep delay to the record. Generally, it is important to keep the direct arrival on the record, as well as all the seismic information. Continue to increase the delay until either the maximum allowable delay (dictated by the fire rate) is used, or until the direct trace and the seismic traces can no longer be kept on the record at the same time. A change in the amount of delay should always be accompanied by an event mark on the record. This will facilitate later preparation of the record, when it must be cut at these delay changes. This preparation will also be greatly facilitated if the amount of delay is a fraction of the integral number of time lines. (For example, on a six second record, time lines are generated by the UGR every 0.6 seconds. Therefore, successive delays should be integral multiples of this: 0.6, 1.2, 1.8, etc.) Using these fractional delay times will make it easier to align the section when constructing the complete sonobuoy record.

If the sonobuoy is deployed during multichannel operations, particularly for sonobuoys on the shelf, it is helpful to obtain wiggly trace camera records from the GUS 24 channel system. These records enable the identification of shallow reflectors and the definition of reflectors which may be obscured at the beginning of the sonobuoy station.

Generally, all sonobuoys are recorded until radio signal is lost, or

until it is clear that no additional seismic information is forthcoming. It is always advisable to continue recording until long after the buoy appears to have stopped sending useful information. We have found that atmospheric "skipping" of the radio signal often will provide small windows of seismic information well beyond the normal range of the sonobuoy. Later replay or processing may illuminate previously obscure information. In the course of very long sonobuoys, more than one reel of magnetic tape will be required for a single station. The tape change should be accomplished as quickly as possible to avoid obvious loss of information. The number of shots missed in changing reels should be accurately counted and noted in the log.

When the sonobuoy station is completed, the radio room and bridge should be notified so that the may resume their normal operations. The navigation watch should also be notified, so that necessary speed or course changes can be ordered. Upon completion, it is also useful to mark the start and end times of the station on the vertical incidence records. This will help locate the station later when the vertical incidence record must be referred to for dip information.

Replaying analog tapes

Replaying sonobuoy tapes is most easily done during the cruise while the necessary equipment is available and operational. The playback time can be reduced considerably if the sonobuoy tapes are replayed at higher speeds than those at which they were recorded. We normally replay our buoys at 15 ips, which is 4 times faster than the recording speed of 3 3/4 ips. To produce an equivalent sonobuoy record at the higher playback speeds, both the filter settings on the external Krohn-Hite filter and the sweep speed on the UGR must be changed by the appropriate fraction: playback speed/recording speed. On

playback, the filter settings should always be <u>higher</u> and the UGR sweep speed should be <u>lower</u> than the equivalent original sonobuoy record. At 15 ips we use Khron-Hite filter settings of 20-240 Hz to get a 5-60 Hz record and we use a sweep speed of 2 seconds to get an 8 second record.

Since the reason for making replays is to recover information that may have been lost or obscured on the original record, it may not be necessary to replay the sonobuoy if the original record is good. Some enhancement of the seismic data is possible by using different filter settings during replay. We routinely make one replay that is filtered to contain only the waterbreak channel (600-1200 Hz) so that the accurate direct times, often not available on the original record, can be determined.

For accurate replays, insure that the tape recorder is using the precision drive frequency that was recorded on the tape during the sonobuoy station.

III. REDUCTION AND INTERPRETATION OF FIELD RECORDS

Shipboard Interpretation

Preliminary analysis and interpretation of sonobuoy records may be done onboard ship with a few drawing supplies (Mylar, straight edge, pencil) and a hand calculator. Refraction records are straightforward since velocities can easily be determined from the ratio of the slope of the refractor to the slope of the direct arrival. The depths to the refractors can then be computed using the refraction velocities and the refractor intercepts at x = 0 (nearest approach of the sonobuoy to the sound source). An approximate technique for determining interval velocities from the wide angle reflection records can also be done onboard ship. Velocities (rms) for successively deeper reflecting horizons are first determined by a graphical method, and are then used in Dix's equation for computing the interval velocities. Detailed procedures for shipboard analysis of refraction and wide angle reflection data are given in Appendix C.

Office Procedures

Careful analysis of the sonobuoy records can be done only in the office where special digitizing and computer facilities are available. The analysis procedure involves five basic steps:

	Processing Step	System/Procedures Used	Pages/Appendix
1.	preparing the records	done by hand	41-42
2.	choosing and tracing seismic horizons	done by hand	42-44

3.	digitizing and editing seismic horizons	TEKTRONIX 4051: interactive BASIC programs REFRACT LINDIGIT and SlODIGIT	44-61/F,J
4.	processing the digitized data on MULTICS (to determine velocities and depths)	HONEYWELL 68/80 MULTICS System: FORTRAN Programs LINFT and SLOWI	62-65/H,K
5.	interpreting the computer results	done manually and with FORTRAN programs POLYFIT and SONOMODEL	66-68/I,L

A complete sequential listing of all the computational steps is given in Appendix E.

Preparing the Records

Once the sonobuoy records have been excised from the seismic reflection rolls (easily done onboard ship) they should be mounted on a stable backing (48" wide, heavy brown wrapping paper works well). Records that contain time shifted data must be carefully cut along a single vertical trace at the time shift. Use a good pair of scissors and a steady hand, or a straight edge and an exacto knife. The cut sections are then time shifted, aligned so that timing lines are parallel, and taped to the backing. The sections must be shifted and aligned very carefully because the digitizing and computer processing techniques are highly sensitive to discrete shifts in the reflecting, refracting, or direct arrival traces. The record is then covered with a sheet of clear mylar acetate (3 mil thick), that has been "cured" for shrinkage. (Leave the unrolled sheet of mylar on a flat surface for a few days before using.)

All interpretations and reference lines should be drawn on this overlay with drafting pens (point 00 or smaller). The horizontal timing lines, the initial trace (the closest approach of the sonobuoy to the source) and a reference dot on each corner of the record should be drawn on the overlay for

later orientation. The UGR recorders do not draw either the uppermost of lowermost horizontal time lines, so these must be determined using a Gerber scale or ten point dividers.

Choosing & Tracing Seismic Horizons

Next, the seismic traces should be marked on the overlay. The seismic arrivals generally consist of a complex wave train, and it is important to pick the same phase of the wave on successive recorder sweeps. The use of transparent colored inks (red, blue, violet) leaves the phase clearly discernable beneath the inked line. Because the ink tends to spread on the acetate, it is advisable to use the narrowest drawing pen available.

The direct trace should be drawn and extended back through the initial sweep trace. The intersection of these two lines (the initial sweep and direct tract) is the time origin of the sonobuoy record. If the sonobuoy hydrophone had been precisely adjacent to the airguns on the first sweep, and if the air guns and the recorder had been triggered simultaneously, this intersection would correspnd exactly to the time origin of the graphic recorder. Thus, any difference in zero times results from delays in the timing and recording circuitry and from a difference between the depth of the sonobuoy hydrophone and the airgun. When drawing the direct trace, be aware that slope changes in the direct arrival trace may occur; these result from small relative course or speed changes during the sonobuoy station.

The refractors can be drawn next. In shallow water (less than 300 meters), this is a relatively straightforward process, because all refractors appear as first breaks on the record (see Figs.2 and 5). On records from stations in deeper water, however, shallow refractions do not

always come in as first breaks, but may be masked by refractions from deeper horizons, (Figs. 3 and 6). Therefore, care must be exercised when picking the deep water records to guarantee that all possible refractors have been marked.

Generally, shallow water sonobuoy stations (less than 300 meters) produce good refraction records, but do not yield useable wide angle reflection records. Because the moveout of a reflection hyperbola occurs rapidly for shallow reflectors, the reflection information is usually impossible to read from the high vertical exaggeration sonobuoy records. As a general rule, the horizontal distance over which useful wide angle reflection information can be collected is equal to twice the water depth. With a 50 meter sample interval, measurement of wide angle reflections does not become feasible on the sonobuoy records until the water depth exceeds 1000-15000 meters, and is best done in the deep ocean basins (greater than 3000 meters of water).

Even on a good quality sonobuoy record, there may be a multitude of possible reflection traces to pick, primarily because the reflection section is often complicated by multiples and artificial "bubble pulse" reflectors. In the absence of other information, it is permissable to pick all possible reflections and rely on later editing to identify and remove the questionable traces. This is a time consuming process, however, and a preferable method is to establish initial criteria to determine which reflection traces should be picked.

The first criteria involves choosing those reflection traces which have associated refractors. A refractor, once identified, usually can be traced back to the reflection to which it is tangent. As mentioned earlier (p. 11), assignment of the refraction to the correct reflection hyperbola may be aided by noting which reflection hyperbola undergoes an abrupt increase in

reflection amplitude near the point of tangency. Computer results from the refraction data, if available, can also be used as a guide in determining the normal incidence time to the refracting horizon. The normal incidence times to the refractor (from the refraction solutions) should be compared to the vertical incidence seismic reflection profile recorded just prior to launching the sonobuoy to locate the correct reflecting horizon.

A second criteria is that all prominent reflectors observed on the reflection profile (ideally a processed multichannel record) over the sonobuoy station should be picked on the sonobuoy record. Artificial reflections are sometimes suppressed on the vertical incidence record, making it easier to pick out the real reflections. The real reflections can be identified on the early traces of the sonobuoy record.

A final criteria can be employed if there are several sonobuoy stations that are close together. Reflectors can often be correlated from one station to another, assuming that reflectors in the region are continuous. Correlating reflectors between stations will not only aid in picking the records, but will benefit the interpretation by producing a more realistic picture of the sub-surface velocity structure.

<u>Digitizing and Editing Seismic Horizons</u>

Once the sonobuoy record is prepared and marked, the interactive computer programs for the TEXTRONIX 4051 System are used to digitize the sonobuoy record. Refractions and wide angle reflections are digitized separately, using two different programs LINDIGIT and SLODIGIT. In the following sections, we first describe the machine on which the digitizing is done (the hardware) and then describe the computer programs which have been written to perform the digitizing (the software). Appendix G contains

examples of the digitizing programs, while Appendix J contains program listings.

In the past, digitizing the sonobuoy records was a time consuming process that had to be done manually. The time pairs were measured off the record using a Gerber scale, then recorded on computer coding forms, keypunched, and read into the computer. Now the process is semi-automated and relatively fast. The individual points are picked by hand using a cross-hair cursor and a digitizing tablet. The position of the digitized point on the sonobuoy record is automatically input to the minicomputer program and is stored in the memory. The minicomputer program also allows interactive editing of the data points before the program writes a final data set on magnetic tape. The final data set is, in turn, transferred to and used by the U.S.G.S. Honeywell computer (MULTICS) to complete the data reduction.

Simplification of the numerous intermediate steps (coding, keypunching, card reading, etc.) has substantially decreased the time necessary for processing a sonobuoy record.

The computer programs for digitizing the sonobuoy records are written in a modified BASIC language for a Tektronix 4051 Graphics System. Two pieces of peripheral equipment, a Graphics Tablet (Tektronix 4956) and a Digital Cartridge Tape Drive (Tektronix 4924) are used by the Graphic System during the digitization process. A third peripheral device, a Hard Copy Unit (Tektronix 4631) is useful, but not required, for copying information from the CRT screen. The 4051 Graphic System must be equipped with 16k bytes of memory, a binary program loader, and a data communications interface in order to run the programs and communicate with the MULTICS computer.

General Notes on the Tektronix System

Before using the sonobuoy digitizing programs, it is helpful to become acquainted with the Tektronix 4051 through the Graphics System Tutorial, available on the Plot 50 Systems Software Tape. To get started, turn the 4051 on (the switch is under the console on the right) and allow the machine a few seconds to warm up. (The screen will become bright, and can be cleared with the "HOME PAGE" at the upper left of the keyboard). Insert the Systems Software Tape and press AUTOLOAD (at the upper right of the keyboard). The program will enter an interactive mode. To the first question reply "4" and press "RETURN". This will initiate the tutorial.

During the tutorial, you may wish to retain a copy of the information on the screen. This requires that the hard copy unit be on and warmed up (5-10 minutes in advance). Then, the screen image may be copied by pressing "MAKE COPY" (at the upper right of the keyboard) or the button on the hard copy unit. The "light-dark" control adjusts the intensity of the copied image.

Digitizing Programs

The digitizing programs written for the 4051 are completely interactive. All input is requested through the program, and is entered from either the terminal console or the Graphics Tablet. All console input is free format. Program output is sent either to the terminal CRT screen or, if requested, to magnetic tape through the auxiliary tape cartridge drive. Permanent record of output to the CRT screen is possible only with the hard copy unit.

The final output data set is written to and stored on the data tape in the auxiliary tape drive. This data set is subsequently transferred to the MULTICS computer system for reduction. Each data set is written on a separate tape file, which must be marked prior to writing. The digitizing programs will mark the tape file automatically if requested. Previously marked tape

files may be overwritten without disturbing the data on the rest of the tape.

MARKING A NEW TAPE FILE, HOWEVER, WILL DESTROY ALL SUCCEEDING TAPE FILES!!

Therefore, care must be taken to maintain a record of the tape files

previously used, if several data sets are written on the same tape before they

are transferred to MULTICS for permanent storage.

The magnetic tape cartridges contain a write protect mechanism. This is a small slot at one corner of the cartridge, with a black triangle inscribed next to it. The slot can be turned with a screwdriver or even a strong thumb nail. When the trangle points to "SAFE", the magnetic tape cannot be written on, and is write protected. When the triangle points the other way, the tape is "write enabled", and data can be written to tape.

To initiate either digitizing program, the sonobuoy program tape should be inserted into the 4051 internal tape drive, and the data tape, write enabled, should be inserted into the peripheral tape drive. The user starts the program by pressing the "AUTOLOAD" button and, when queried, by indicating which type of data (refraction or reflection) is to be digitized. This will direct the program to the correct starting point, and the interactive process will begin.

The operation of the program can be monitored in several ways: by the questions or statements written on the CRT screen, by the status lights at the upper righthand side of the console, and by the cursor (the blinking signal on the screen). While the program is operating, the "BUSY" status light will be illuminated. When user input is required, the I/O status light will also be illuminated, and the cursor will either be blinking "?" (indicating console input) or will have disappeared (indicating digitized input from the Graphics Tablet). When the program has reached a stopping point, all lights (except "POWER") will be dark, and the cursor will display a blinking rectangle. At

this point, the program is awaiting direction via the user definable keys.

The user definable keys (referred to later in the text by UD #) are located at the upper left of the terminal console, and serve as a nerve network, directing program flow and providing user commmand control. Generally, the user definable keys either branch to a subroutine which, upon completion, returns to the program point at which the branch requested; or they link to subsequent program sections and continue execution. The specific function of each user definable key is indicated on a plastic overlay which can be placed over the keys for easy reference.

Whenever the CRT screen becomes full with input data, the "page full" condition will be indicated by a blinking "F" in the upper left corner of the screen. The "HOME PAGE" button at the upper left of the keyboard will erase the screen and allow the program to continue. If a copy of the information on the screen is desired, it can be made at any time by pressing "MAKE COPY". Any input from the keyboard is terminated by a keyboard "RETURN". An input error can be corrected before the "RETURN" by either erasing (with the "RUBOUT" key) and retyping, or by pressing the "CLEAR" key (at the top center of the console) and reentering the data.

Digitized data values are input to the program through the Graphics Tablet, which must be powered up <u>before</u> the digitizing program has been started. The toggle switch to turn the power on is located at the back of the control box, on the right. There are two digitizing cursors available, a pen cursor and a cross-hair cursor. To digitize a point with the pen, place it directly on the point and press slightly. With the cross-hair cursor, align the hairs over the point and press the white button in the middle of the cursor. The pen cursor is easier to use, while the cross hair cursor is more accurate. Most sonobuoy digitizing should be done with the cross hair cursor.

Whenever a point is digitized, the 4051 will emit a short, high pitched tone. If this tone is not forthcoming, then something is wrong. It may be necessary to quit the program (by pressing the "BREAK" key twice), turn the digitizing table off and on again, and restart the program. Before the program is started, later trouble may be avoided by pressing the white button on the cursor (or by pressing the pen point) and observing the red lights at the left of the control box. Before the program is operating, the "Z-AXIS" light should go on when the button is pressed, but the "PROX" light should remain off. When the program is operating, both lights should go on, and the "PROX" button will generally stay on.

Each of the digitizing programs requires that the origin of the record be set before the other points are digitized. The program will direct the user when this step is required. To set the origin, press the "ORIGIN" button on the control box, and digitize the origin point, with the origin button depressed. After hearing the tone, release the the origin button.

The sonobuoy record should be placed on the digitizing table with the time axis aligned approximately parallel to the long edge of the table. Therefore, the origin will usually lie near the lower left corner of the table. The record need not be aligned exactly parallel with the table, however, because the program performs a coordinate transformation on each point to correct for misalignment.

In order to process the sonobuoy reflection or refraction data, the computer program must be provided with both the distance from the ship to the sonobuoy as well as the total reflection or refraction time required for the energy to travel from the airguns through the water and subsurface rocks to the sonobuoy. The distance is computed from the direct arrival time and the

total travel time is read directly from the sonobuoy record. Consequently, the digitized input required for the processing programs consists of time:time pairs (e.g. direct arrival time:total reflection time).

Refraction traces are easier to pick than reflection traces. Five point are usually sufficient to define a refraction, whereas at least 15, and commonly 30 or more points are required to reliably determine a reflection hyperbola. Refraction traces are most easily picked by digitizing a direct time and a refraction time for each data point. Therefore, five points along a refractor will require 10 time picks. Because successive reflectors on a record underly one another, digitizing reflection points is facilitated by picking a direct time and then all the reflection times along the same recorder trace. Therefore, if 8 reflecting horizons are to be measured, then 9 data points (one direct and 8 reflection) will be picked along a given recorder trace.

<u>Digitizing Refractions (Textronix Program LINDIGIT)</u>

The program for digitizing refraction records is straightforward and self-explanatory. All the input data required is available on the record itself or on the log sheets. The following procedure describes the basic steps in the program, and a complete example may be found in Appendix D.

- 1. Place the sonobuoy record on the Graphics Tablet and secure it in place.
- 2. Initialize the program by following the instructions given.
- 3. Set the Origin and determine the scale factor.
- 4. Check the reference marks and reset the origin, if necessary.
- 5. Digitize the data points (direct arrival: total travel time pairs).


- 6. Write out the parameters to the screen for copying.
- 7. Write and output data set to tape for transmittal to Multics.

The program is controlled interactively; there are no user definable functions available, with the exception of the MULTICS login procedure (UD 14).

Two options are available in the program. The first is the number of points per refractor that are to be picked. We have found that in general, five points are sufficient to determine refractions accurately. However, in some situations it may be preferrable to pick more points. The program will also provide a hypothetical seafloor refractor (given the depth of the seafloor and an assumed velocity of 1.55 km/sec). This option is probably not necessary in shallow water, but is required on deep water buoys where the seafloor refraction is probably not visible on the record.

Digitizing Reflections (Textronix Program SLODIGIT)

The reflection digitizing program is completely interactive and prompts the user for all necessary input information. A good rule to follow in choosing the horizontal distance over which the wide-angle reflection traces can be used for the velocity analyses is that the total reflection angle from seismic source to sonobuoy should not exceed 90° (incidence angle of 45°; Knott and Hoskins, 1975). The 90° reflection angle is reached for the seafloor roughly at the vertical trace on the sonobuoy record at which the direct arrival time is equal to the normal incidence time for the seafloor (see Figure 10). All reflection picks should be made prior to this vertical trace. Thirty data points are sufficient to determine the wide angle reflection, although as few as fifteen and as many as forty may be used.



TOTAL NUMBER OF TRACES = 100
NUMBER OF SAMPLES = 25

$$\Delta x^2 = \frac{(100)^2}{25} = 400$$

Δx^2	Δ×	Trace
0	0	0
400	20	20
800	28.3	28
1200	34.6	35
1600	40 :	4 0 :
10000	100	100

Figure 10 Method for picking wide angle reflections in deep water to ensure even distribution of samples in x-squared.

TABLE 2

Function of User Definable Keys Reflection Digitizing Program

UD #	UD Key Name	Function	Program Section
1	Repick point	Repick point - correction while digitizing	DIGIT
2	Skip layer	Skip layer - correction while digitizing	DIGIT
3	Stop on trace	Skip rest of vertical trace-correction while digitizing	DIGIT
4	STOP digitizer	Stop digitizing	DIGIT
5	List parms	List input parameters	DIGIT
6	Delete layer	Delete layer	EDIT
7	Delete trace	Delete vertical trace	EDIT
8	EDIT points	Edit (remove/reinsert) points	EDIT
9	Residual table	Print residual table	EDIT
10	SLOWI list	List SLOWI formatted data set	EDIT
11	X2T2	Branch to $X^2 - T^2$	DIGIT, EDIT
12	DHRC	Branch to DHRC	DIGIT EDIT X2T2
13	Reference check	Verify record alignment	DIGIT
14	MULTICS login	Login to MULTICS	EDIT
15	List picks	List digitized picks	DIGIT
16	EDIT	Branch to EDIT	X2T2
17			
18	DUMP to tape	Dump digitized data to tape	DIGIT
19	RECYCLE from tape	Read data from tape	DIGIT
20	SLOWI to tape	Write SLOWI formatted data set to tape	EDIT

Because the reflection time versus distance equation is linear in X^2 , the digitizing interval should also be equal increments of X^2 . If instead, equal increments in X are used, the least squares solution for the X^2 - T^2 line will be too heavily weighted near the origin. Therefore, the digitizing intervals should get closer together with increasing values of X. The digitizing process is considerably facilitated by counting and marking the recorder traces before they are digitized. Figure 10 illustrates which traces would be picked if we wished to make 25 picks over 100 traces of the seismic record.

If the digitizing is done from two records (one containing the direct arrival and the other containing the seismic information) it is essential that the traces on each record be accurately counted and that identical traces on both records be marked before digitizing. The direct time and reflection times must be measured along the same trace or significant errors will result. (It is for this reason that emphasis was placed in the operation section on carefully marking the intitial trace on both sonobuoy records, and on placing simultaneous even marks on both records at periodic intervals).

The program for digitizing wide angle reflection records is a more complicated program than the refraction digitizing program, since it performs several functions in addition to simply digitizing the record and writing an output data set to tape. The program is broken into five subprograms; these subprograms are linked together through the user definable keys. An example of the reflection digitizing program is given in Appendix F, and the BASIC program in Appendix J. Table 2 indicates the user definable functions available, with descriptions of their use and the program sections under which the functions operate. Table 3 lists the procedure to be followed for digitizing and editing a wide-angle reflection record. The five program sections are:

I. Initializing and digitizing: DIGIT

II. Delayed hydrophone release correction: DHRC


III. X^2-T^2 calculation: X2T2

IV. Data editing: EDIT

V. Dump to tape and recycle from tape: DUMP

I. Initializing and digitizing

This section interactively queries the user for all required input information. It asks the user to digitize all relevant points on the record (e.g. the origin, the zero point, the point at which the hydrophone was released, the seafloor, etc.) The program allows for data points to be digitized from a single record, or for the direct times to be digitized from a second record. Generally, the direct time is digitized first, followed by the reflection times along the same recorder sweep for all the reflecting layers. (If two records are used, all the direct times are digitized first, then the same recorder traces are located on the second record and the successive reflectors digitized.) While digitizing, the user is capable of making minor corrections or changes in the digitizing order through the user definable keys. If a user definable key is used while digitizing, it must be "activated" by digitizing a random point on the table. (The point digitized to activate the UD function is discarded, so its position is irrelevant.) These allow a point to be repicked, if done before the succeeding point is picked (UD 1), for a single layer to be skipped along a trace (UD 2), and for all succeeding layers to be skipped along a trace (UD 3). When all points have been picked, the digitizing is halted with a user definable key (UD 4). A final step in this section is to write out a table of






Figure 11 Overlays for user definable keys for the reflection digitizing program and data communication interface (MULTICS interface). UD 14 (MULTICS login) on the reflection digitizer also works from the refraction digitizer. The only user definable functions required for MULTICS operation are UD 13 (find file), UD 4 (data send) and UD 5 (return to BASIC).

input parameters (UD 5), as well as a table of raw data picks (UD 15).

II. Delayed hydrophone release correction: DHRC-(UD 12)

This section is optional, and corrects all points prior to the time of the hydrophone release by an amount proportional to the hydrophone depth. This adjustment is explained in Appendix F.2 on corrections concerning the hydrophone lower. This program section automatically transfers program execution to the next section $X^2 - T^2$.

III. $X^2 - T^2$ calculation (UD 11)

First, this section converts the direct times to true distance and squares the distance:time pairs. Then the program performs a linear least squares fit to the squared values and calculates the slope and intercept of the least squares line. From these results, the velocity and depth to the reflecting horizon are determined, and the interval velocity calculated from Dix's equation (see Dix, 1955 and Appendix B). For each layer, a table is produced listing the input times, the converted distance, squared distance and time, and the residual (observed T^2 value minus least square T^2 value). These listings are optional. A second table lists the rms velocity, reflection time, interval velocity, depth, and coefficient of determination ("FIT") for each layer. Finally, the program plots the X^2 - T^2 values with the linear fit line. This plot may be reproduced at different scales.

IV. Data Editing: EDIT (UD 16)

Program control is next transferred to the Edit portion of the program, which allows the user to remove horizontal layers, vertical traces or individual points from the data set (UD 6, 7, and 8 respectively). Editing is performed on the basis of the table and plot produced by the X^2 - T^2 section, and by a "residual table" which the

editing section also produces (UD 9). This residual table lists the same residuals that were listed in X^2 - T^2 , but the tabular form makes the identification of poorly picked reflectors and erroneous direct picks much easier. The criteria for editing points is discussed in the subsequent section on Editing Reflection Data. The final function of the Edit section is to write a formatted output data set to magnetic tape so that it can subsequently be transferred to MULTICS. However, this need not be done after the first call to Edit, because X^2 - T^2 can be called up again from the Edit section, and the two sections iteratively invoked until a satisfactory data set is produced.

V. Dump to tape and recycle from tape

This section dumps the digitized data (after completion of section I) onto a magnetic tape file for later retrieval and use. Since the digitizing of the data is the most time consuming part of the process, dumping to tape immediately after completing the digitizing will protect against complete loss of data if something goes awry later in the process. This feature is also useful if it is necessary to interrupt the program before reaching the final editing step.

Section V also allows the user to read the digitized data from tape and to reenter the program as though the initial digitizing section (I) had just been completed. To recover this data, respond affirmatively to the first question asked by the program ("Do you wish to recover data from tape?"), and when queried, specify to which tape-file the data you wish to recover has been dumped. After the data read is completed, the "Parameter List" key can be pressed to verify that the correct data has been recovered, and then the HDRC or X^2 - T^2 button can be pressed to continue.

Table 3

Procedure for digitizing and editing wide-angle reflection data

- 1. Digitize record (Part I)
- 2. Dump raw digitized data to tape (Part V). This step protects against later error or interruption in the process.
- 3. Delayed hydrophone release correction (Part II). The Delayed hydrophone correction can be called directly after the digitizing step, or can be made after X^2 - T^2 and/or Edit have been called. It is sometimes helpful to see the X^2 - T^2 plot before and after the correction to determine whether the data was improved. This correction is reversible, that is the correction can be removed if it appears detrimental. This subprogram branches directly to X^2 T^2 . See Appendix F.1 for a more complete explanation of this correction.
- 4. $X^2 T^2$ (Part III). This is the first pass at $X^2 T^2$.
- 5. Edit (Part IV). First print out a residual table, and use it in conjunction with the X^2 T^2 table and plot to edit traces and points through the user definable keys.
- 6. $X^2 T^2$ (Part III). With the edited data set, return to $X^2 T^2$ and reevaluate preliminary velocities and depths.
- 7. Edit (Part IV). Return to Edit. The iterative process between X^2 T^2 and Edit can continue until satisfactory data set is produced. EDIT allows previously removed points, layers or traces to be reinserted. When a final data set is reached, it should be dumped to tape (V) for later transmittal to MULTICS, and it should be recorded on paper by pressing the "MAKE COPY" button.

Editing Reflection Data

After the reflection traces are digitized, they must be checked carefully for digitization errors. Two principal sub-programs for editing the data are available. These sub-programs, which must be used sequentially, are $X^2 - T^2$ (UD 11) and EDIT (UD 16). Several criteria, based on numbers generated by these sub-programs help the user decide which traces or data points are questionable and should be discarded. The criteria include:

1. $X^2 - T^2$: The parameter "FIT" (e.g. coefficient of determination) is a number between 0.0 and 1.0 that indicates the "goodness of fit" between the X^2 , X^2 points and the least square line that passes through these points. Our experience has shown that "FIT" should not be smaller than either 0.99990 for shallow layers (0.0-1.0 sec sub-bottom) or 0.99900 for deep layers (greater than 1.0 sec sub-bottom).

- 2. $X^2 T^2$: The RMS VELOCITY should increase with depth. A reflector that has an RMS VELOCITY, which is the smaller than that of the overlying layer, is probably a multiple reflection event and should, therefore, be removed.
- 3. X² T²: The INTERVAL VELOCITY normally increases with depth, therefore, any decrease in the INTERVAL VELOCITY (less than 80% of the overlying layer) should be examined carefully. The interval velocity is calculated with the Dix equation (Dix, 1955), so a decrease may be caused by a computational, rather than a real geologic, effect. Normally, computational instabilities (e.g. velocity inversions) are found when reflectors are too close to one another. The "resolution" of the sonobuoy technique is generally no better than a layer thickness that is 1/12 of the water depth (LePichon et al., 1968). If a velocity inversion in the INTERVAL VELOCITY occurs in a layer, try discarding that layer (or discard the next deeper layer if the deeper layer is thinner).

4. EDIT: The residual values $(T_{\rm observed}^2 - T_{\rm calculated}^2)$ which are tabulated for all data points, should generally be smaller than 300. Omit points with larger values. The residual table also shows bad traces (high residuals for every point along the trace) as well as traces that have a high, but acceptable, degree of scatter (this is also reflected in the parameter FIT in the $X^2 - T^2$ section). Often the pattern of the residuals for a trace (negative at both ends of the trace but positive in the middle) indicates curvature in the $X^2 - T^2$ line, which is caused by dip in the reflector.

Once the initial X^2 - T^2 and EDIT steps have been completed and the erroneous data removed, another iteration of the process is usually advisable. The X^2 - T^2 section can be recalled and calculations made with the corrected data set. Then editing routine can be entered a second time, and additional data removed, or previously edited data reinserted, if desired. When the data has been satisfactorily edited, the final function of the editor is to write a SLOWI formatted data set to tape. This data set is then suitable for transferral to MULTICS and input directly to SLOWI.

Processing The Digitized Data on MULTICS

The two programs for processing the digitized sonobuoy records are called LINFT (for LINear FiT) and SLOWI (for SLOping WIde angle). These programs were obtained from Woods Hole Oceanogaphic Institute, and are described in detail in Knott and Hoskins (1975). Program LINFT is used to process the digitized refraction data, while SLOWI is used to process wide angle reflection data. A theoretical basis for SLOWI is given in Appendix D. When these programs were converted for use on the U.S.G.S. computer system, some significant errors were found and the necessary corrections were included. Both SLOWI and LINFT are available on the U.S.G.S. Honeywell Multics system in Menlo Park, California. Complete descriptions of the input required for each program, as well as an example data set, are included in the introductory comments to each program (see the FORTRAN listings in Appendix K). Examples of the output from these programs are shown in Appendix H.

The Honeywell Multics System is rather formidable, and the inexperienced user is advised to obtain some assistance before attempting to use it. The procedure below outlines the basic sequence of commands necessary to access and execute the programs, but these will be given without further explanation. Communication with MULTICS computer, through the Data Communication Interface of the Tek 4051, is initialized by calling a BASIC program, which is available through UD 14 from either digitizing program. (Warning: by calling this program, all digitizing program information is lost. Therfore, the MULTICS login must not be called before all the digitized information has been written to tape.)

The following sections describe the method by which the MULTICS programs are accessed and executed. Within the text are the commands and replies from an actual terminal session, during which links to the sonobuoy programs were created. The digitized data were transferred from magnetic cassette tape to MULTICS, and the reduction program (in this example SLOWI) executed. The terminal session is shaded in the text, and the arrows (——) indicate commands or information entered by the user.

When the MULTICS system has been called up with UD 14, the user is ready to login:

→ 1 ASmith
Password:
→ ■PAESESSASS

You are protected from preemption until 2252.

ASmith Marine logged in 04/05/78 2252.5 pst Wed from ASCII termina Last login 04/05/78 2154.7 pst Wed from TN300 terminal "none". check_info_segs: No change.

No memos.

- Wed 04/05 2252.6

The terminal parameters necessary for the Tektronix are initialized by:

→ stty -modes *1fecho.pl34,1172

where ^lfecho disables the line feed echo by the carriage return (assuming that the user has enable lfecho, perhaps through a start_up.ec). The pl34 parameter sets the page length to 34 lines and 1172 specifies that the Tektronix CRT is 72 characters wide. The stty command can be imbedded in a start_up.ec for convenience. With the page length set, MULTICS will stop sending data to the terminal after every 34 lines printed, and issue an EOP (for End of Page). To continue, press "HOME PAGE" and then "control L". (The control key works like the shift key.)

All the segment links necessary to access the programs mentioned here

are provided through an exec_com entitled sonobuoy.ec. This exec_com need only be linked to and invoked one time. The procedure is:

```
- link >udd>Marine>JChilds>sonobuoy.ec
- Tue 03/21 1750.7

- ec sonobuoy
link >udd>Marine>JChilds>sonobuoy>slowi.fortran
link >udd>Marine>JChilds>sonobuoy>slowi
link >udd>Marine>JChilds>sonobuoy>linft.fortran
link >udd>Marine>JChilds>sonobuoy>linft
link >udd>Marine>JChilds>sonobuoy>linft
link >udd>Marine>JChilds>sonobuoy>sonomodel.fortran
link >udd>Marine>JChilds>sonobuoy>sonomodel
link >udd>Marine>JChilds>sonobuoy>sonomodel
link >udd>Marine>JChilds>sonobuoy>sonomodel
link >udd>Marine>JChilds>sonobuoy>sonomodel
link >udd>Marine>JChilds>sonobuoy>sonomodel
link >udd>Marine>JChilds>sonobuoy>plot.ec
- Tue 03/21 1750.8
```

All data stored on the tape cassettes is transferred to MULTICS through a text editor. We always use "ted", but "qedx" can be used in an identical manner:

```
→ ted

— a

(find file)
(data send)

— \( (User definable key 13) \)
(User definable key 4)

— \( (User definable key 4) \)

— \( (User definable key 13) \)
(User definable key 4)

— \( (User definable key 13) \)
(User definable key 4)

— \( (User definable key 4) \)

— \( (User definable key 13) \)
(User definable key 13)

(User definable key 4)

— \( (User definable key 13) \)
(User definable key 4)

— \( (User definable key 4) \)


— \( (U
```

To execute a sonobuoy program (we have here used SLOWI as an example) it

is first necessary to specify the segments for data input and output. This is done with io.ec, which requires two arguments: the input data segment and the target segment for output.

```
ec io testa.data testa.result
io attach file05 vfile_testa.data -no_trunc
io attach file06 vfile_testa.result -no_trunc
- Tue 03/21 1754.0
```

Finally, the program itself is executed:



The results are either printed out at the terminal (with the print command), e.g.

pr testa.result

or printed offline with daemon_print

dp testa.result

When entirely finished, the user should logout, and return the Tektronix to BASIC control, with UD 5 (see Fig. 11).

Sonobuoy Interpretation Programs

Two interpretive programs are available. The first, called SONOMODEL, produces a Benson-Lehner pen plot of an artificial sonobuoy record. The program requires as input a layered model, with specified velocities and thicknesses for the layers. Based on ray tracing theory and assuming flat lying layers, the program produces a pen plot, which is scaled to match an actual sonobuoy record. This plot includes wide angle reflections, refractions, direct arrival, and indicates the critical point for each layer. Also produced by the program is an output table listing which includes critical distance and critical time for each layer.

Before executing the modelling program, an input segment must be created, generally through a text editor. The required information and format are specified in the introductory comments prefacing the fortran listing of the program (sonomodel.fortran). This listing is included in Appendix K.

The terminal session which follows was used to run the SONOMODEL example in Appendix I. We assume that this model data set has already been entered as a segment called testc.model.data. We ask that the output from SONOMODEL be directed to a segment called testc.model. The plot produced by the program is contained in the segment called bl_plot. When the plot is produced, the U.S.G.S. project account to which the plotting should be billed must be furnished. This is a nine digit number and is referred to below as "account#".

—→1s

Segments = 1, Lengths = 1.

rew 1 testc.model.data

- Wed 03/22 2114.8

ec asr
asr >udd>bl lib -after working_dir
- Wed 03/22 2114.9

ec io testc.model.data testc.model
io attach file05 vfile testc.model.data -no_trunc
io attach file06 vfile testc.model -no_trunc
- Wed 03/22 2115.1

STOP

fortran io : Close files? yes ← Wed 03/22 2115.9

Segments = 3, Lengths = 24.

r w 21 bl_plot r w 2 testc.model rew 1 testc.model.data

- Wed 03/22 2116.1

ec plot account#
ec >udd>bl lib>plotter "bl plot" "30" "1" "account#"
Tape bl plot Marine,7track,den=556 will be mounted with a write ring.
Tape plot.parm Marine,7track,den=556 mounted on drive 5 with a write r
TAPE: plot.parm JChilds written at 03/22 2123.8 Wed
io detach plot
- Wed 03/22 1217.9

dp testc.model 1 request signalled, 3 already in printer queue 3 - Wed 03/22 2203.8 The sonomodel program also contains the option to produce page size illustrations of sonobuoy records. A comment in the program listing notes which lines must be changed to enable page size plots. To do this, the user must copy the fortran listing (sonomodel.fortran) into their own directory, make the changes through the text editor, and recompile the program. Figures 5 and 6 were produced in this manner.

The other interpretive program called POLYFIT, performs polynomial regressions and operates on the Tektronix 4051. The polynomial regression can be used to determine the relationship between travel time and sediment depth from the sonobuoy results, and hence provides excellent use of the sonobuoy data in the analysis of vertical incidence seismic records. See Appendix I for further details. The regression program itself is available on the Statistics package of the Tek 4051, and is fully cocumented in the Statistical package manual. Examples of both SONOMODEL and POLYFIT are contained in Appendix I.

REFERENCES CITED:

- Bialek, E. L. (editor), 1966, Handbook of oceanographic tables: Special Publication SP-68, U.S. Naval Oceanographic Office, Washington, D. C., Section III, Table II, p. 63-95.
- Dobrin, M. B., 1976, Introduction to geophysical prospecting (3rd ed.). McGraw-Hill Book Company, San Francisco, 630 pp.
- Hamilton, E. L., Bachman, R. T., Curray, J. R., and Moore, D. G., 1977, Sediment velocities from sonobuoys: Bengal Fan, Sunda Trench, Andaman Basin, and Nicobar Fan: Jour. Geophys. Research, v. 82, p. 3003-3012.
- Hamilton, E. L., Moore, D. G., Buffington, E. C., Sherrer, P. L., and Curray, J. R., 1974, Sediment velocities from sonobuoys: Bay of Bengal, Bering Sea, Japan Sea, and North Pacific: Jour. Geophys. Research, v. 79, p. 2653-2668.
- Hill, M. N., 1963, Single-Ship Seismic Refraction Shooting, in <u>The Sea</u>, vol. 3. M. N. Hill ed., John Wiley & Sons, New York, 963 p.
- Houtz, R. E., Ewing, J., and Buhl, P., 1970, Seismic data from sonobuoy stations in the northern and equatorial Pacific: Jour. Geophys. Research, v. 75, p. 5093-5111.
- Houtz, R. E., Ewing, J. I., and Le Pichon, X., 1968, Velocity of deep-sea sediments from sonobuoy data: Jour. Geophys. Research, v. 73, p. 2615-2641.
- Knott, S. T., and Hoskins, H., 1975, Collection and analysis of seismic wide angle reflection and refraction data using radio sonobuoys: Technical Report 75-33, Woods Hole Oceanographic Institute, 86 pp.
- Le Pichon, X., Ewing, J., and Houtz, R. E., 1968, Deep-sea sediment velocity determination made while reflection profiling: Jour. Geophys. Research, v. 73, p. 2597-2614.
- Levin, S. (editor), 1968, Velocity profile atlas of the North Pacific (Composite profiles): National Oceanographic Data Center, Washington, D. C. 20390.

- Matthews, D. J., 1939, Tables of the velocity of sound in pure water and sea water for use in echo sounding and sound ranging: Hydrographic Dept., Admiralty, London.
- Nettleton, L. L., 1940, Geophysical prospecting for oil. McGraw-Hill Book Company, New York, 444 pp.
- Officer, C. B., 1974, Introduction to theoretical geophysics. Springer-Verlag, New York, 385 pp.
- Telford, W. M., Geldart, L. P., Sheriff, R. E., and Keys, D. A., 1976, Applied geophysics. Cambridge Univ. Press, Cambridge, chapter 4.

Appendix A: Range and Penetration of Sonobuoys

(excerpted from an internal memo dated 12/14/77)

Subject: What type of sonobuoy do I need to get the job done?

NAVY or Commercial?

The answer to the above question depends on where you will be working, deep or shallow water. After talking to many of you about your sonobuoy results from 1976 and 1977, and after considering our work in the Bering Sea, we have put together a rather complicated diagram (attached) of a typical continental margin. The diagram is intended to illustrate how much crustal penetration we can expect to attain using either the Navy 41B or commercial sonobuoys with the 1326 cu.in. airgun array.

Three important observations have been made after examining the '75, '76, '77 records from sonobuoys that functioned properly:

- A. On the shelf (200 m), an acoustic basement refractor (v=4.5-5.5) is seen on all sonobuoy records; however, this is the deepest refractor that can be identified on either the Navy or commercial buoy records. Insufficient seismic energy, rather than buoy transmitting range, is the limiting factor.
- B. At intermediate depths (200-3000 m), a sub-basement refractor (v=6.0-6.7) is often seen with commercial buoys; the deepest refractor on Navy records is from acoustic basement.
- C. In deep water (3000 m), a mantle refractor (v=7.9-8.4) can sometimes be identified with commercial buoys; Navy buoys normally only show a refractor from oceanic layer 3.

The type of buoy that will get the job done for you, based on our previous experiences on the LEE, is shown in the table:

Type of Area study	Shelf (200m)	Intermediated (200-3000m)	Deep water (3000m)
Sediment and Basement velocity	Navy	Navy	Navy
Deep crustal structure	Need Explosives	Explosives or Commercial	Commercial

TYPICAL CONTINENTAL MARGIN




Figure 12 Sonobuoy penetration and range as a function of tectoni province. All results indicated in this diagram are strictly hypothetical, based upon sonobuoy models. The limits shown are approximate depths of penetration for commercial and military sonobuoys.

Appendix B

Velocity of sound in sea water

Velocity of sound in water is a function of several variables, primarily water temperature, pressure, and salinity. For a given area and time of year, however, the velocity of sound may be expressed simply as a function of water depth. Figure 14 illustrates this variation for the Southern Bering Sea during the summer months of July through September. The diagram is taken from Levin (1968, vol. II, p. 393). The plot shows sound velocity in meters/second versus water depth in meters. Also shown in the diagram are the hydrophone depths for sonobuoys equipped with 60,120, and 240 foot lowers.

From the plot, we can see that the velocity at the sea surface, v_h , is about 1485 m/s. There is a sharp negative velocity gradient to a depth of 100 meters, at which point the velocity gradient reverses, and from there increases, almost linearly, to a depth of just less than 2000 meters (off the bottom of the graph). While this curve is not representative of all ocean waters, it does serve to point out some difficulties of which the sonobuoy user should be aware.

First, the marked velocity inversion, which results from the thermocline observed in most areas, should be considered when choosing the hydrophone lower depth. In the Southern Bering Sea, the inversion is quite deep, but in other areas it can occur at a much shallower depth. If the hydrophone is too deep and drops below this inversion, the velocity structure of the water may actually reflect the direct arrival energy away from the hydrophone, resulting in a very weak direct arrival. The deeper hydrophone may also result in less clearly defined seismic reflection arrivals. Each individual seismic wavelet recorded at the hydrophone consists of the primary wavelet and an accompanying




Figure 13 Variation of velocity of sound in sea water with depth for the Southern Bering Sea, summer months.

"ghost" wavelet from the sea surface (water-air interface). With a deeper hydrophone, the time delay between the primary arrival and its ghost will be greater, and the composite wavelet more diffuse. (Knott and Hoskins, 1975, p. 24). Errors may also be introduced into the wide angle reflecton and refraction solutions through incorrectly assumed values for the average vertical velocity of sound in water, $v_{\rm v}$, and the horizontal velocity, $v_{\rm h}$. Both velocities are input parameters to the reduction programs. In LINFT, the refraction velocity is determined directly from the ratio of the slope of the refractor to the slope of the direct arrival line. Therefore, the accuracy of the final refraction velocity results is directly proportional to the accuracy with which the horizontal velocity of sound is known. The horizontal velocity in Figure 14 is 1485 m/s, which is the default value in the digitizing programs. A variation of $^{\pm}$ 10 m/s is less than a 1% error, but in other areas and at another time of year, the variation may be much greater.

The wide angle reflection program SLOWI, requires both v_h and v_v as input. However, these two variables are not independent. The program actually solves for v_h , based on the input value for v_v and the seafloor depth. The input value of v_h is used as a trial solution to the interative process. Therefore, it is critical to provide SLOWI with a reliable value for the average vertical of sound as some function of depth, f(z). For a given depth of water, z_1 , the average vertical velocity is determined by integrating the curve f(z) from 0 to z_1 :

$$\overline{\nabla}_{V} = \frac{1}{Z_{1}} \int_{0}^{Z_{1}} f(z) dz$$

This integration can be done numerically. If we apply this technique to Figure 14 from 0 to 1100 meters, we arrive at a value for $v_{_{\mbox{\scriptsize V}}}$ of approximately

1472 m/s. The default value provided for v_v by the digitizing program is 1500 m/s, a difference of 2%. In other areas this difference could be greater. Since v_v is required for the determination of v_h , this error would effect both the solutions for reflection velocities, as well as the depth to the seafloor.

These problems illustrate the importance of having some independent information regarding the variation of velocity with depth. One of the most valuable tools is an XBT, or expendable bathythermograph. This is an expendable thermistor which is dropped into the water, attached to the ship by a slender copper wire. As the thermistor drops through the water, the resistance is measured and converted to temperature. Thus, a temperature-depth profile is obtained. The variation of velocity of sound is very nearly directly proportional to the temperature of the water, so this measurement may provide a very close approximation to the variation of velocity with depth. With underway multichannel operations, XBT's cannot be used. Therefore, tables similar to Mathew's and the velocity profile atlas must be relied upon. The S.P. Lee is also equipped with a velocimeter, which determines the horizontal velocity of water near the sea surface, and this value should be recorded in the logs during a sonomodel station. Any remarkable variation from the expected value (1485 m/s) should be investigated carefully noted.

APPENDIX C: Shipboard interpretation of Refraction and wide angle reflection data


Preliminary analysis of both refraction and reflection data can be done with reasonable accuracy (10-15%) using a hand calculator. The objective of these analyses is to determine velocities (refraction and interval) and layer thicknesses. The two following sections present all the equations necessary to achieve this goal. For brevity, the more complicated equations are given without derivation.

REFRACTION DATA

Interpretation of refraction data from shallow water areas is usually a straightforward process of:

- 1. identifying each successively deeper refracting horizon, which almost always occurs as a 'first arrival' with a distinct change in slope (see Fig. C.1);
- 2. determining the refraction velocity from the slope of the refractor (eq. 1);
- 3. computing the depth to the refractor at vertical incidence (eq. 2 and 3).

In deep water areas, the refraction data is often complicated by 'second arrival' refractions that are difficult, but important, to identify (see R_1 , Fig. C.2).







FIG. C.1

The velocity of the refractor (V_{REF}) can be determined from (assuming flat-lying layers):

$$V_{REF} = \frac{\Delta x}{\Delta T} = \frac{V_{w} T_{D2} - V_{w} T_{D1}}{T_{R2} - T_{R1}}$$

$$V_{REF} = \frac{1500 (T_{D2} - T_{D1})}{(T_{R2} - T_{R1})}$$
 (Eq. 1)


VREF in meters/sec



The depth to each refracting horizon involves a somewhat cumbersome set of calculations in which the thickness of the last penetrated layer (Z_{n-1}) is determined in terms of the thicknesses and velocities of the overlying layers. The generalized equation for determining the thickness

of the (n-1)th layer is: (see Nettleton, 1940, p. 254)

$$\frac{1}{2\sqrt{V_{n}^{2}-V_{n-1}^{2}}} \left[\frac{2z_{0}\sqrt{V_{n}^{2}-V_{0}^{2}}}{\sqrt{V_{0}V_{n}}} - \frac{2z_{1}\sqrt{V_{n}^{2}-V_{1}^{2}}}{\sqrt{V_{1}V_{n}}} \cdots - \frac{2z_{n-2}\sqrt{V_{n}^{2}-V_{n-2}^{2}}}{\sqrt{V_{n-2}V_{n}}} \right] (Eq. 2)$$



T_{in} is the intercept time for the n layer (see Fig. C.3)

V...V are refraction velocities.

The thickness of the first four layers, in a format that is readily programable on a hand calculator is:

$$Z_{0} = \frac{V_{0}}{\sqrt{V_{1}^{2} - V_{0}^{2}}} \left(\frac{T_{1}V_{1}}{2}\right)$$

$$Z_{1} = \frac{V_{1}}{\sqrt{V_{2}^{2} - V_{1}^{2}}} \left(\frac{T_{2}V_{2}}{2} - \frac{Z_{0}\sqrt{V_{2}^{2} - V_{0}^{2}}}{V_{0}}\right)$$

$$Z_{2} = \frac{V_{2}}{\sqrt{V_{3}^{2} - V_{2}^{2}}} \left(\frac{T_{3}V_{3}}{2} - \frac{Z_{0}\sqrt{V_{3}^{2} - V_{0}^{2}}}{V_{0}} - \frac{Z_{1}\sqrt{V_{3}^{2} - V_{1}^{2}}}{V_{1}}\right)$$

$$Z_{3} = \frac{V_{3}}{\sqrt{V_{4}^{2} - V_{3}^{2}}} \left(\frac{T_{4}V_{4}}{2} - \frac{Z_{0}\sqrt{V_{4}^{2} - V_{0}^{2}}}{V_{0}} - \frac{Z_{1}\sqrt{V_{4}^{2} - V_{1}^{2}}}{V_{1}} - \frac{Z_{2}\sqrt{V_{4}^{2} - V_{2}^{2}}}{V_{2}}\right)$$

The depth to the top of the n layer is given by:

$$\sum_{n} = \sum_{i=0}^{n-1} \overline{Z}_{i}$$
(Eq. 3)

REFLECTION DATA

Constructing velocity versus depth sections from reflection data is generally done by:

determining the interval velocities between each of the prominent reflecting horizons (see steps I and II below);

2. converting the vertical incidence reflection times to depths using the interval velocities (eq. 11).

Procedure:

- I. Determine the RMS velocities for each of the reflecting horizons using either (A) or (B):
 - (A). the Tangent method (eq. 7 or 8);
 - (B). the two point method (eq. 9).
- II. Then use Dix's equation to compute the interval velocity between two reflecting horizons (eq. 10).




FIG. C.5 $T^{2} = T_{D}^{2} + \frac{x^{2}}{V_{rms}}^{2}$ $= \left(\frac{27}{V_{rms}}\right)^{2} + \left(\frac{x}{V_{rms}}\right)^{2}$ (Eq. 4)

$$\left(\top V_{\text{rmS}} \right)^2 = \left(2 \Xi \right)^2 + \chi^2 \qquad \text{(Eq. 5)}$$

I.A. RMS Velocity - Tangent method

Differentiate the travel time equation (5) with respect to ${\bf x}$ and at a constant depth ${\bf z}$:

$$2\sqrt{\frac{2}{rms}} \frac{\Delta T}{\Delta x} = 2X \qquad \sqrt{\frac{2}{rms}} = \left(\frac{x}{T(\frac{\Delta T}{\Delta x})}\right)^{\frac{1}{2}}$$
 (Eq. 6)

Where $\frac{\Delta T}{\Delta x}$ is the slope of the travel time equation.

All terms in equations (2) and (6) can easily be determined from the sonobuoy record. The quickest method (see Fig. C.6) is to look for a region of good data along the reflection hyperbola of interest and to draw a tangent line to the hyperbola. The tangent point (x_1, T_{R1}) , the direct arrival time (x_1, T_{D1}) , and the slope of the line $(\Delta T/\Delta X)$ are used to determine the RMS velocity from equation (7).

$$V_{RMS} = \left(\frac{1500 \, T_{DI}}{T_{RI} \left(\frac{T_{RI} - T_{I}}{1500 T_{DI}}\right)}\right)^{\frac{1}{2}}$$

$$V_{RMS} = \frac{1500 \, T_{D1}}{\left(T_{R1} \left(T_{R1} - T_{I}\right)\right)^{\frac{1}{2}}} \quad (Eq. 7)$$

RMS VELOCITY IN METERS/SEC

$$x = 1500 T_{DI}$$

$$\Delta T_{\Delta x} = \left(T_{RI} - T_{I}\right) / 1500 T_{DI}$$




FIG. C.6

If the refraction velocity for a specific reflecting horizon has already been determined, then a simplified version of equation (6) can be used. Since refractions are always tangent to the reflection hyperbola, at the critical distance point (x_c, T_{RC}) , the equation for RMS velocity

becomes (see Fig. C.5):
$$V_{RMS} = \left(\frac{X_{C}}{T_{RC}(V_{REF})}\right)^{\frac{1}{2}}$$

$$V_{RMS} = \left(\frac{1500 T_{DC} V_{REF}}{T_{RC}}\right)^{\frac{1}{2}}$$

RMS VELOCITY IN meters/sec

$$\frac{\Delta T}{\Delta x} = \frac{1}{V_{REF}}$$

$$X_{c} \approx 1500 \, T_{DC}$$

$$V_{REF} \text{ is the refraction velocity in meters/sec.}$$
(Eq. 8)

I.B. RMS Velocity - Two point method

Using the travel time equation (4) for two different points (x_1, T_{R1}) and (x_2, T_{R2}) (see figure C.5) and eliminating the common T_0^2 term:

$$T_{RI}^{2} - \frac{\chi_{I}^{2}}{V_{rms}^{2}} = T_{R2}^{2} - \frac{\chi_{z}^{2}}{V_{rms}^{2}}$$

$$V_{rms} = \left(\frac{\chi_{z}^{2} - \chi_{I}^{2}}{T_{R2}^{2} - T_{RI}^{2}}\right)^{1/2}$$

$$\chi_{z} = 1500 T_{D2}$$


$$V_{rms} = 1500 \left(\frac{T_{D2}^{2} - T_{DI}^{2}}{T_{R2}^{2} - T_{RI}^{2}}\right)^{1/2}$$

II. Interval Velocity - Dix Equation

From Dix (1955), the interval velocity when $x \ll z$ is approximated by:

$$V_{|NT} = \left(\frac{V_2^2 T_2 - V_1^2 T_1}{T_2 - T_1}\right)^{\frac{1}{2}}$$
 (Eq. 10)

where V_1 and V_2 are RMS velocities and T_1 and T_2 are zero offset (vertical incidence) times (see figure C.7).



Once the interval velocities are known, the depths to each of the reflecting horizons can be determined from the vertical incidence reflection times. The depth (D) to the top of the N^{th} layer is:

where T_{vi} is the vertical incidence reflection time (2-way) within the i^{th} layer (read from the reflection profile) and V_i is the interval velocity of the i^{th} layer.

APPENDIX D: Reflection ray tracing theory

In these derivations, the following notation is used:


- 1. All distances in lower case letters
- 2. All times in upper case letters
- x horizontal distance; source receiver separation
- h₁ thickness of layer 1 (here the water layer)
- h₂ thickness of layer 2
- r₁ length of reflection path (2 way) to first reflecting horizon (here the water sediment interface)
- ${\bf r}_2$ length of reflection path to second reflecting horizon
- T₁ reflection time (2 way) to first reflecting horizon (here the water-sediment interface)
- $T_1(0)$ minimum reflection time to first reflecting horizon
- $\mathtt{T}_1^{\, \prime}$ reduced reflection times for \mathtt{T}_1
- ${\rm T_{\rm 2}}$ reflection time (2 way) to second reflecting horizon
- $T_{2}(0)$ minimum reflection time to second reflecting horizon
- $\mathtt{T}_2^{\:\raisebox{3.5pt}{\text{\circle*{1.5}}}}$ reduced reflection times for \mathtt{T}_2
- T_d time of direct water arrival
- \mathbf{T}_{con} correction term to produce reduced times
- \boldsymbol{V}_{h} horizontal velocity of propagation of sound at the water surface
- V_1 interval velocity of layer 1 (here the water layer)
- ${\rm V_2}$ interval velocity of layer 2
- V_{a2} assumed interval velocity of layer 2

 ω_1 - slope of first reflecting horizon ω_2 - slope of second reflecting horizon (with respect to ω_1) ω_{a2} - assumed slope of second reflecting horizon

$$D_1 - T_{d1}$$

$$D_2 - T_{d2}$$

I. Pythagorean Theorem for flat lying layers



By the Pythagorean Theorem:

$$\left(\frac{1}{2}x\right)^2 + \left(h_i\right)^2 = \left(\frac{1}{2}T_iV_i\right)^2 \tag{1}$$

$$\chi^2 + (2h_i)^2 = (T_i v_i)^2$$
 (2)

$$T_i^2 = (\frac{1}{v_i^2})_{X^2} + (\frac{2h_i}{v_i})^2$$
 (3)

This equation (3) is linear in x^2 and T^2 . Therefore, a line fitted by least squares to the x^2 - T^2 data points will have a slope inversely proportional to the square of the interval velocity (v_1)

of the layer. The intercept of this line is the square of the minimum reflection time ($T_1(0)$) to the reflecting interface. From $T_1(0)$ and v_1 , the true depth to the interface can be determined.

II. Image method (law of cosines) for dipping interfaces

Using the image method to solve the wide angle reflection equation with dipping reflector interfaces (see Figure D.2):

By the law of cosines

$$r_i^2 = x^2 + (2h_i)^2 - 2(x)(2h_i)\cos(x)$$
where $x = 90 - \omega_1$

Therefore

$$r_1^2 = x^2 + (2h_1)^2 - 4xh_1\cos(90 - \omega_1)$$

= $x^2 + (2h_1)^2 - 4xh_1\sin\omega_1$ (5)

Expressing the distances in terms of time and velocity:

$$\left(T_{i}V_{i}\right)^{2} = \left(T_{d}V_{h}\right)^{2} + \left(T_{i}(0)V_{i}\right)^{2} - 2\left(T_{d}V_{h}\right)\left(T_{i}(0)V_{i}\right)\sin\omega_{i}$$

Finally, the equation for travel times for dipping reflectors is:

$$T_{i}^{2} = T_{d}^{2} \left(v_{h} / v_{i} \right)^{2} + T_{i}(0)^{2} - 2T_{d} T_{i}(0) \left(v_{h} / v_{i} \right) \sin \omega_{i}$$
 (6)




FIGURE D.2

(From Knott & Hoskins, p. 2-4)

- III. SLOWI (SLOping WIde angle) reflection method
 - A. First (water) layer: Computation to iteratively $\label{eq:computation} \text{determine a reliable value for the horizontal water}$ $\text{velocity } v_h$
 - 1. Assume that \mathbf{T}_1 , the total travel time, \mathbf{w}_1 , the slope of the first reflecting interface, and \mathbf{v}_1 , the interval velocity of the first layer, are known.
 - 2. Find the minimum reflection time, T₁(0):
 If the T/x curve starts close to the origin,
 (x=0), T₁(0) is determined by a fourth order least squares fit to the time distance curve:

$$T_1 = T_1(0) + C_1T_d + C_2T_d^2 + C_3T_d^3 + C_4T_d^4$$
 (7)
where $T_d = x/v_h$

If the T/x curve starts beyond the origin (x>0), $T_1(0)$ is found by a linear least squares fit to:

$$T_1^2 = T_1(0)^2 + C_1(x/v_h)^2 = T_1(0)^2 + C_1T_d^2$$
 (8)

From $T_1(0)$, the minimum thickness, h_1 , is found.

From the law of cosines solution (see equation 6, Part II):

$$T_{i}^{2} = T_{d}^{2} \left(\frac{v_{h}}{v_{i}}\right)^{2} + T_{i}(0)^{2} - 2T_{d}T_{i}(0)\frac{v_{h}}{v_{i}} \sin \omega_{i}$$
 (9)

Reduced times, T_1 , are calculated from equation 9 by removing the normal incidence travel time within the layer, $T_1(0)$, as well as the difference in travel

time resulting from the slope of the interface:

$$T_1^2 = T_1^2 - T_{cont}$$

where

$$T_{conl} = T_1(0)^2 - 2T_d T_1(0) \frac{V_h}{V_i} \sin \omega_i$$

or

$$T_1^2 = T_d^2 \frac{V_h^2}{V_l^2}$$
 (10)

This reduced travel time squared - distance squared equation is fit by linear least squares to determine v_h . (This value for v_h is compared to the input value for v_h and if the difference is large, another iteration is made from step 3 using the corrected value of v_h).

B. Second layer

- 1. Assume that T_2 , the travel time to interface 2, ω_1 , the slope of the first reflecting interface, and v_1 , the interval velocity of the first layer, are known. Also, the apparent slope, ω_{a2} , determined from an assumed interval velocity, v_{a2} , for the second layer, must be known.
- 2. Determine by least squares the fourth order polynomial:

$$T_2 = T_2(0) + C_1T_d + C_2T_d^2 + C_3T_d^3 + C_4T_d^4$$

where $T_d = \frac{x}{v_h}$

- 3. Find $T_2(0)$, the normal incidence reflection time to the second interface, in the same manner as for the first layer (see section D.2), be either linear least squares or fourth order polynomial fit. Calculate h_2 from $T_2(0)$ and the assumed velocity v_{a2} .
- 4. Recall the ray parameter, p:

$$\rho = \left(\sin \theta_i\right) / V_i \tag{11}$$

where $\boldsymbol{\theta}_{\text{i}}$ is the emergent angle of the ray for layer i and $\boldsymbol{v}_{\text{i}}$ is the interval velocity for the layer.

The ray parameter may be expressed as the derivation of the time - distance curve (see Officer, 1958, pp. 48 - 52):

$$p = \frac{dT}{dx} \tag{12}$$

Therefore, by differentiating the fourth order polynomial for T_2 above and substituting into equation (11) and (12):

$$\sin\left(\beta_1 - \omega_1\right) = V_1 \frac{dT_2}{dx} \tag{13}$$

where ($\beta_1 - \omega_1$) is the emergent angle (see Figure D.3).

5. From Snell's Law and reflection geometry, we see from equations at the bottom of Fig. D.4, that the incident angle, β_1' can be calculated from the emergence angle ($\beta_1 \rightarrow \omega_1$) for each value of x.




FIGURE D.3

- 6. Knowing the incident and emergence angles, compute the one way travel times $T_{AA'}$, $T_{BB'}$, $T_{A'H'}$, and the distance A'B' .
- 7. With these travel times, "strip off" the upper layer and determine the travel time in the second layer alone:

$$T_{A'C'B'} = T_{AA'C'B'B} - T_{AA'} - T_{B'B}$$
 (14)

8. This now is the one layer case. As before (Eq. 9), the travel times are expressed:

$$(T_2 V_{a2})^2 = (A'B')^2 + (2T_{A'H'} V_{a2})^2$$

- $2(A'B')(2T_{A'H'} V_{a2}) \sin \omega_{a2}$

$$T_{2}^{2} = (A'B'/v_{2})^{2} + (2T_{A'A'})^{2} - \frac{2(A'B')(2T_{A'A'})}{v_{2}} \sin \omega_{a2}$$
(15)

The distance A'B' is known explicitly, and therefore it is not necessary to calculate a horizontal velocity along the interface as was done for the first layer.

9. These squared travel times are reduced by:

$$T_2'^2 = T_2^2 - T_{con}^2 \tag{16}$$

where

$$T_{con2}^2 = (2T_{A'H'})^2 - \frac{2(A'B')(2T_{A'H'})}{V_{a2}^2} \sin \omega_{a2}$$

10. Any negative travel times are eliminated, and a least squares fit made to


$$T_2^{'2} = \frac{(A'B')^2}{V_2^2} \tag{17}$$

This fit provides a corrected value of \mathbf{v}_{γ} .

11. The apparent angle, $\boldsymbol{\omega}_{\text{a}2}$, is corrected according to

$$\tan \omega_2 = \tan \omega_{a2} \cdot \frac{v_2}{v_{a2}} \tag{18}$$

12. With new values for ω_2 and v_2 , the program returns to step 3 and repeats. The same sequence of steps is then followed for each subsequent layer.



$$\frac{\sin \beta_{1}'}{\sin \beta_{2}'} = \frac{V_{1}}{V_{2}}$$

$$\frac{\sin \beta_{1}}{\sin \beta_{2}} = \frac{V_{1}}{V_{2}}$$

$$\beta_{2} = \arcsin \left(\frac{V_{2}}{V_{1}} \sin \beta_{1}\right)$$

$$\beta_{2}' = \beta_{2} + 2N = \beta_{2} + 2\omega_{a2}$$

$$\beta_{1}' = \arcsin \left(\frac{V_{1}}{V_{2}} \sin \beta_{2}'\right) = \arcsin \left(\frac{V_{1}}{V_{2}} \sin \left(\beta_{2} + 2\omega_{a2}\right)\right)$$

$$\beta_{1}' = \arcsin \left(\frac{V_{1}}{V_{2}} \sin \left(\frac{V_{1}}{V_{2}} \sin \beta_{1}\right) + 2\omega_{a2}\right]$$

Appendix E

Procedure outline for digitizing and processing sonobuoy records

This appendix provides a suggested procedure for digitizing and processing sonobuoy records, from initial preparation of the record, through digitizing, reduction and interpretation.

Procedure outline for digitizing and processing sonobuoy records

- I. Preparation of records prior to digitizing
 - 1. Cut records and paste on a stable backing
 - 2. Overlay record with "cured" mylar acetate overlay
 - 3. Draw time lines and other reference points on mylar
 - 4. Choose refractions and/or reflections and trace on the mylar

II. Refraction data

1. Load refraction digitizing program and execute

The refraction digitizing program is interactive, and request all necessary information from the user. The digitizing is carried out one refraction trace at a time, and each data point requires two time picks: a direct time and a refraction time. Upon command, the program will automatically write an output data set to magnetic tape.

- 2. Transfer data set to MULTICS computer
- 3. Execute preliminary LINFT program

LINFT performs a linear fit (least squares) to the refraction data and prints out velocity and depth solutions.

- 4. Determine the slopes of refracting surfaces from vertical incidence seismic reflection records, using the velocity solutions from preliminary LINFT.
- 5. Execute LINFT program again with slope corrections
- 6. Edit refraction results for spurious refractions and other errors
- 7. Execute final LINFT with corrected data set if necessary

III. Wide angle reflection data

- 1. Load reflection digitizing program and execute
 The reflection digitizing program is interactive, and
 requests all necessary information from the user. The
 order of digitizing data points is a direct time followed
 by "n" reflection times, where "n" is the number of ref lection layers. The reflection digitizing program also
 provides preliminary analysis of the data in the form of
 X² T² calculations, and allows editing of the data
 points before writing an output data set to magnetic tape.
 Therefore, the suggested order within the digitizing program is:
 - a. Digitize the reflection recorde
 - b. Execute X² T² program
 - c. Execute the Edit program to correct bad picks
 - d. Execute $X^2 T^2$ again with edited data set
 - e. Execute the Edit program again, if necessary
 - f. From Edit section, write an output data set to tape
- 2. Transfer data set to MULTICS computer
- Determine apparent slopes of reflectors from vertical incidence seismic reflection records, using an assumed velocity of seawater for the sediments.
- 4. Execute SLOWI with program with assumed slope correction SLOWI performs a sophisticated variation of $X^2 T^2$ analysis on the reflections and prints out velocity and depth solutions. The program also calculates true dips of the reflectors from the calculated velocities
- 5. Edit final SLOWI results
- 6. Execute SLOWI again with edited data set, if necessary

IV. Interpretation

- 1. Compile all refraction and reflection results
- 2. Determine the velocity depth relationship

The velocity - depth relationship may be determined by a program that performs a polynomial fit to the sonobuoy results. Other relationships may be possible as well

- 3. Correct final reflection results according to the velocity depth curve (optional). (Refer to Houtz et.al, 1968, pp2631-2632)
- 4. Construct velocity sections from the refraction results, and separate sections from the reflection results, if desired

Appendix F

Corrections to the reduction results

This appendix contains two sections:

- 1. Corrections for hydrophone lower
- 2. Corrections for dipping interfaces

The first part of this appendix describes correction factors which are necessitated by the hydrophone suspension system, and by the delayed release timer which activates the suspension.

The second section describes the manner in which sloping reflection and refraction interfaces are corrected for in the reduction programs. The digitizing programs do not require or accept slope corrections, and therefore these corrections must be included in the data sets after they have been transferred to MULTICS.

Correction for depth of the hydrophone

During normal operations, the sonobuoy hydrophone drops to depths of 60 to 300 feet beneath the sea surface as soon as the buoy is placed in the water. The error in the reflection times that is introduced by the depth of the hydrophone is corrected in program SLOWI, if the final hydrophone depth is input to the program and the "correct E/S depth" option is chosen.

If a sonobuoy station is conducted during multichannel seismic operations, it is necessary to delay the deployment of the sonobuoy hydrophone for 20 minutes, the time required for the buoy to clear the far end of the multichannel hydrophone cable. The delayed drop, from near the sea surface to depths of 60 to 240 feet, introduces two problems in the sonobuoy interpretation. First, the sudden increase in the distance from the hydrophone to the sea surface changes the general configuration of the reflectors in the sonobuoy record by increasing the time between the primary reflected arrival and the secondary sea surface reflection (from 4 msec to 48 msec with a 120 foot drop) (See also App. B). Secondly, the time difference resulting from the shortened travel path introduces an abrupt vertical shift in the reflectors (-25 m sec with a 120 foot depth) at the point when the phones drop. The first problem of reflector configuration can only be compensated for subjectively through the interpreter's ability to accurately follow each of the primary reflection arrivals across the sonobuoy record. However, an explicit correction for the abrupt vertical shift in the reflectors can be made during the data reduction after the reflectors are digitized in their shifted configuration. The program determines the time of the hydrophone release by asking the interpreter to mark the direct time on the trace recorder where the release occurred. Then, based on the final

hydrophone depth (input earlier), a correction value is calculated and subtracted from all reflection times along prior traces. The effect is to change the data to appear as if the hydrophone had released immediately. SLOWI then corrects all reflection times for the hydrophone depth. This "delayed hydrophone release correction" is an option with the SLOWI digitizing program, and is usually called after digitizing the record, but before the $X^2 - T^2$ calculations. However, the correction can be called from other parts of the digitizing program. Therefore, it may be desirable to calculate the $X^2 - T^2$ plot without the correction, check the residual values, then add the correction to see whether the solutions improve. The option to add the correction can also be used to remove the same correction if it is determined that the original data is better. Often, the effect of the delayed release will be very noticeable as a discontinuity on the X^2-T^2 plot.

Slope Corrections

Slope corrections are important for both the wide angle reflection and refraction data to insure good velocity and thickness values. The slope information usually comes either from the dip of the reflectors in the vertical incidence seismic data recorded during the sonobuoy station or from the dip of refraction interfaces seen on a series of back-to-back sonobuoy stations. In both reduction programs LINFT (refraction data) and SLOWI (wide angle reflection data), input dips are relative dips (i.e. the dip for a deeper layer is calculated with respect to the layer directly above it). For example, if two layers are dipping parallel to one another (absolute dip = A), then the relative dip of the shallower layer is A, while that of the deeper layer is O. The sign convention is the same for both programs and is that upward relative dip in the direction of travel (updip from the buoy) is

positive, while downdip is negative (refer to Figure 14). All dip calculations presuppose that the velocity of the overlying layer is-known, whereas usually it is not known. Hence, a trial velocity must be assumed to calculate the dips from the seismic reflection profiles. LINFT and SLOWI differ significantly in the way they use the trial velocities. Therefore, the dips should be determined specifically for the program that is to be used.

In calculating slopes for SLOWI a velocity of 1.5 km/sec (water velocity) must be assumed for the overlying water and sediment layer. SLOWI will iteratively correct the input slopes as better values for the velocity are obtained. The correction is:

$$tan W = \frac{V}{V_0} tan W_a$$

where W and v are corrected slope and velocity and W_a and v_a are input slope and assumed velocity. The final values for the relative slopes of the layers and the slope corrected velocities are given in a summary table.

LINFT, however, uses the correct relative dips, as they would be output from SLOWI. Because there are often no SLOWI solutions for a sonobuoy, or no reflections from a refracting layer, LINFT must be executed twice: the first time with zero slopes to determine trial velocities and a second time with estimated relative dips calculated from the trial velocities. If the dip corrections are large, the velocities may change enough to warrant a third run with recalculated dips.

It is usually necessary to calculate dip for SLOWI and LINFT independently even when good output dips from SLOWI are available.

Reflections are observed over a much shorter range (8 km distance in 3000 m of water) than are refractions, (12-30 km distance) and, therefore, are affected by layer dips only in the first part of the sonobuoy record.

Dip corrections are not included in the data sets output by the digitizing programs, and therefore, must be entered into the data set through the text editor.




Figure 14 Convention used by SLOWI and LINFT to specify slopes of interfaces.

Appendix G

Examples of digitizing programs

The following appendix contains complete examples of both LINDIGIT and SLODIGIT, the Tektronix programs for digitizing refractions and reflections. The examples illustrate the complete process for digitizing the refractions and reflections from a single sonobuoy station, but do not explore all the possible options and variations that are available within the programs.

Either digitizing program is located and invoked by means of the "AUTOLOAD" function. To use, simply insert the program tape into the 4051 and press "AUTOLOAD". Much of the program is controlled through the user definable keys (UD #), and occasionally by the FLAG buttons on the cross hair cursor. When these buttons are us a note is included in the margin of the example listing.

The refraction record is a rather straightforward record of a deep water sonobuoy with both sedimentary and sub-crustal refractors. The option to calculate a seafloor refractor (velocity = 1.55 km/s) is requested, and five points per refractor are picked.

The example used for the reflection digitizing is from the same station as the refraction example. However, the reflection digitizing must be done from two records. The direct times are picked from the 0-8 second record, while the reflection times are picked from a delayed 6 second record.

SONOBUOY DIGITIZING PROGRAMS

WHICH TYPE OF RECORDS DO YOU MISH TO DIGITIZE?

1. WIDE ANGLE REFLECTIONS 2. REFRACTIONS

(respond with correct number and type RETURN)

107

ZING		1.487	/sec)	9	k?
REFRACTION DIGITIZING	76-BS	velocity (in km/sec) km/sec)	sound velocity (in km/sec)	of layers to be digitized:	nts per layer do you wish to pick? It = 5)
LINDIGIT	ig for sonobuoy ST D LEES-76-BS F sonobuoy run	ital sound it = 1.485	se vertical sound lit = 1.5 km/sec>		ints per layer to
PROGRAM	Enter heading SONOBUOY TEST Enter date of 1 APRIL 1978	Enter horizor (defaul	Enter average (defau)	Enter number	How many point (defaul

<return>

Position sonobuoy on digitizing tablet ****

Set the origin of the sonobuoy record.

Determine the scaling factor:

Mark the time tick at the bottom of the record.

How many seconds long is the record? 8

DO YOU WISH TO CHECK THE TIME REFERENCE MARKS?

HERE

10 CHECK OUT SATISFIED, PR 10 RESET THE 8.000 1.600 2.482 3.201 8.801 7.999 10.399 10.401

DOES THE RECORD HAVE A DEEP WATER DELAY? N

MARK THE DIRECT ARRIVAL WHERE IT INTERCEPTS THE FIRST RECORDER TRACE (x=0).

MARK THE SEAFLOOR REFLECTOR AT THE FIRST TRACE (x=0).

DO YOU HISH TO INPUT A SEAFLOOR TINE?

DO YOU WISH TO ADD AN ASSUMED SEAFLOOR REFRACTOR?

WHAT IS THE SEAFLOOR VELOCITY: (default = 1.55 km/s)

くていけつとく

START DIGITIZING THE DATA POINTS

Pick first the direct time, D(1), and then the refractor time, R(1), for each data point. 10 picks must be made for each refractor.

14.390 10.888 12.161 10.999 11.670 14.048 14.080 12.518 15.463 13.876 10.594 11.818 10.829 11.548 13.410 10.206 13.223 11.870 14.843 13.386 10.128 11.487 10.632 11.305 9.290 12.393 11.325 13.732 14.084 12.983 9.974 111.214 111.194 111.746 12.198 8.993 11.712 10.964 13.256 12.461 9.798 11.028 110.485 11.657 11.646 8.659 11.229 18.539 12.644

DO YOU WISH TO SEE A LINFT FORMATTED DATA LIST?

LINFT FORMATTED OUTPUT LIST

100.100 100.100 100.100 100.00
9.033 13.838 11.818 11.529 12.039
8.185 13.418 10.286 13.223 11.878 14.843
7.119 13.386 10.128 11.487 10.682 11.385
6.185 12.718 9.298 12.393 11.325 13.732
5.200 2.903 9.974 11.214 11.194
4.105 2.198 1 8.993 1 11.712 1 13.258 1
3.282 12.461 9.798 11.028 10.485 11.611
2.185 11.646 8.659 11.229 10.539

10.956 10.888 110.888 110.999 111.670

DO YOU WISH TO WRITE THE OUTPUT TO TAPE?

INSERT THE OBJECT TAPE IN THE TAPE READER.

WHICH TAPE FILE DO YOU WISH TO WRITE TO?

THE HEADER OF THAT FILE READS:

M

DO YOU HISH TO MARK THIS FILE?

ARE YOU SURE ?

SONOBUOY DIGITIZING PROGRAMS

WHICH TYPE OF RECORDS DO YOU WISH TO DIGITIZE?

1. WIDE ANGLE REFLECTIONS
2. REFRACTIONS

(respond with correct number and type RETURN)

115

PROGRAM SLODIGIT REFLECTION DIGITIZING

Z Do you wish to recover data from tape - (please answer EyJ or EnJ):

Enter heading for sonobuoy SONOBUOY TEST D LEE5-76-BS

Enter date of sonobuoy run 1 APRIL 1978 Enter horizontal sound velocity (in km/sec) (default = 1.485 km/s)

1.487

Enter average vertical sound velocity (in km/sec): (default = 1.500 km/s)

Enter hydrophone depth lower (in feet): 128

Enter number of layers to be digitized: (A maximum of 12 is allowed.)

Ø

< return >

•

ORDER ARE YOU CAN HERE MAKE ANY NUMBER OF DATA PICKS IN TO CHECK OUT YOUR REFERENCE SYSTEM. WHEN YOU SATISFIED, PRESS FLAG NUMBER 1 ON THE CURSOR.

IF YOU WISH TO RESET ORIGIN, PRESS FLAG NUMBER 2

Mark the point on the direct trace when the phones dropped.

< flag number
1 on cursor >

MARK THE SEAFLOOR ARRIUAL ON THE FIRST RECORD

START DIGITIZING DIRECT TIMES

(A MAXIMUM OF 36 ARE ALLOWED)

To stop digitizing, press u.d. key #4 and digitize any point.

œ

2:45 4 "R" indicates correction 7 20 PLACE SECOND RECORD ON THE DIGITIZING TABLET.

Set the origin of the sonobuoy record.

Determine the scaling factor:

Mark the time tick at the bottom of the record.

How many seconds long is the record:

9

DO YOU WISH TO CHECK THE TIME REFERENCE MARKS:

YOU CAN HERE MAKE ANY NUMBER OF DATA PICKS IN ORDER TO CHECK OUT YOUR REFERENCE SYSTEM. WHEN YOU ARE SATISFIED, PRESS FLAG NUMBER 1 ON THE CURSOR.

IF YOU WISH TO RESET ORIGIN, PRESS FLAG NUMBER 2

6.683 1.282 1.885 6.681 8.599

< flag number
2 on eursor >

Set the origin of the sonobuoy record.

Determine the scaling factor:

Mark the time tick at the bottom of the record.

How many seconds long is the record: 6

DO YOU MISH TO CHECK THE TIME REFERENCE MARKS:

V 1 00 correction with < "R" indicates a

YOU CAN HERE MAKE ANY NUMBER OF DATA PICKS IN ORDER TO CHECK OUT YOUR REFERENCE SYSTEM. WHEN YOU ARE SATISFIED, PRESS FLAG NUMBER 1 ON THE CURSOR.

2 IF YOU WISH TO RESET ORIGIN, PRESS FLAG NUMBER

3.6821 1.2892 1.8882 3.688

MARK THE SEAFLOOR ARRIVAL ON THE SECOND RECORD

1 on cursor > < flag number

START DIGITIZING REFLECTION TIMES When finished, hit u.d. key #4 and touch the cursor.

	8.012	8.893	8,132	
7.948 7.967 7.989	4 W	35.	ימישי	20
7.407 7.426 7.439	7.83.58	40.5	,	. 73%
6.949 6.965 6.978	69	. 822 . 822 	6.6	360
6.278 6.388 6.339	10.4 10.4	4.00	969	7.1
5.000 5.000	948	201	22.	. 4 . 4
5.688 5.645 5.691	88	92.	900	74
245 245 286 286 286	58	67	1200	91.
5,108 5,151	32	₩ 4 m	າເກີດ ການກາ	. 29
6.188 6.756	4 m	α .σ	10141	いい

		©
3222	いいいい 444	88888888888888888888888888888888888888
55.28 5.22.88	@ <u>0</u> 00000000	88.08218 8.136 8.136 8.238 2.238
2000 2000 2000 2000	480.000 480.000 480.000	7.747 7.747 7.803 7.862 7.862
200 200 200 200 200 200 200 200 200 200	000000	7.7.7.7.7.7.7.7.7.7.7.7.7.7.7.7.7.7.7.
4 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	981 861 861	6.980 7.980 7.948 7.988 7.123
0400 0400	244NN00 222222222	6.939 6.831 6.919 6.919 6.919
97 91 96 18	9000044	6.5333 6.5336 6.626 6.70 6.710
7-889 6-189	2001-1000 201-1000	66.00 6.00

SUGGESTED PROCEDURE:

1.	MAKE COPY OF INPUT PARAMETERS	(U.D. KEY #5)
2.	MAKE COPY OF DIGITIZED PICKS	#15
'n	SAUE RAM DATA ON TAPE	#18
4.	ADD HYDROPHONE DELAYED RELEASE CORRECTION AND GO TO X2 - T2	#12
Ö		
4.	GO DIRECTLY TO X2 - T2	#11

INPUT PARAMETER LIST

SONOBUOY TEST D LEES-76-BS 1 APRIL 1978 Horizontal sound velocity in water = 1.487 km/sec Average vertical sound velocity = 1.500 km/sec

Hydrophone depth = 120.0 feet

Water depth≈ 3912.1 meters

Conversion factor is 0.016684 sec/millineter

Delta: time zero correction factor is -0.1084 sec

Hydrophones dropped at a direct time of 2.384 sec

8 layers were picked

38 traces were picked

DATA PICKS WERE FROM TWO SEPARATE RECORDS

Conversion factor for second record is 0.0125235 nm/sec

Reference point on first record is 5.096 sec.

0.589 sec. Reference point on second record is

Reference point time difference is 4.508 sec.

7.948	909	9	300	222	いいい	32	32	W.4.	44	4.N.	300		χ. Σ
7.487	4 R R	59	999	73	. 23 81	.84	22	.97	99	. 84	18	Sign of the control o	9
6.949 6.965 6.978	200	199	200	33	36	4.6	58	52	68	7.4	80	0000	χ α
6.278 6.388 6.339	244 2016	36.2	999	71.	833	91	95	98	13		38	W.W.	. 46
5.982 5.983 5.985	200 H	23	35	41.	58	.58	.66	.76	.91	40.	94	98	
5.699 5.645 5.691	, 88 80 80 80	96	900	.28	24 82 83	.33	43	533	.63	75	833	92.	, V
5.342 5.386 5.438	555	.72	. 25 85	.91	. 91 . 96	. 16	.28	.31	.42	.55	. 53	.71	4
5.198 5.295	38 38 38 38	248	0 0 0 4	78.	85	96.	99.	.17	233	38.	440	4 10 1	. 26
0.108 0.756 1.094	4,00	. 93	7.44 7.67	84 84	4.00 4.40	24	4.4	54	. 74 . 84	98	. 11	22.	5.

CHECK TO INSURE THAT THE 4924 IS TURNED ON AND THAT YOUR TAPE CARTRIDGE IS WRITE ENABLED

INSERT YOUR TAPE IN THE 4924

WHICH TAPE FILE DO YOU WISH TO WRITE TO? 5

IS THE FILE YOU ARE WRITING TO ALREADY MARKED? N

DO YOU WISH TO SEE DATA FROM ALL LAYERS?

Ż

DO YOU WISH TO SEE DATA FROM ANY OF THE LAYERS? N


(press return to continue)

FIT	6666	6666	6666	6.99945 6.99892	
INTERUAL UELOCITY (2) (KM/SEC)	S	1.900 2.059	2.193 2.327	4	
DEPTH (1)	3.791	4.178	4.854 5.605	6.184 7.380	
INTERCEPT TIME (SEC)	983	42	13	828	
RMS UELOCITY (KM/SEC)	52	1.00 100 100 100 100 100 100 100 100 100	58	1.783	
LAYER	(1	IW 4	ഗവ	~∞	

(1) Depth to the top of the refracter: U(rms)*intercept

(2) Interval velocity calculated from Dix' equation.

DO YOU WISH TO SEE THE X2-T2 PLOT? YES



DO YOU WANT TO SEE THE PLOT AT A DIFFERENT SCALE? N

EDITOR

PRESENTLY, THE EDITOR PERFORMS THE FOLLOWING FUNCTIONS, WHICH ARE CALLED BY THE USER DEFINABLE KEYS:

REMOUES OR REINSERTS AN ENTIRE LAYER
REMOUES OR REINSERTS AN ENTIRE TRACE
EDITS INDIDIDAL POINTS
PRINTS OUT A TABLE OF RESIDUAL VALUES
LISTS SLOWI FORMATTED OUTPUT ON THE SCREEN
WRITES SLOWI FORMATTED OUTPUT TO TAPE

TO PERFORM EDITING FUNCTIONS, PRESS THE DESIRED U.D. KEY AND FOLLOW THE DIRECTIONS.

و ا

	13	
	12	
	11	
sec 12>	18	
	Ø	
(X18##-3	œ	
S	~	111111
VALUES	9	######################################
RESIDUAL	AYER	######################################
RESI	LAY 4	0.0000410000000000000000000000000000000
LE OF	m	2 111 111 W11 10044010 W100440 8 111 111 W11 10044010 W1004400 8 1000000000000000000000000000000000000
TABLE	N	81 10W0WW4W11 1 410W14414W4114 17711100000000000000000000000000000
	•	11 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
	-	- CM 4 N O C B O B - CM 4 N O C B O B - CM 4 N O C B O B - CM 4 N O C B O B

YOU CAN EDIT POINTS ACCORDING TO TRACE NUMBER AND LAYER

TYPE THE LAYER NUMBER, TRACE NUMBER AND THE LETTER:

D - DELETE A BAD POINT

R - REPICK A POINT

I - INSERT A PREVIOUSLY DELETED POINT

Q - QUIT EDITING

LAYER, TRACE, ACTION 6, 1, D

LAYER, TRACE, ACTION 6,2,0

LAYER, TRACE, ACTION 7,23,0

LAYER, TRACE, ACTION 7,23,0

THAT POINT HAS ALREADY BEEN DELETED!

LAYER, TRACE, ACTION 7,25,0

LAYER, TRACE, ACTION 1,10

SLOPE = 0.432 INTERCEPT = 24.829 FIT = 0.99998 NUMBER OF POINTS USED = 30

ū	-9.656	0.024	9.004	9.013	9.883	. 994	. 864	0.829	. 612	9. 018	.016	. 909	. 964	. 917	.016	. e17	. 875	. 883	. 832	. 985	. 812	. 041	.014		.018
A DE	24.829	5.229	5.756	6.484	7.028	7.656	8.359	8.860	9.411	0.011	9.615	1.267	1.970	2,582	3.853	3.617	4.280	4.808	5.460	6.128	6.766	7.444	8.176	8.64	9.159
20	4.772	5.284	5,752	6.471	7.032	7.651	8.363	8.889	9,399	9.993	0.631	1.277	1.974	2,519	3.869	3,635	4.276	4.805	5.493	6,115	6.779	7.486	8.162	38.6834	9.132
a	. 885	128	. 183	. 253	.307	.366	434	. 483	.530	. 585	.643	. 791	.763	.811	.859	.988	.963	. 808	. 866	. 118	.173	.231	.286	6.3280	.364
	.000	.927	.147	.832	. 092	.546	.173	.334	0.610	2.000	3,398	4.908	6.535	7.766	9.842	9.348	1.698	3, 196	4.616	6.144	7.648	9.210	8.995	-	.161
T L	8.10 8	.756	. 694	.425	.626	.829	.031	.163	299	.438	.576	. 765	843	943	. 043	.142	.241	341	445	547	644	.743	.847	.912	9

9.0115 -0.0623 -0.0312 -0.0339 -0.062			017 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00 00.00
39.6357 40.1515 40.6995 41.1938 41.7198		86666.8	COMP 27.2 23.7 20.0 23.0 23.7 20.0 23.7 20.0 23.7 20.0 23.7 20.0 23.0 23.0 23.0 23.0 23.0 23.0 23.0
39.6472 40.6883 40.6483 41.1599 41.7135		38 FIT =	27. 156 27. 156 27. 156 28. 156 29. 454 31. 2986 32. 3584 34. 3586 34. 3586 34. 3586 35. 9775 35. 9775
6.4400 6.4400 6.4400 6.4400 6.4400		EPT = 27.2 SED = 30	######################################
34.2835 35.4778 36.7467 37.8912 39.1891		31 INTERC F POINTS U	RANGE 0.0000 2.1479 3.8329 5.0926 6.5461 12.0001 13.3985 16.5352
4.0468 4.1148 4.1858 4.2488	LAYER 2	SLOPE = 0.4. NUMBER O	018 02.1.1.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0

00000000000000000000000000000000000000		-
88888888888888888888888888888888888888		86666.0
35. 35. 36. 36. 36. 37. 39. 47. 47. 47. 47. 47. 47. 47. 47. 47. 47		868 FIT =
6.8618 6.1618 6.1618 6.3528 6.3118 6.5338 6.5338 6.6268 6.7488		EPT = 30.0 SED = 30
19.0423 20.3488 23.1061 24.5165 33.1610 35.4778 39.12 39.18912		30 INTERC F POINTS U
0.000000000000000000000000000000000000	LAYER 3	SLOPE = 6.4. NUMBER O

DIFF -0.0957 0.0021 -0.0109

COMP R2 30.0081 30.4867 30.9313

R2 29.9124 30.4887 30.9264

R 5.5776 5.6228 5.6690

RANGE 0.0000 0.9273 2.1479

DIRECT 0.1080 0.7560 1.0940

4

SLOPE = 0.418 INTERCEPT = 33.405 FIT = 0.99993 NUMBER OF POINTS USED = 30

97	0	9.056	6.833	6.923	9.941	.018	8.827	.668	. 866	.067	. 102	. 893	.114	. 895	.053	.961	. 829	. 959	. 843	6.666	. 057	0.827	. 883	6.033	. 014
X 40	3.79	4.302	5.886	5.532	6.139	6.819	7.384	7.837	8.418	9.882	9.633	9.312	9.827	1.360	1.986	2.478	3.058	3.689	4.327	4.952	5.698	6.316	6,769	7.258	7.727
R2 3.307		4.276	4.973	5.589	6.098	6.899	7.277	7.769	8,484	9.026	9,735	9.406	0.942	1.455	1.959	2.531	3.028	3,739	4.283	4.951	5.665	6.289	6.766	7.218	7.742
R. 879	5.9158	.963	. 022	. 967	.116	.174	.213	.254	.312	.359	.412	.465	.507	.547	.586	.630	999.	.722	.763	.813	.866	.912	.947	.989	.018
GE .009		.147	.832	. 092	.546	.173	.334	0.610	2.000	3,398	4.908	6.535	7.766	9.042	9.348	1.698	3,106	4.616	6.144	7.640	9.210	8.905	1.989	.161	4.283
	~	. 094	. 425	.626	.829	. 031	. 163	. 299	.438	.578	. 785	843	.943	. 843	. 142	.241	.341	.445	547	. 644	.743	.847	.912	.981	. 946

-0.0686 -0.0559 -0.0303 -0.0751
48.2267 48.7568 49.2349 49.7437
48.1588 48.7889 49.2846 49.6687
7.0480 7.0870 7.1230 7.1560
35.4778 36.7467 37.8912 39.1091
4.1140 4.1858 4.2489 4.3148

LAYER

SLOPE = 0.400 INTERCEPT = 37.677 FIT = 0.99997 NUMBER OF POINTS USED = 30

0.00 0.00 0.00 0.00 0.00 0.00 0.00 0.0
COMP R237.6769 339.05477 339.05569 449.2756 444.289 4444 45.0578 45.0579 45.0579 45.0599 55.05
82 338.0610 338.0610 339.0610 339.0610 40.2466 43.0610 44.2837 44.2837 44.2837
6.2476 6.2778 6.3691 6.58691 6.5898 6.5799 6.6359 6.8399 6.8399
RANGE 0.0000 0.9273 3.8329 5.0926 6.5461 12.0001 13.3985 17.7666
DIRECT 00.100 1.000 1.000 1.00000 1.00000 1.00000 1.00000 1.00000 1.00000 1.00000 1

992	6.852	900	911	836
	-0.8689	444	935	836
	-0.8689	444	555	842
5.811	47.5180	9.354	933	2.367
	48.1289	8.832	1.382	2.824
	48.7269	8.465	1.868	3.311
5.813	47.5907	9,359	8.945	2.368
	48.8689	8,887	1.417	2.861
	48.6869	8,489	1.834	3.269
919	7.0070 7.0410 7.0860	134 189 214	246. 279. 388	345
9.348 1.698	24.6167 26.1448 27.6406	9.210 8.905 1.989	3.161 4.283 5.477	6.746 7.891 9.189
241.241	3. 5478 3. 5478 4488	243 847 912	.981 .046	. 185 . 248 . 314

LAYER 6

9.0447 -0.0558 DIFF 46.8426 COMP R2 SLOPE = 0.371 INTERCEPT = 46.047 FIT = 0.99986 NUMBER OF POINTS USED = 28 46.8873 **R**2 6.9558 6.9940 œ 2.1479 3.8329 RANGE 1.6948 DIRECT

162 961 948	0.00.00.00.00.00.00.00.00.00.00.00.00.0	404 7.7.07	3 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	6.656 6.636 6.636	010	-0.00135 -0.0714 -0.0306 -0.0324
7.933 9.872 9.875	20.00 .00.00 .00.00 .00.00 .00.00	2.638	5 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	5.168 5.734 6.289	6.878 7.499 7.988	58.7588 59.1934 59.6636 68.8877 68.5398
7.771 8.411 9.827	60 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	2.281 2.672 2.672	1044 1004 1006 1006 1006	5000 5000 5000 5000 5000 5000 5000 500	6.868 7.484 7.799	58.7461 59.2869 59.5922 68.1183
929	216 216 25 25 25	0000 0000 0000 0000 0000	344R VW 02	546 576 689		7.738 7.8838 7.8288 7.8628
992 346 173	4000 4000 4000 6000	4.998 5.335 7.666	69.46 1.69.46 1.69.86 1.69.86	6.144.67.64.66.144.67.64.69.7	9.210	34.2835 35.4778 36.7467 37.8912
626 829 831	- 0.4 N 0 0.0 V 0 0.0 0	C 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	244 244 244	444 100	244 244 2743	4.2488 3.4888 4.2488

SLOPE = 0.353 INTERCEPT = 52.709 FIT = 0.99961 NUMBER OF POINTS USED = 28

DIFF	0.2347	. 185	9.0551	.877	9.834	9.118	6.171	\$	0.223	.123	.174	.173	. 148	. 697	. 845	. 044	.055	. 997	. 973	. 032	. 978	. 997	-0.0188) 1)	-0.0230	. 802
HP R	52.708	3.036	3,467	4.063	4.588	5.821	5.596	56.0069	6.458	6.948	7.443	7.976	8.551	3.986	9.437	6.833	9.375	8.873	1.487	1.947	2.475	3.838	64.0124		64.8228	5.244
	2.943	3.221	3,412	3.985	4.414	4.903	5,425	55.7841	6.234	7.072	7.617	8.149	8.790	9.083	9.391	9.855	0.320	9.880	1.334	1.914	2.546	3.037	63,9936) : :	64.7639	5.247
œ	.384	.403	416	455	485	.518	.553	7,5773	.697	.663	669	.734	. 778	. 795	.815	.845	875	.911	.940	.977	.017	. 048	8, 1080) 	8.1569	. 186
U	0.000	.927	.147	.832	. 892	.546	.173	9.3342	0.610	2.000	3,398	4.968	6.535	7.766	. 042	9.348	1.698	3,106	4.616	6.144	7.640	9.210	31,9898		34.2835	5.477
C	0.108	.756	.094	.425	626	829	. 931	2, 1630	.299	.438	.570	. 705	.843	.943	. 843	. 142	241	.341	.445	.547	.644	743	3.9120		4.0460	.114

0.0237 -0.0073 0.0511			01FF -0.2225(\) -0.0597 -0.1661 -0.1661 -0.1875(\) -0.0720
65.6932 66.8977 66.5280		0.99892	COMP R2 61.2864 61.4678 61.8899 62.2833 62.6372 63.8298 64.1876 65.8228 65.8522 65.8522 66.1982 66.1982
65.7178 66.8984 66.5791		206 FIT =	82 68.9839 61.4873 61.7537 62.4497 63.48497 63.7719 65.9539 65.9834 66.3834 66.1843
8.2150 8.2380 8.2680		EPT = 61. SED = 30	8.04440 8.04440 8.04440 8.04440 8.1520 8.1520 8.2290 8.2290 8.2290
36.7467 37.8912 39.1091		81 INTERC F POINTS U	RANGE 0.00000 0.9273 2.1479 3.8329 5.0926 6.5461 8.1733 9.3342 12.0001 13.3985 14.9084 17.7666 17.7666
4.1859 4.2480 4.3140	LAYER 8	SLOPE = 0.28 NUMBER O	018ECT 0.100 1.0


.1603	2139	100	9 69 69 69 69 69 69 69 69 69 69 69 69 69 69 69 6	6.63 6.13	-0.2027<<>>> -0.3045<<>>> -0.307<
7.302 7.698	8. 122 8. 552	9.0 9.0 9.0 9.0 9.0	0.194 0.523	9.838 1.174	71.5308 71.8524 72.1946
7.94	8,33	9.69	9.21	9.80 1.94	71.3282 71.5479 71.8867
322	375	446	488 584	523	8,5548 8,5678 5878
1.698 3.186	4.616 6.144	7.00 0.00 0.00 0.00 0.00	1.989 3.161	4.283 5.477	36.7467 37.8912 39.1891
.241	. 545	• • • • • • • • • • • • • • • • • • •	912	. 114	4.1858 4.2488 4.3148

(press return to continue)

FIT	9999	99999°	0.99997 0.99986	9886°.
INTERUAL UELOCITY (2)	1.559 1.564	20	2.138 2.178	•
F 1	T ~ 0	4.178	4.854 5.574	(7)
HER	(SEC 983	74	\sim	828
RMS VELOCITY	(KM/SEC) 1.522	1.525	1.582	1.682
AYER	~ (um 4	ring	~∞

(1) Depth to the top of the refracter: U(rms)*intercept (2) Interval velocity calculated from Dix' equation.

DO YOU WISH TO SEE THE X2-T2 PLOT? '



DO YOU WANT TO SEE THE PLOT AT A DIFFERENT SCALE?

< 01 00 >

			12.00 20.00		1,626 6,254 2,943
		5.253 3.253 3.341 4.114	2000.04 4000.04 4000.04 4000.04 1000.04	5.233 6.299 3.341 6.631 4.114	6.022 2.299 6.465
			6.393 6.393 6.393 6.393	24.00 24.00 24.00 24.00 24.00 20 20 20 20 20 20 20 20 20 20 20 20 2	1.425 6.214 2.843
	120.	5.183 2.163 3.241 6.173 6.567	5.416 3.2416 4.941 6.365 745	3.0669 3.0669 4.063 6.948 6.946	5.963 2.163 6.412
	-0.108		4669 4669 4669 4669 4669 4669	1.099. 2.898. 6.3398. 6.3333. 6.444. 1.460. 4.600.	1.894 6.175 2.785
26-BS	1.0000	5.129 2.643 3.142 6.118 6.524	5.364 5.831 3.142 6.311 6.710	5.623 2.031 6.092 3.142 6.533 6.910	5.916 2.031 6.359
LEES-	1.4879 1 39 28	8.23 8.33 8.33 8.33 8.24 8.24 8.24 8.24 8.24 8.24 8.24 8.24	9.756 2.578 6.978 3.547 6.513	6.2838 6.289 6.289 7.447 6.248	6.117 6.117 2.578
.978 TEST D	1.5888 8 1 38 38	5.086 3.0885 3.0843 6.9666 4843	5.328 1.829 5.797 3.943 6.262 6.678	5.578 1.829 6.839 6.483 6.83	5.880 1.829 6.312
1 APRIL 1 SONOBUOY	3912. 1 1 38 38	6.108 5.308 3.811 6.286 1.85 1.85	86.1.0 2.0 3.0 3.0 8.0 8.0 8.0 8.0 8.0 8.0 8.0 8.0 8.0 8	6.688 2.781 3.781 4.438 1.888 8.888 8.888	8.188 6.867 2.438

6.668 3.847 7.848	1.626 6.589 7.958 7.388 7.388	2.831 3.142 7.557 3.981 7.862	1.626 7.607 7.911 3.912 8.238	1.626 8.115 3.943 8.351 8.537
3.341 6.866 4.114	6.369 6.769 7.134 114	7.066 7.370 3.570 7.711 7.711	2.25 2.29 3.27 8.37 8.40 8.40 8.40 8.40 8.40 8.40 8.40 8.40	2.298 3.2298 4.44.1 4.146
6.630 3.743 7.818	1.00 4.00 4.00 6.00	1.829 7.216 7.548 7.912 7.828	2.54.7 2.54.3 3.7.8 3.7.8 3.7.8 5.7.8 5.7.8 5.7.8 5.7.8 5.7.8	-80.8888 40.88778 0.04480 0.48888
3.241 6.813 4.046 7.156	6.317 2.163 3.241 7.086 7.407	7.020 2.456 3.4455 7.685 7.885	7.417 2.163 3.244 3.241 8.017	7.967 2.163 3.284 3.241 8.421
6.386 4.314	1.0094 6.1008 6.705 8.77 7.246 4.314	1.626 7.173 2.943 7.581 3.847 7.883	1.094 7.553 2.785 3.644 8.186	1.094 8.071 2.705 8.305 3.644 8.504
3.142 6.763 3.981 7.123	6.278 6.667 3.142 7.981 7.379	6.994 2.299 3.339 4.114 4.114	7.484 2.631 3.142 7.937 4.114	2.945 3.174 3.142 3.981
6.947 748.04 748.047 748.04	6.452 6.832 3.547 7.214 4.248	2. 425 2. 843 3. 7469 7. 773	8.156 3.547 3.547 8.156	8 8 8 4 4 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8
3.043 6.722 3.912 7.087	6.248 6.635 3.995 7.3912 7.345	6.956 2.163 3.241 7.689 7.887	7.385 1.829 7.663 3.943 7.948 8.268	7.918 1.829 3.043 3.912
6.9453 4.1812 5.1812	80.00 80	1.009 2.100 2.705 7.705 4.30 4.31 4.31 4.31	8844. 887. 887. 888. 888. 889. 849. 849. 849.	83.8.4.88 8.0.11 8.0.138 8.2.5.4.4.66 8.4.5.6

(

(

4.185 8.554 4.248 8.567 4.314 8.587

DO YOU HISH TO WRITE THIS DATA SET ONTO A TAPE FILE?

WHICH FILE DO YOU MISH TO WRITE TO? (IF YOU ARE IN DOUBT AS TO WHICH FILE IS FREE, TYPE 999 TO DO A TLIST, WHICH WILL INDICATE THE FIRST AVAILABLE FILE? 999

892	N	96	N	16	4	N	N	0	0	1280	892	
AD	16	HOR.	27	EDIT	5		DIGIT	ì				
ROGR	PROGRAM			ROGR	ROGR	ROGR	œ	A	A	α		
SCI	INAR	INAR	INAR	INAR	INAR	INAR	INA	INAR	INAR	ASCII	AST	
+-4	2	M	4	3	9	~	8	9		11		

WHICH FILE DO YOU WISH TO WRITE TO? 12

IS THE FILE YOU ARE WRITING TO ALREADY MARKED? n

Appendix H

Examples of reduction programs

This appendix includes examples of the reduction programs SLOWI and LINFT. Shown are the input and output segments only. Refer to section IV.4 to determine the process for executing the programs themselves. The input segments are the same as those listed in the introductory comments to the program listings. (See Appendix J.) Furthermore, the input segment for the SLOWI example is derived from the output of the program SONOMODEL, (see Appendix I.1), and is based on the test model of Figure 5. By comparing the SLOWI result with the input model to SONOMODEL, one can verify that both programs are operating correctly.

The LINFT example is shown twice with identical input data sets, save only for the output parameters. The data listings are suppressed in the second example (ISSW1 = 1).

The examples used in these programs are included in the introductory comments prefacing the program listings (see Appendix K), so that if these programs are installed elsewhere, test programs are available for comparison.

Note: No attempt has been made to describe the output tables produced by these programs. However, a considerable amount of information is available, which can be invaluable in interpreting the results. This is particularly true of the SLOWI output lists. To interpret this information fully, refer to Knott & Hoskins .1975.

Example of SLOWI input data set

This example input data set is described in the comments prefacing the SLOWI program listing (App. K, p.201). The output result from this data set follows.

The data for this test program was artificially produced through the program SONOMODEL (see App. I.1, p.165), so that the results could be compared with a known input.

```
$75. 1.500n 1.4P70 1.00n0 -0.0nn 60.

15 15 15 15 15

10 0 1 1 0 0 1

11 1 0 0 1

11 1 0 0 1

12 10 0 1

13 15 15 15

0.000 0.000 0.000 0.000 0.000

0.000 0.000 0.000 0.000 0.000

0.000 0.0265 5.014 0.531 5.034 0.800 5.069 1.074 5.11

2.916 5.281 3.284 6.139 5.363 2.240 2.577 6.70

0.000 6.028 0.192 6.031 0.384 6.139 0.576 6.052 0.770 6.07

0.000 6.028 0.192 6.031 0.384 6.139 0.576 6.052 0.770 6.07

0.000 6.004 1.164 6.124 1.364 6.139 1.567 6.201 1.774 6.24

0.000 7.083 0.217 7.086 0.435 7.093 0.654 7.105 0.884 6.59

0.000 8.046 0.216 8.047 0.435 7.455 2.995 7.522 3.260 7.60

0.000 8.046 0.216 8.047 0.433 8.052 0.650 8.059 0.869 8.07

1.089 8.199 2.469 8.233 2.714 8.271 2.966 8.314 3.285 9.995 3.724 10.02

2.018 9.933 2.434 9.950 2.855 9.971 3.285 9.995 3.724 10.02

2.018 9.933 2.434 9.950 2.855 9.971 3.285 9.995 3.724 10.02

2.175 10.054 4.155 10.091 5.118 10.132 5.616 10.178 6.135 10.23
```

SLOWI output listings from test data set.

SONOBUOY TEST A

Refer to Knott & Hoskins, 1975, pp. 51-59, for a complete explanation of these result listings.

,		מברב	19761 1970					
1 APRIL	1978							
ONOBOOA	TEST A							
WATER	E/S WATER DEPTHE 3755. HORIZ SOUND VELOCITY# 1.4	755. MEAN TY= 1.4870	SEC/INCH	SEC/INCHE 1.0000	.0CITY=	1.5000		
10 = 1	1 SSW1=	1 ISSU2= 0	ISSW12	= 1 155	5W13= 1			
15 15	15 15							
000	.000	.000 0.000	000 0 0					
FICATI	ON OF DA	S	₹.				,	
· O	0 200.	265		6	٠,	·	6:	Ξ
.353 .916 S.	781 3	.280 5.970	3.669	5.363 6.189	060.7	> 7 × 80 9 · 4 4 2	4.547	5.619
Ξ	7	PICKS	LAYER					
	_	0.9 20	0.384	6.0		6.052	•	0
0.966	4.00.4	1.164 6.124	1.364	6.159	1.567	6.201	1.774	6.248
		0.0	7.07	•	•	9.208	•	•
ERIFICATION 2	ON OF (DATA PICKS IN	A YE	,		•		•
. •	777	• •	•					٠,
~	336	.490 7.392	2.739	7.455	2.995	7.525	3.260	7.603
CAI	_	PICK	AYER					
۲.	.0 970.	16	7 0.433	8.052	.65	8.059	.86	8.070
			_	8.119	1.763	8.142	1.994	8.169
_		69	۲.	8.271	96.	~	.22	۳.
CATI	N OF DA	TA PICKS	AYER	,	:	•		,
~ .	895	007	o'	106.6	202	٠, ۱	9	0.0
4.175 10.	2 7 7 0	.639 10.091	5.118	10.132	5.616	10.178	5.724 6.135	10.230
R (IN)	2	DIR (SEC) REF (SE	S				
000	2.007		2.007					
- 265	5.014		5.014					
1.55	5.034		5.034					
. 800	7.064		V					
353	5.183		100					
.641	5.264		5.264					
.939	5.363		5.363					
5.249	2.480		5.480					
2.573	5.619		5.619					
2 8 0	5.070		2.020					
8 6 6 9	6.180		4					
0.00	6.442		6.442					
295.9	6.737		6.737					
Q (KM)	R2(SEC)	R2 COMPUT	ED DIFFERENC	NCE				
000	2.07	55.06						

2	-	0.000	0.000 REFLECTION 0.000 REFLECTION 0.102 6.034 0.384 6.034 0.384 6.034 0.384 6.034 0.384 6.034 0.384 6.034 0.384 6.284 0.384 6.284 0.002 0.003 0.003 0.004 0.003 0.004 0.003 0.004 0.003 0.004 0.003 0.004 0.004 0.006 0.004 0.006 0.007 0.006 0.007 0.006 0.007 0.006 0.007 0.	870 11ME	EC)		2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	E D VALUES DISCARDED 1 / 14 TERCEPT= 0.0001 X2= 0.2402 TIME= 6.028 THICKNESS= 1.041 .00 2 WATER TRAVEL TIME FOR LAYER SEC)	
---	---	-------	--	-------------	-----	--	---------------------------------------	---	--

5 7 .	2	٠,	6.60	000			ě	-0.001	ŏ	0.00	0.00	3 5	00.0	00	00.	0	TOTAL STREET	TIVE D VALUES DISCARDED 1 / 1	INJERCEPT# 0.0003 X2# 0.	U.S	2 6	3.10 WATER TRAVEL TIME FOR LAVE		7367		Ċ	Ċ	0	è	č	Ξ	1	16	5	23	~	8.314	Š		0.001	ě	ĕ	ě	ě		2	35		0			50.
.73	2.995	3.26	R2 COM	0.002	0.0	0.0	0.0	0.037	0.0	0.07	0.0	0.12	0.16	0.20	0.24	0.30	0.000 ME.C	ED POLYNOMIA	004 × 5m20	2.409 86615	0.008	ICAL RANGE,	(SEC)	0.000	.216	433	650	869	089	311	536	763	766	556	697	714	3,225	()	õ	.001	*00*	.010	.018	.028	. 041	. 057	. 075	260	- 221	151	186	.225
4.5	. 52	• 60	SE	ĕ	ĕ	Ö	õ	0.037	0	6	Ĉ	12	16	20	57	20	EVIATION=	S OF F	x:= 0.	ELOCITY	90	IMUM	_	ě	ò	0	8.059	õ	õ	õ	= :	-	9	2 ;	C	:	8.361			ĕ	ĕ	9	5	20	ŏ	0	6	ô	7	15	0.185	2
2.739	•	٠,٥	2	ĕ	6	à.	- 7	$\overline{}$	5:	3.0	<u>`</u> ;	2 :	÷:	9 :	3 4	•	NDARD D	OEFF ICIE	3= 0.06	AYER	# #	.65 MI	DIR (IN)	Ō	~	•	c	ĕ	3	7:	. ,	- 6		, 4	7	8	3.225		DSQ (KM)	5	š:		Ç	,	~	2	Ę	5,5	` :	7 7		-

			7
	THICKNESS= 1.810		L TIME FOR LAYFR
	8.046		TRAVE
-0.000-	EFLECTION TIME = 8	SLOPE 0.00	E. 2.24 WATER
x3= 0.0410 x4= 0.0006 x5=-0.0002	LAYER 4 VELOCITY= 3.760 REFLECTION TIME= R.046 THICKNESS= 1.810	HE 7.877 SVE 0.033	3.37 MINIMUM CRITICAL RANGE, 2.24 WATER TRAVEL TIME FOR LAYFR 4
x3= 0.(LAYER	DEPT	3,3

L TIME FO																														
2.24 WATER TRAVEL	<u>.</u>	.89	0	.90	.90	. 91	93	.95	9.971	66.	0.02	• 05	•00	0.13	.17	0.23		.00	-0.001	۰.	0.00	00.	00.	00.	.00	0.0	00.	00.	90.	•
ICAL RANGE,	S	00.	07.	.80	. 20	.60	.01	.43	2.855	.28	. 72	. 17	.63	Ξ	.61	.13	OM P	.00	0.016	.03	• 00	٠,	. 14	• 20	• 26	.34	.43	. 54	• 66	a
NIMUM CRITI	Ξ	.89	.89	.90	.90	.9	.93	.95	9.971	66.	• 02	.05	0.09	.13	.17	.23	SEC	.00	0.015	.03	• 06	.10	. 14	. 20	• 26	. 34	. 43	. 54	• 66	9
3.37 MIN	Ξ	.00	07.	.80	. 20	6.	5	.43	2.855	. 28	.72	.17	.63	-	.61	.13	E	17	0.696	.5	. 83	. 47	. \$2	.0	.97	.47	9.55	4.31	9.85	4

STANDARD DEVIATION= 0.001 NEGATIVE D VALUES DISCARDED 1 / 14
COEFFICIENTS OF FITTED POLYNOMIAL; INTERCEPT= 0.0006 X2= 0.0222
X3= 0.0124 X4= 0.0001 X5=-0.0000
LAYER 5 VELOCITY= 6.704 REFLECTION TIME= 9.895 THICKNESS= 6.199
DEPTH=14.076 SV= 0.061 SLOPE 0.00
2.91 MINIMUM CRITICAL RANGE, 1.94 WATER TRAVEL TIME FOR LAYER 5

DEVIATION SLOPE 0.000 0.000 0.009 0.008 0.033 DELTA TT 5.007 1.021 1.055 0.963 THICKNESS 3.755 1.041 1.271 1.810 6.199 SONOBUOY TEST A VELOCITY REFL TIME 5.007 6.028 7.083 8.046 9.895 1 APRIL 1978 1.500 2.040 2.409 3.760 6.704

Compare these results with the model from which this data set was produced (p. 165). Example of LJNFT input data set

This example input data set is described in the comments prefacing the LINFT program listings (App. K, p. 197). Refer to the listings for description of the input parameters and formats. The output result from this data set follows.

This data set represents real data, with slope corrections included. The output parameters (ISSW1) specifies that all data shall be listed.

```
SONOBUOY TEST B

1.500 1.400 1.000 -0.025

1.500 0.100 -0.100 0.000

2.020 2.775 4.020 4.638 6.020 6.500 8.020 8.363 10.020 10.2

4.790 5.612 5.617 6.126 6.740 6.830 7.215 7.138 7.695 7.4

4.790 5.568 5.617 5.998 6.740 6.880 7.215 6.840

6.740 6.619 7.215 6.876 7.695 7.020 8.000 7.150 8.540 7.3
```

,

2 DECEMBER 1976

PROGRAM LINEAR FIT

LINFT input data set

This data set is identical to the previous example, with the exception that complete output listings are suppressed. The result from this example follows

```
1.000 -0.025
1 APRIL 1978
SONORUOY TEST B
1.500 1.490 1.000 -.
1 1 0 0
5 5 6 6
0.000 0.100 -0.100 0.000
1.500 2.775 4.020
4.790 5.568
6.740 6.66
```

1 APRIL 1978 SONOBUOY TEST B

MEAN VERT SOUND VELE 1,5000 HORIZONTAL SOUND VELE 1,4900 INCH/SEC 1,0000 TIME ZERO CORR -0,020 ISSUM 1 ISSUM 1 ISSUM 0 ISSUM 0 ISSUM 1
2 DECEMBER 1976

SONOBUOY TEST B

1 APRIL 1978

PROGRAM LINFAR FIT

A=0.2872 B= 3.721 VLAVE(4)= 3.481 ORTIM(4)= 3.721 DEPTH(4)= 3.093 B= 0.893 VLAVE(1)= 1.600 ORTIM(1)= 0.893 DEPTH(1)= 1.924 B# 3.051 VLAVE(3)# 2.849 ORTIM(3)# 3.051 DEPTH(3)# 2.692 2.574 VLAVE(2)= 2.359 ORTIM(2)= 2.574 DEPTH(2)= 2.501 AVERAGE VELOCITY ABOVE SHALLOWEST REFRACTION= 1.5000 AVERAGE VELOCITY ABOVE SHALLOWEST REFRACTION# 1.5000 *8 LAYER 2 A=0.4239 B LAYER 3 A=0.3511 B LAYER 4 LAYER 1 A=0.6250

\$LOPE 0.000 0.100 -0.100 11 INC 2.565 0.813 0.355 VELOCITY 1.600 2.354 2.845 3.476 1.924 0.650 0.418 1.049 1.924 2.574 2.992 4.042 INTCPT 0.893 2.574 3.051 3.721

EOJ - REFRACTIONS

.

163

Appendix I

Examples of interpretation programs

This appendix contains two sections:

- Example of SONOMODEL
- Calculation of sediment thickness versus travel time curves: Example of program POLYFIT.

The model used in the SONOMODEL example is also listed in the introductory comments prefacing the program listing (see Appendix L). The printed output from the program is listed after the model input segment, and the plot result is shown in Figure 15. This plot is also used in Figure 5. The modelling program also produces from the calculations of the reflection hyperbolas, a data set of direct time - travel time pairs that can be input to the wide angle reflection reduction program, SLOWI. We have used the SLOWI formated output set from this model example in our SLOWI example (see Appendix G). The close correlation of the model input to SONOMODEL and the SLOWI results indicate that both programs are working as we would expect them to.

The second part of the appendix illustrates the use of the polynomial regression program POLYFIT. This program is available through the Tektronix Plot 50 Statistics Package, volume 3. Complete instructions for it's use are contained in the manual for the statistics package.


In the example, the regression program is used to fit a third order polynomial equation to depth and travel time solutions from sonobuoy data of the Bering Sea region. The solution, depth as a third order function of travel time, is shown at the bottom of the figure. The solution is constrained to pass through the origin (O thickness at O travel time). A curve or equation of this type is very useful when converting travel times from vertical incidence seismic records to true depth.

SONOMODEL example input data set

This example input data set is described in the comments prefacing the SONOMODEL program listing (App. L, p. 215). The input parameters and format are described there.

From this model , an experimental data set was constructed for input to program SLOWI. The results from SLOWI (p. 159) compare very favorably with this input model.


This model was used to produce the SONOMODEL plots shown in Figures 6 and 15.



horizontal velocity of sound= 1.4870 blot parameters are: sreat= 0.7000 liyer velocity(tm/sec) thickness(tm) 1.500 2.401 1.500 3.755 3.2.411 1.500 3.755 4.207 4.207 5.772 5.772 5.773 6.207 5.773 6.207 5.773 6.207 5.773 6.207 6.	horizo plot p	ontal ve saramete	ţ	sounds 1.4870 xscals 0.50f		
velocity(tm/sec) thickness(tm) velocity(tm/sec) thickness(tm) 1.500 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 3.028 4.0207 2.010 3.028 4.0207 5.020 5.020 6.020	plot p	aramete		Ascals 0.500		
velocity(tm/sec) thickness(tm) 1.500 2.010 2.010 3.055 3.755 3.751 4.200 4.72 5.010 5.007			7 S & 7 & 3		. 011	
1.500 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.010 2.012 3.755 1.810 6.207 3 0.208 3 0	layer	veto	city(km/sec	thick	s (km)	
2.010 2.411 1.272 3.611 6.207 7.953 phi x(km) t(sec) critical distance critical travel 0.000 5.007 1 0.000 5.007 1 0.000 5.007 1 0.000 5.007 1 0.000 5.007 1 0.000 0.008 24 19.564 13.971 25 19.564 13.971 26 19.564 13.971 27 15.000 28 13.971 29 15.31 24.080 20 1.272 6.201 21 0.000 6.028 21 0.000 6.028 22 1.288 6.292 23 1.202 24 18.37 25 10.659 11.705 26 10.659 11.705 27 10.659 11.705 28 1.242 29 1.628 1.242 20 1.628 1.242 21 1.628 1.242 21 1.628 1.283 22 1.628 1.283 23 1.628 1.283 24 1.628 1.283 25 10.659 1.263 26 1.628 1.263 27 1.628 1.263 28 1.628 1.263 29 1.628 1.263 20 1.628 1.263 20 1.628 1.263 21 1.628 1.283 22 1.628 1.283 23 1.648 1.283 24 1.628 1.283 25 1.648 1.283 26 1.648 1.283 27 1.649 1.283 28 1.644 1.283 29 1.646 1.628 1.628 20 1.646 1.628 1.628 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 21 1.646 1.646 1.646 1.646 21 1.646 1	-	-	\$n0			
2.411 1.272 3.761 6.207 6.207 7.953 phi x(km) t(sec) critical distance 1 0.000 5.007 5 0.789 5.183 9 5.344 5.80 12 4.877 5.970 13 0.784 5.80 14 0.784 10.013 15 4.877 5.970 17 0.000 6.028 18 0.274 6.004 19 0.570 6.039 10 0.570 6.039 11 0.000 6.028 12 1.374 6.904 12 1.388 6.592 13 0.573 6.904 14 0.723 11.705 15 0.477 7.933 16 0.723 7.392 17 0.000 7.083 18 0.471 7.891 18 0.471 7.891 18 0.471 7.891 19 0.000 8.046 12 1.084 9.784 10 0.000 8.046 11 0.000 8.046 11 0.000 8.046 12 12.084 9.784 11 0.000 8.046 12 12.084 9.784 11 0.000 8.046 12 12.084 9.784 11 0.000 8.046 12 12.084 9.784 11 0.000 8.046 12 12.084 9.784	~	~	0,0	1.04		
5.7661 1.810 6.272 7.953 phi x(km) t(sec) critical distance critical travel 1 0.000 5.007 8.15 6.207 7.39 1 0.000 5.007 8 0.274 7.956 21 13.008 10.013 24 13.071 25 13.071 26 13.071 27 35.217 28 0.026 29 0.028 20 0.020 20 0.020 20 0.020 21 0.000 6.028 22 0.020 23 0.020 24 0.020 25 0.020 26 0.020 27 0.020 28 0.020 29 0.020 20 0.020 20 0.020 20 0.020 20 0.020 21 0.000 7.083 22 0.000 23 0.000 24 0.000 25 0.000 26 0.000 27 0.000 28 0.000 28 0.000 29 0.000 20 0.0000 20 0.0000 20 0.0000 20 0.0000 20 0.0000 20 0.0000 20 0.0000 20	₩	2.	411	1.27		
phi x(km) t(sec) critical distance critical travel by x(km) t(sec) critical distance critical travel continued by x, x(km) t(sec) critical distance critical travel continued by x, x(km) t(sec) x, x(km)	•	~	761	1.81(
1 0.000 5.007 6.15 6.15 6.15 7.39 1 0.000 7.000	د ،	٠,	712	9.50		
1 0.000 5.007 8.15 7.39 1 2 0.78 5.007 1 3 34 5.480 1 3 34 5.480 1 1 0.000 6.028 1 0.000 6.028 2 1.37 6.094 2 1.37 6.094 2 1.37 6.094 2 1.37 6.094 3 0.570 6.028 3 0.570 6.028 3 0.570 6.038 4 1.437 6.094 5 1.437 6.094 6 1.437 6.094 6 1.437 6.094 7 1.000 7.083 1 0.000 7.083 1 0.000 7.083 2 1.628 8.287 1 0.000 8.046 2 2.64 9.784 2 2.64 9.784 3 0.647 7.603 4 9.784 5 12.084 9.784 5 12.084 9.784 1 0.000 8.046	,					
1 0.000 5.007 5 0.789 5.034 6 2.012 5.183 12 4.877 5.970 13 0.762 6.737 14 9.564 13.971 24 19.564 13.971 27 35.331 24.080 30 0.570 6.028 1 0.000 6.028 6 1.437 6.094 9 2.330 6.201 1 0.000 7.083 1 0.000 7.083 1 0.647 7.603 1 0.000 7.083 1 0.427 7.603 1 0.000 7.083 1 0.000 7.083	-	5	E		8.15	
3 0.789 5.034 6 2.012 5.483 12 4.877 5.970 13 6.762 7.956 21 13.008 10.013 24 19.564 13.971 25 35.331 24.080 30 0.570 6.028 30 0.570 6.028 4.288 6.592 1 0.607 7.093 2 1.628 7.146 9 2.640 7.242 1 0.607 7.093 1 0.607 7.093 1 0.607 7.093 1 0.607 7.093 2 6.417 7.891 2 6.421 8.854 2 7.88 8.287 2 6.404 3 0.647 7.603 4 0.784 5 12.084 9.784 3 0.646 8.056 4 0.646 8.056 5 10.659 8.057 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.628 7.603 6 1.646 8.056		-	0000	2.00.5		
6 2.012 5.183 12 4.877 5.970 13 9.274 5.970 14 9.274 17.056 24 19.564 13.071 25 35.331 24.080 3 0.570 6.028 1 0.000 6.028 2 13.0 6.039 6 1.437 6.036 1 2 2.330 6.201 1 2 2.330 6.201 1 2 2.330 6.201 1 3 0.647 7.093 1 0.000 7.083 1 0.647 7.093 1 0.647 7.603 1 0.000 8.046 2 12.884 2 12.084 9.784 3 0.646 8.056 3 0.646 8.056 4 8.877 6.033 5 12.084 9.784 5 12.084 9.784 3 0.646 8.056 3 0.646 8.056 4 8.676 8.066 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046 5 10.000 8.046		m	0.789	5.034		
9 3.344 5.480 15 6.787 6.795 18 9.274 7.956 21 19.508 10.013 24 19.508 10.013 27 35.331 24.080 3 0.570 6.028 6 1.437 6.201 12 3.272 6.363 14 6.723 7.933 24 8.341 7.933 25 10.657 7.933 27 10.657 7.933 28 16.273 7.933 29 16.473 7.983 10.647 7.983 11 0.000 7.083 12 3.272 8.854 24 8.341 7.05 12 3.272 8.902 25 10.659 11.705 10.647 7.983 11.705 7.891 21 7.288 8.854 22 12.084 9.784 30 19.149 12.537 5.81		•	2.012	5.183		
12		o	3.344	5.480		
15 6.762 6.737 21 13.001 10.013 24 19.564 13.071 27 35.331 24.080 30 ***** 95.657 9.28 1 0.000 6.028 1 0.570 6.028 1 0.570 6.004 2 2.350 6.201 1 2.37 6.004 2 2.35 6.201 2 4.28 6.592 2 4.28 6.592 3 10.647 7.303 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.647 7.093 3 10.644 8.854 2 6.117 7.8891 2 17.086 9.784 3 10.000 8.046 3 10.644 8.052		12	4.877	5.970		
18 9.274 7.956 24 19.008 10.013 25 15.008 10.013 30 0.514 24.080 31 0.500 6.028 3 0.570 6.039 4 1.437 6.094 5 1.437 6.094 12 3.273 7.930 24 8.341 7.933 25 10.659 8.902 3 0.647 7.144 9 2.640 7.242 15 4.847 7.603 16 12 13.73 7.392 17 10.000 8.954 21 7.588 8.542 22 10.648 8.553 24 8.544 9 2.640 8.954 25 10.000 8.046 26 117 7.892 26 9.421 8.854 27 10.000 8.046 28 8.046 29 12.537 20 10.464 8.055		15	6.762	6.737		
21 13.00R 10.013 24 13.971 27 35.331 24.080 30 95.657 9.28 1 0.000 6.028 9 2.350 6.201 12 5.272 6.363 15 5.417 6.904 21 6.723 7.330 24 8.341 7.933 27 10.659 8.902 28 16.713 11.705 30 16.47 7.083 4 6.117 7.891 21 7.888 8.287 22 12.084 9.784 30 19.149 12.537 3 0.644 8.052 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065 3 0.644 8.065		18	9.274	7.956		
24 19.564 13.971 35 331 24.080 30 0.028 1 0.000 6.028 6 2.330 6.201 12 3.272 6.363 18 5.417 7.933 27 10.000 7.083 1 0.000 7.242 12 5.428 8.954 2 1.628 7.144 2 2.640 7.242 12 5.640 7.242 13 6.117 7.283 24 6.117 7.283 26 6.128 8.854 27 12.084 9.784 30 19.149 12.537 2 10.644 8.052		21	13.00R	10.013		
27 35.331 24.080 30 95.657 9.28 8 1 0.000 6.028 6 1.437 6.004 9 2.350 6.201 12 3.272 6.363 14 5.417 6.904 15 4.288 6.592 18 5.417 6.904 27 10.659 8.902 27 10.659 8.902 30 16.713 11.705 6.74 9 2.640 7.242 12 3.703 7.392 13 6.117 7.392 14 6.117 7.392 15 4.847 7.603 16 6.117 7.891 17 2.884 8.287 24 9.784 27 12.084 9.784 30 19.149 12.537 5.81		54	19.564	13.971		
30		27	35, 331	24.080		
1 0.000 6.028 3 0.570 6.039 6 1.437 6.094 12 3.272 6.363 14 5.417 6.904 21 6.723 7.330 22 6.723 7.330 24 8.341 7.933 27 10.659 8.902 30 16.713 11.705 6.74 1 0.000 7.083 6 1.628 7.144 9 2.640 7.242 15 4.847 7.603 16 6.117 7.891 21 7.588 8.287 22 12.084 9.784 30 19.149 12.537 3 0.644 8.052		30	•••••	95.657		
1 0.000 0.028 6 1.437 6.004 9 2.330 6.201 12 4.288 6.203 18 5.417 6.004 21 6.723 7.330 24 8.341 7.933 27 10.659 8.902 28 16.713 11.705 6.74 30 10.47 7.083 4 6.117 7.891 21 7.888 8.287 22 12.084 9.784 30 19.149 12.537 5.81 8	~	•		,	~	8.31
5 0.570 6.039 9 2.330 6.201 12 3.272 6.363 13 6.728 6.592 14 6.723 7.330 24 8.341 7.933 27 10.659 8.902 27 10.659 8.902 30 1647 7.093 6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 13 6.117 7.392 14 6.117 7.392 15 6.117 7.392 16 6.117 7.392 17 2.084 9.784 20 19.149 12.537 2 12.084 9.784 3 0.644 8.052 3 0.644 8.052		- (0000	8.028		
9 1.437 6.094 12 3.273 6.201 15 4.288 6.592 18 5.417 6.904 21 6.723 7.330 24 8.341 7.933 27 10.659 8.902 30 16.713 11.705 6.74 88 1 0.000 7.083 1 0.647 7.144 9 2.640 7.242 12 3.703 7.392 13 4.847 7.603 14 6.117 7.392 15 4.847 7.603 16 4.847 7.603 17 5.88 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81		₩,	0.570	6.039		
12		•	1.437	760.9		
12 5.272 6.363 18 5.472 6.904 21 6.723 7.330 24 8.341 7.933 27 10.659 8.902 30 16.713 11.705 6.74 8 1 0.000 7.083 5 1.647 7.093 6 1.648 7.144 9 2.640 7.242 12 3.703 7.392 13 6.117 7.391 15 6.117 7.381 24 9.784 27 12.084 9.784 30 19.149 12.537 5.81 8		٠,	2.330	6.201		
15 5.288 6.592 21 6.728 7.330 22 10.659 8.902 27 10.659 8.902 30 16.713 11.705 6.74 8 1 0.000 7.083 6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 15 4.847 7.603 15 4.847 7.603 16 6.117 7.891 21 7.588 8.287 22 9.721 8.854 23 19.149 12.537 5.81		12	3,272	6.363		
24 8.321 7.330 24 8.341 7.933 27 10.659 8.902 30 16.713 11.705 4.972 1 0.000 7.083 1 0.647 7.093 12 1.628 7.144 9 2.640 7.242 15 4.847 7.603 16 6.117 7.891 21 7.588 8.287 24 9.784 30 19.149 12.537 3 0.644 8.052 4 4.49 9.784		٠:	282.5	6.592		
27 6.723 7.530 27 10.659 8.902 30 16.713 11.705 6.74 8 1 0.000 7.083 5 1.628 7.144 9 2.640 7.242 12 3.703 7.392 15 4.847 7.891 21 7.588 8.287 22 9.421 8.854 23 19.149 12.537 5.81 8		8 .	7.617	9.404		
27 10.559 8.955 30 16.713 11.705 6.74 8 1 0.000 7.083 6.74 8 6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 15 4.847 7.603 15 6.117 7.891 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 8		- 2	0.723	7.530		
30 16.713 11.705 6.74 8 1 0.000 7.083 5 1.628 7.144 9 2.640 7.242 12 3.703 7.392 13 4.847 7.603 14 6.117 7.891 24 9.728 25 9.421 8.854 27 12.084 9.784 30 19.149 12.537 3 0.644 8.052			- 30.00			
1 0.000 7.083 6.74 8 8 1.628 7.144 6 1.628 7.144 6 1.628 7.144 6 1.628 7.144 6 1.628 7.144 6 1.628 7.144 6 1.628 7.603 15 4.847 7.603 18 8.287 24 9.421 8.854 27 12.084 9.854 27 12.084 9.758 8 10.000 8.046 8.052 7.548 8.046 8.052 7.548 8.046 8.052 7.548 8.046			****	204.0		
1 0.000 7.083 3 0.647 7.093 6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 15 4.847 7.603 16 6.117 7.891 21 7.588 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 8	-	20	617.01		76. 7	80
3 0.647 7.093 6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 15 4.847 7.603 18 6.117 7.891 24 7.588 8.287 24 7.588 8.287 27 12.084 9.784 30 19.149 12.537 5.81 8	1	-	000	7 082	•	60.8
6 1.628 7.144 9 2.640 7.242 12 3.703 7.392 13 6.117 7.803 14 6.117 7.891 24 0.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 1 0.000 8.046 5 14.4 8.052		. pr	2770	200.		
12 3.703 7.342 15 4.847 7.503 15 6.117 7.891 24 7.588 8.287 24 9.784 27 12.084 9.784 30 19.149 12.537 5.81 8		• •	428	7 166		
12 3.703 7.392 15 4.847 7.603 18 6.117 7.891 24 7.588 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 8 3 0.644 8.062		0	070.	7 24.3		
15 4.847 7.605 18 6.117 7.891 21 7.588 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 8 3 0.644 8.052			102	7 103		
18 6.117 7.8951 21 7.588 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 3 0.644 8.052 4 1.419 8.052		. F	20.00	200		
21 7.588 8.287 24 9.421 8.854 27 12.084 9.784 30 19.149 12.537 5.81 1 0.000 8.046 5 14.19 8.052		· -	4.17	7 801		
24						
27 12.084 9.784 30 19.149 12.537 5.81 8 1 0.000 8.046 3 0.644 8.052		7 2	0 621	750		
30 19,149 12,537 5,81 8 1 0,000 8,046 5,81 3 0,644 8,052		, ,				
3 0.644 8.052 6 1 4.19			*80.21	,0,0		
1 0.00 R.046 3 0.644 R.052 4 1.410 8.082	4	20	631.6	12.557	Ü	œ.
1.644	,	•	000	770 8		9.50
1.610		. *	274.0	0.50		
		٠.				

	5.119 5.619 6.737 6.737 6.248 6.592 7.122 7.122 7.286 7.603 8.169 8.361 9.919
	7.074 6.5573 7.573 10.777 10.777 10.834 10.869 10.969 10.908 10.608
	5.069 5.480 6.442 6.201 7.242 7.242 7.242 7.242 7.242 7.242 7.253 8.059 9.909
	0.800 6.800 1.567 1.567 2.649 0.654 1.765 1.765 1.765 1.765 1.265 5.616
24.78	5.034 5.035 6.189 6.189 6.159 7.204 7.455 8.055 8.271 9.901
	0.531 3.669 3.669 1.384 1.384 1.554 1.536 1.536 1.536 1.536 5.714 5.818
8,233 8,361 8,361 8,788 9,137 9,246 11,837 9,995 10,091 10,230 10,430 10,430 10,430 11,193 12,106	5.014 5.264 5.870 6.124 6.124 6.363 7.086 7.086 7.172 7.392 8.099 8.099 8.233 9.897
2000 2000	0.265 1.641 1.641 1.164 1.164 1.164 1.311 1.311 1.311 2.469 0.400 2.434
VV8=4V0 -W40VV86-4V0	matted of 5.007 5.183 5.781 6.0028 6.302 7.144 7.314 8.083 8.046 8.08 8.083 9.993 9.993 10.054
~ 	stowi formatted output 0.000 5.007 0.26 1.353 5.183 1.64 2.916 5.781 3.28 0.900 6.094 1.16 1.985 6.302 2.20 0.000 7.083 0.21 1.085 8.36 2.49 0.000 8.046 0.21 1.089 8.083 1.31 2.229 8.989 0.46 2.018 9.933 2.43 4.175 10.054 4.63

This SLOWI formatted data set is used to test program SLOWI (see pp. 151-155).



A Sediment thickness versus Travel Time Curve

An equation for sediment velocity as a function of travel time can easily be computed from the wide angle reflection (SLOWI) and refraction (LINFT) results. A good approximation to the velocity-travel time data is obtained with a third order polynomial (Houtz et al., 1968):

$$V = C_o + C_1 T + C_2 T^2 + C_3 T^3 \qquad (A)$$

where the C_i 's are the coefficient, T is the one-way travel time beneath the seafloor, and C_o is the velocity at the water-sediment interface. Usually, a large number of data values from sonobuoy stations in the same physiographic region are used to determine the coefficients by a least squares fit to the data. If sonobuoy data are sparse, the coefficients can be determined by as few as four velocity-travel time data pairs.

A more useful equation for sediment thickness versus travel time is obtained by integrating the above equation:


$$D = \int Vdt = C_{-1} + C_{0}T + \frac{1}{2}C_{1}T^{2} + \frac{1}{3}C_{2}T^{3} + \frac{1}{4}C_{3}T^{4}$$
 (B)

where C_{-1} , which is the thickness at zero reflection time, is normally 0. Using the thickness versus one-way travel time equation (equation B), reflection times in vertical incidence seismic profiles can quickly be converted to sediment thickness (or depth below sea level, if the water depth is known).

A computer program for determining the third-order polynomial equation to the velocity-reflection time data (equation A) is available on the Tektronix 4051 through the "statistical package". Complete documentation for the program exists in the Statistical Reference Manual. An example of this

analysis which was performed on sonobuoy reflection data from the Bering Sea is shown in Figure 16.

ALEUTIAN BASIN : SONOBUOY DATA



Polynomial regression:

 $d = 1.287t + 0.931t^2 - 0.073t^3$

Figure 16 Example of polynomial regression used to determine sediment depth (in km) as a function of one way sub-seafloor travel time (in seconds) from sonobuoy data in the Bering Sea deep ocean basins.

Appendix J

Listings of digitizing programs

This appendix contains line numbered listings of the digitizing programs LINDIGIT and SLODIGIT. Both programs are in Tektronix BASIC language. Special characters unique to the Tek language are:

```
G (control G): rings bell
H (control H): backspaces the cursor
J (control J): moves the cursor down one line
(control _): " " " " "

K (control K): moves the cursor up one line
(control L): erases the screen and moves the cursor
to home

- arithmetic symbol to indicate exponent
```

(e.g. 2³ = 8)

These characters do not print, so they are shown simply as the upper case letters or underscore. Their context, in print or image statements, identify them.

```
LINFT FORMATTED DIGITIZING PROGRAM SONOBUOY REFRACTIONS
1 REM
Z INIT
3 GO TO 100
           MULTICS LOGIN
56 REM
57 FIND 7
58 CALL "LINK",100
59 RETURN
100 DIM AS(40),85(40),ZS(1),QS(1)
110 PAGE
120 PRINT 032,26:2
130' SET KEY
140 SET DEGREES
                PROGRAM LINDIGIT REFRACTION DIGITIZING___"
145 PRINT "
150 PRINT "Enter heading for sonobuoy"
160 INPUT AS
170 PRINT "_Enter date of sonobuoy run"
180 INPUT BS
190 PRINT "__Enter horizontal sound velocity (in km/sec)"
200 PRINT " (default = 1.485 km/sec)
                                                                   ":
               (default = 1.485 \text{ km/sec})
210 B1=1.485
220 INPUT VS
230 IF VS="" THEN 250
250 PRINT "___Enter average vertical sound velocity (in km/sec)"
260 PRINT " (default = 1.5 km/sec)"
240 B1=VAL(V$)
270 B7=1.5
280 INPUT VS
290 IF VS="" THEN 310
300 B7=VAL(VS)
                                                                    ~ ";
310 PRINT "___Enter number of layers to be digitized:
320 INPUT N1
330 PRINT — How many points per layer do you wish to pick?"
340 PRINT " (default = 5)
350 N2=5
360 INPUT VS
370 IF VS="" THEN 390
380 N2=VAL(VS)
390 GOSUB 420
400 GO TO 630
410 REM FOLLOWING LINES ARE A SUBROUTINE TO SET ORIGIN AND SCALE
420 PRINT "L***** Position sonobuoy on digitizing tablet
430 PRINT "__Set the origin of the sonobuoy record."
440 INPUT &8:X,Y,Z$
450 PRINT "GGG__Determine the scaling factor:"
460 PRINT "_Mark the time tick at the bottom of the record."
470 INPUT 28:X,Y,Z$
480 PRINT "GGG";
            CALCULATE ANGLES. FOR COORDINATE ROTATION
500 A1=SIN(ATN(Y/X))
510 A2=Y/X
520 A3 = COS(ATN(Y/X))
530 PRINT "_How many seconds long is the record? ";
540 INPUT S.
545 X=Y*A1+X*A3
550 83=S/X
560 PRINT "_
            ___DO YOU WISH TO CHECK THE TIME REFERENCE MARKS?"
570 INPUT Q$
580 IF QS="N" THEN 620
590 IF Q$ <> "Y" THEN 560
600 GOSUB 2110
```

```
610 IF Z<8 THEN 430
 620 RETURN
 630 PRINT "LDOES THE RECORD HAVE A DEEP WATER DELAY?"
 640 INPUT QS
 650 IF QS="N" THEN 760
 660 IF QS<>"Y" THEN 630
 670 PRINT "_WHAT IS THE PRECISE WATER DEPTH (in 2 way seconds)?"
 680 INPUT B6
 690 PRINT "__MARK THE SEAFLOOR AT THE FIRST RECORDER TRACE (x=0)."
 700 INPUT @8:X,Y,Z
 710 PRINT "GGG";
 720 X=(Y+A1+X+A3)+B3
 730 D1=B6-X
 740 B4=D
 750 GU TU 930
 760 PRINT "__MARK THE DIRECT ARRIVAL WHERE IT INTERCEPTS THE FIRST"
 770 PRINT "RECORDER TRACE (x=0)."
 780 D1=0
 790 INPUT &8:X,Y,ZS
 800 B4 = (Y * A1 + X * A3) * B3
 810 PRINT "GGG__MARK THE SEAFLOOR REFLECTOR AT THE FIRST TRACE (x=0)."
 820 INPUT @8:X,Y,Z$
 830 PRINT "GGG";
 840 B6=(Y*A1+X*A3)*B3
 850 B6=B6-B4
 860 PRINT "_
              _DO YOU WISH TO INPUT A SEAFLOOR TIME?
 880 INPUT QS
 890 IF QS="N" THEN 930
 900 IF Q$ <> "Y" THEN 860
 910 PRINT " SEAFLOOR TIME (2-WAY SECONDS):
 920 INPUT 66
 930 REM THE FOLLOWING VARIABLES ARE:
 940 REM
              V1 - ASSUMED SEAFLOOR VELOCITY
               01 - OUTPUT DEVICE NUMBER
 950 REM
 960 V1=1.55
 970 01=32
. 980 N3=1
 1010 REM CALCULATE ASSUMED SEAFLOOR REFRACTOR, VELOCITY = 1.55 KM/SE(
               __DO YOU WISH TO ADD AN ASSUMED SEAFLOOR REFRACTOR?
 1020 PRINT "_
 1030 INPUT QS
 1040 IF &S="N" THEN 1180
 1050 IF Q$<>"Y" THEN 1020
 1060 N1=N1+1
 1065 DIM D(N1,N2),R(N1,N2)
 1066 D=0
 1067 R=0
 1070 N3=2
 1080 PRINT "__WHAT IS THE SEAFLOOR VELOCITY:"
1090 PRINT " (default = 1.55 km/s)
 1100 INPUT VS
 1110 IF VS="" THEN 1130
 1120 V1=VAL(VS)
 1130 FOR I=1 TO N2
 1140 D(1,1)=1*2
 1150 R(1,I)=(B1+D(1,I)+B6+(V1+V1-B7+B7)*0.5)/V1+B4
 1160 D(1,I)=D(1,I)+B4
 1170 NEXT I
 1175 GO TO 1260
 1180 DIM D(N1,N2),R(N1,N2)
```

1190 D=0

```
1200 R=0
1260 PRINT "LSTART DIGITIZING THE DATA POINTS"
1280 PRINT "_
              Pick first the direct time, D(i), and then the ref-"
1290 PRINT " ractor time, R(i), for each data point. ";
1295 PRINT USING "20,"" picks""": 2*N2
1300 PRINT " must be made for each refractor.__"
1310 FOR I=N3 TO N1
1320 FOR J=1 TO N2
1330 INPUT @8:X,Y,Z$
1340 D(I_{J}) = (Y * A1 + X * A3) * B3 + D1
1350 PRINT USING 1360:D(1,J)
1360 IMAGE "GGG", 30.30, S
1365 IMAGE "GG", 30.30,S
1370 INPUT @8:X,Y,Z$
1380 R(I,J) = (Y * A1 + X * A3) * B3 + D1
1390 PRINT USING 1365:R(I,J)
1400 NEXT J
1410 PRINT USING 1420:
1420 IMAGE / "GGG" S
1430 NEXT I
1440 PRINT 632,26:0
1450 PRINT "___DO YOU WISH TO SEE A LINFT FORMATTED DATA LIST?"
1460 INPUT QS
1470 IF QS="N" THEN 1500
1480 IF Q$<>"Y" THEN 1450
1490 GOSUB 1530
1500 END
1530 REM GOSUB TO WRITE OUTPUT LIST AND LINFT FORMATTED
1540 REM
                 OUTPUT SET TO TAPE
1550 PRINT "L
               LINFT FORMATTED OUTPUT LIST"
1560 PRINT
1570 PRINT 201,12:A$
1580 PRINT @01,12:8$
1590 PRINT 201,12: USING 1600:87,81,-84
1600 IMAGE 30.40,30.40," 1.0000",40.30
1610 PRINT #01,12:"
                     1
1620 FOR I=1 TO N1
1630 PRINT 201,12: USING "2x,20,5":N2
1640 NEXT I
1650 PRINT 201,12: USING "/":
1660 PRINT 201,12:"1.5000"
1670 FOR I=1 TO N1
1680 FOR J=1 TO N2
1690 IF 01<>32 THEN 1730
1700 PRINT @01,12: USING 1710:D(I,J),R(I,J)
1710 IMAGE 2(30.30),S
1720 GO TO 1750
1730 PRINT @01,12: USING 1740:D(I,J),R(I,J)
1740 IMAGE 2(40.30),S
1750 NEXT J
1760 PRINT 001,12:
1770 NEXT I
1780 PRINT 001,12:" 0"
1790 IF 01<>32 THEN 1870
1800 PRINT "____DO YOU WISH TO WRITE THE OUTPUT TO TAPE?"
1810 INPUT Q$
1820 IF Q$="N" THEN 1870
1830 IF GS<>"Y" THEN 1800
1835 01=1
1840 GOSUB 1890
```

```
1860 GO TO 1570
1870 PRILT 832,26:0
1875 PRINT 201,2:
1880 RETURN
1890 REM FIND TAPE FILE AND MARK
1900 PRINT "LINSERT THE OBJECT TAPE IN THE TAPE READER."
1910 PRINT "__WHICH TAPE FILE DO YOU WISH TO WRITE TO?"
1915 PRINT "(TYPE [999] FOR A TAPE LIST)"
1920 INPUT N
1922 IF N<999 THEN 1930
1925 GOSUB 2300
1928 GO TO 1910
1930 PRINT @01.0:0.0.1
1940 FIND 201:N
1950 INPUT 201:CS
1960 PRINT "__THE HEADER OF THAT FILE READS:"
1970 PRINT CS
1980 PRINT #01.0:0,0.0
1982 PRINT "__DO YOU STILL WISH TO WRITE TO THIS FILE?
1984 INPUT QS
1986 IF QS="N" THEN 1910
1988 IF G$<>"Y" THEN 1982
1990 PRINT "__DO YOU WISH TO MARK THIS FILE? ";
2000 INPUT QS
2010 IF QS="N" THEN 2090
2020 IF Q$<>"Y" THEN 1990
2030 PRINT "__ARE YOU SURE ?
2040 INPUT QS
2050 IF QS="N" THEN 1910
2060 IF G$<>"Y" THEN 2030
2070 FIND 201:N
2080 MARK &01:1, (8+N1) +80
2090 FIND 201:N
2100 RETURN
2110 REM
           GOSUB TO CHECK REFERENCE PICKS
2120 PRINT "LYOU CAN HERE MAKE ANY NUMBER OF DATA PICKS IN ORDER"
2130 PRINT "TO CHECK OUT YOUR REFERENCE SYSTEM. WHEN YOU ARE"
2140 PRINT "SATISFIED, PRESS BUTTON NUMBER 1 ON THE CURSOR."
2150 PRINT "TO RESET THE ORIGIN, PRESS BUTTON NUMBER 2"
2160 INPUT @8:X,Y,Z
2170 IF Z>1 THEN 2210
2180 X = (Y * A1 + X * A3) * B3
2190 PRINT USING """GG"", 20.30":X
2200 GO TO 2160
2210 RETURN
-2300 REM
           SUBROUTINE TO PERFORM TAPE LIST AT ANY DEVICE
2305 PAGE
2310 PRINT 801,0:0,0,1
2320 FOR N=1 TO 999
2330 FIND &01:N
2340 INPUT 001:C$
2350 PRINT CS
2360 CS=SEG(C5,9,4)
2370 IF CS="LAST" THEN 2390
2380 NEXT N
2390 PRINT 001,0:0,0,0
2400 RETURN
```

```
430 INPUT 08
4.0 IF 08="N" THEN 470
450 IF 08<2"" THEN 470
450 IF 08<2"" THEN 420
460 GOSUB 2310
470 GERB3
480 PRINT " dropped."
500 IMPUT DRIXY,28
500 IMPUT DRIXX,28
500 IMPUT DRIXX,2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    The order is a direct time followed by n reflection"
                                                                                                                                                                                                                                                          210 PRINT "Enter average vertical sound velocity (in km/sec);
212 PRINT " (default = 1,500 km/s)"
214 87=1,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        :`
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           585 C6=n
590 print "L_ arf you picking data points off two records:
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     PRINT "LPosition sonobuoy on digitizing tablet."
PRINT "Set the origin of the sonobuoy record."
INPUT BRIXY.28
PRINT "Detrimine the scaling factor:"
INPUT BRIXY.28
INPUT BRIX.Y.28
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        420 PRINT "BO YOU WISH TO CHECK THE TIME REFERENCE MARKS:
                                PRINT "___Enter horizontal sound velocity (in km/sec) PRINT " (default = 1.485 km/s)"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   :`
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               ___fnter number of layers to be digitized:". ( A maximum of 14 is altowed. ) ".
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           PRINT "Enter hydrophone depth lower (in feet):
INPUT 82
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  640 PRINT "___START DIGITIZING THE DATA POINTS" 650 PRINT " The season
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      ASHCOS(ATN(Y/X))
PRINT "How many seconds long is the record:
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        610 IF D$="Y" THEN 1070
                                                                                                                                                                                                                                                                                                                                                                    IF VS="" 14FN 210
                                                                                                                                                                                                                             200 81=VAL(VS)
INPUT BE
                                                                                                            P1=1.485
                                                                                                                                                    INPUT VS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   410 RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    630 01=-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          580 N7=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  570 R=P
```

```
times, where n is the number of layers specified above." When finished, press u.d. key \#4 and digitize any point."
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1000 PRINT "__MARK THE SEAFLOOR ARRIVAL ON THE FIRST RECORD"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          1130 PRINT "START DIGITIZING DIRECT TIMES"
1140 PRINT To stop digitizing, bress u.d. key #4 and"
1145 PRINT " digitize any point."
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1060 GO TO 1790
1070 RFM OPTION TO PICK TIMES FROM TWO SEPARATE RFCORDS
1080 01=1
                                         (A maximum of 40 traces is allowed.)"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1190 IF F1<>4 THEN 1240
1200 PRINT USING """ P""S":
1210 NS=NX-1
1220 I=1-2
1230 GO TO 12PO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1000 PRINT USING 1010:R(J,1);
1010 IMAGE "G",30,30,5
                                                                                                                                                                                                                                                                                        810 M3=N3+1
820 M1)=X+93
820 M1)=X+93
830 PRINT USING R40:D(1);
840 IMAGE "GGG_"20,30,50
850 FOR J=1 TO N1
860 INPUT #8:X+X-2$
870 X=Y+A1+X+A3
880 IF F1=3 THEN 1040
900 IF F1=2 THEN 1020
910 IF F1<0 THEN 990
910 IF F1<0 THEN 990
920 PRINT USING """F",5";
930 IF J=1 THEN 960
940 J=1-2
950 GO TO 1020
660 PRINT " times where r
670 PRINT " When finished
675 PRINT " (A maximum of
680 FOR 1=1 TO 40
690 INPUT BR:XXXX25
700 X=Y*A1+X*A3
710 IF F1=3 THFN R10
730 PRINT USING """R"",S";
740 I=1-1
                                                                                                                                                                                                                                                                             PRINT USING 1010;R(J.I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1170 X=Y*A1+X*A3
1180 IF F1=3 THEN 130C
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          1160 INPUT BR:X.Y.ZE
                                                                                                                                                                                                                       INPUT BR: X.Y.75
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1150 FOR 1=1 TO 40
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1110 X=Y+A1+X+A3
                                                                                                                                                                                                                                       X=Y+A1+X+A3
                                                                                                                                                                                                                                                         R(J.1)=X+R?
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     990 P(J.1)=X+83
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   980 60 10 1040
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1120 P1=X+R3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1030 NEXT J
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1050 NFXT 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1040 F1=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               970 1=1-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1020 F1=0
                                                                                                                                                                                                    1=1-1
                                                                                                                                                                                                 750
760
770
780
790
```

```
( U.D. KFY #5";
                                                                                                                                                                                                                                             1370 GOSUR 2310

1380 PRINT "MARK THE SEAFLOOR ARRIVAL ON THE SECOND RECORD"

1390 INPUT 3R:x/x/28

1400 X=7x41+xx43

1410 P=2x+B3

1420 P=2+B3

1430 PRINT "JJJ START DIGITIZING REFLECTION TIMES"

1450 PRINT " any point"

1450 FRINT " any point"

1460 FOR 1=1 TO N3

1470 IF FI<>4 THEN 1560

1490 J=3-1

1500 INPUT 3R:x/x/28
                                                                                                                                                                       :`
                                                                                      1290 NFM SECOND RECORD
1310 PRINT "LPLACE SECOND RECORD ON THF DIGITIZING TABLET."
1320 GOSUB 290
1330 PRINT "__DO YOU WISH TO CHECK THE TIME REFFRICE MARKS:
1340 INPUT 0$
1350 IF 0$="M" THEN 1380
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1800 R6=(R(1,1)-B4)+B7+1000/2
1810 PRINT "LCUGGESTEP PROCEDURE:"
1820 PRINT "__ 1. MAKE COPY OF INPUT PARAMETERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1560 PRINT USING "/,""666", 30, 30, 5"; 0(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1530 PRINT USING 1010:R(J.I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1730 PRINT USING 1740;R(J.I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1690 PRINT USING """,5";
1700 J#J-2
1710 GO TO 1750
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1520 PRINT USING """R"", S";
                  1250 D(1)=X+B3
1260 PRINT USING 1270:D(1)
1270 IMAGE 1,"GG",20,30,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     <u>~</u>
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1F F1<>4 THEN 1720
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1570 FOR 15 17 10 N1
1580 INPUT 88:xxx28
1590 X=Y*A1*X*A3
1600 IF F1=3 THFN 1790
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1610 IF F1=2 THFN 1770
1620 IF F1=5 THFN 1750
1630 IF F1<>4 THEN 1720
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1740 IMAGE "6",30.30,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        IF J<>1 THEN 1690
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1650 1=1-1
1660 J=N1-1
1670 PRINT USING """
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1720 P(J.1) = X+P3+P3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   GO TO 1750
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1550 60 10 1770
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1790 R4=-0(1)
1240 K3=N3+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1760 NEXT J
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          1540 3=3+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1770 F1=0
                                                                       1280 11=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        079
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1680
```

```
*15"
                                                                                                           .11
                                                             #12"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           2160 IMAGE "Conversion factor for second record is".2d.7d." mm/sec" 2170 IMAGE "Reference boint on first record is".3d.3d." sec." 2190 IMAGE "Reference boint on second record is".3d.3d." sec." 2190 IMAGE "Reference boint time difference is".2d.3d." sec." 2200 RETURY
                                                                                                                                                                                                                                                                                                                                                                                                       IMAGE "_Horizontal sound velocity in water a",24,34," km/sec"
IMAGE "_Average vertical sound unimity......
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IMAGE "Delta: time zero correction factor is ","1d.4d," sec"
IMAGE "Hydrobiones dropped at a direct time of",2d.2d," sec"
IMAGE "",3d," (ayers were picked"
IMAGE "",3d," traces were picked"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         2320 PRINT "YOU CAN HFRE MAKE ANY NUMBFR OF DATA PICKS IN ORDER"
2330 PRINT "TO CHECK OUT YOUR REFERENCE SYSTEM. WHEN YOU ARF"
                                                                                                                                                                                                                                                                                                                                                                                                                                             IMAGE "Average vertical sound velocity m.,2d.,3d," km/sec" image "Mater depthm",5d,1d," meters" image "Hydrophone depth m",4d,1d," feet" imversion factor is",2d,6d," sec/millimeter"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 2340 PRINT "SATISFIED, PRESS BUTTON NUMBER 1 ON THE CURSOR."
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        2110 PRINT "JJDATA PICKS WERE FROM TWO SEPARATE RECORDS"
2120 PRINT USING 2160:83
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            2220 PRINT "LTABLE OF DIGITIZED PICKS: D(J);R(1,J)JJ"
MAKE COPY OF DIGITIZED PICKS
SAVE RAW DATA ON TAPE
AND HYDROPHONF DELAYED RELEASF"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        2210 RFM PRINTS OUT DATA TABLE (1f # of layers < 9)
                                                               CORRECTION AND GO TO X2
                                                                                                           GO DIRECTLY TO X7 - T2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       GOSUN TO CHECK REFERENCE PICKS
                                                                                                                                       Drints out list of Darageters
                                                                                                                                                                  INPUT PARAMETER LIST_
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              FOR 1x1 TO N3
PRINT USING "/.30.30.5":D(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            2260 PRINT USING "30.10.5":R(J.1)
                                                                                                                                                                                                                                                                                                  USING 2030:86
USING 2050:88
                                                                                                                                                                                                                                                                                                                                                         1980 PRINT USING 2070:85
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     2140 PRINT USING 2180:PZ
                                                                                                                                                                                                                                                                            2040;R2
                                                                                                                                                                                                                                                                                                                                   USING 2040:04
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 2130 PRINT USING 2170;P1
                                                                                                                                                                                                                                                      2020187
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         2150 PRINT USING 2190:P3
                                                                                                                                                                                                                                  1920 PRINT USING 2010:81
                                                                                                                                                                                                                                                                                                                                                                                   USING 2080:N1
                                                                         .
.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          2360 IF 2#8 THEN 2400
2370 X#(Y*A1+X*A3)*H3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     2350 INPUT BR:X.Y.Z
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  2240 PRINT USING "/
2250 FOR J=1 TO N1
                                                                                                                                                                                                                                                    1930 PRINT USING 2
1940 PRINT USING 2
1950 PRINT USING 2
1960 PRINT USING 2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        2390 GO TO 2350
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IMAGE "T
                                                                                             1860 PRINT "
                                                                                                                                                                    1890 PPINT "L
                                                                                                                                                                                                              1910 PRINT BS
                                                                                                                                                                                        1900 PPINT AS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    2380 PRINT X
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              2400 RFTURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       2280 NEXT 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               2300 RETURK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    2270 NEXT J
                                                                 PRINT
                                                                                                                                                                                                                                                                                                                                                                                     PRINT
                       PRINT
                                             PRI & d
                                                                                   1856 PRINT
                                                                                                                                                                                                                                                                                                                                                                                                       2000 PRINT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             2290 PPINT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     2310 REM
                                           1850
1855
                                                                                                                                                                                                                                                                                                                                                                                   1990
                                                                                                                                                                                                                                                                                                                                                                                                                           2010
2020
2030
2040
2050
2050
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          2070
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      2100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  2230
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              2080
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                2090
                                                                                                                               (
```

1 REW SLONIGIT SUPROUTINE HDRC
44 REW GO 100
44 REW GO 10 X2-72
45 GOSUR 4.07
47 RESUR 4.09
410 DRINT "THIS SECTION WILL NO ETHERS."
410 DRINT "THIS SECTION WILL NO ETHERS."
410 DRINT "THIS SECTION WILL NO ETHERS."
4110 DRINT "THIS SECTION WILL NO ETHERS."
4120 DRINT "THIS SECTION WILL NO ETHERS."
4130 DRINT "THIS SECTION WILL NO ETHERS."
4140 DRINT "THIS SECTION WILL NO ETHERS."
4150 DRINT "THIS SECTION WILL NO TOWN WANT"
4150 DRINT "THIS SECTION WILL NO TOWN WANT"
4150 DRINT "THIS SECTION WILL NO TOWN WANT"
4150 DRINT "THIS SECTION "T

(

182

}

```
50 CALL "LINK", 1

51 PFIURN

64 REF LINK TO FDIT AND OUTPUT SEGNENT

65 FIUD S

66 CALL "LINK", 1

67 RETURN

90 REM SUBPROGRAM TO DO X2-T2 AND PLOT

100 DIF T1(N1), T2(N1), 15(N1), N(N1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               NO YOU WISH TO SEF DATA FROM ALL LAYERS?"
                                                              48 RFM RETURN TO HYDROPHOUE RFLFASE DFLAY CORRECTION 49 FIND 3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   17(1) = (12(1) +14(1) +2-12(1) +16(1) +7)/(12(1) +12(1))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            T3=SQR((S)-S1"2/NS(T))/(NS(T)-1))
T4=SQR((S4-S1"2/NS(T))/(NS(T)-1))
T5=SQR((S4-S1"2/NS(T))/(NS(T)-1))
T5(T)=(NS(T)+S5-S1+S3)/(NS(T)+(NS(T)-1)+T4-T4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  T1(1)*(N5(1)+S5-S1+S3)/(N5(1)+S2-S1-2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             12(1)=(S3+S2-S1+SS)/(NS(1)+S2-S1*2)
SLOBIGIT - SUPROUTINE X212
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     530 RFM GOSUR ROUTINE FOR LLSG DATA 540 PRINT USING "1/1/";
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1F P(1,1)<=0 THEN 360
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         570 IF 0$="Y" THEN 740
580 IF 0$<>"N" THEN 550
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            02=((0(1)+84)+81)*2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       IF N(I)<=0 THEN 570
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1F D(J)<0 THEN 360
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IF N(J)>0 THEN SOO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           120 N=N3

130 F1=0

140 E2=1

150 IF N(I)<=0 THEN S7

170 S1=0

170 S3=0

210 S4=0

220 S4=0

220 S4=0

230 F0R J=1 T0 N3

240 D2=((D(J)+B4)-P)

250 P2=(R(L_J)+B4)-P

250 P3=(R(L_J)+B4)-P

250 P3=(R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         16(1) = SQR(1/11(1))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                500 17(J)=(12(J)+14(J)
510 17(J)=S0P(17(J))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1F 1=1 THEW 520
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            PRINT 832,76:0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           550 PRINT "
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            60 10 470
           1 REW SI
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  SZO NEYT I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   J=1-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1-1-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               460
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        067
```

```
IMAGE 3D.4xx.6x.3D.4xx.2(40.3D.4xx).13x,40.5D
PRINT "J.(1) Depth to the top of the refracter: V(rms).intercept"
PRINT "J(2) Interval velocity calculated from Dix" equation."
 :
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           PRINT "DO YOU WANT TO SEE THE PLOT AT A DIFFERENT SCALE"
1100 PRINT USING "27,"" DEPTHK1J VELOCITY
1100 PRINT USING 1200:
1200 IMAGE 10T" (KM/SEC)
1210 FOR 1" TO N1-1
1210 FOR 1" TO N1-1
1220 PRINT "LAYER DELFTED"
1240 GO TO 1280
1250 PRINT "LAYER DELFTED"
1250 PRINT "LAYER DELFTED"
1250 PRINT "LAYER DELFTED"
1260 PRINT "LAYER DELFTED"
1270 IMAGE 3D,4x,4D,3D,4x,3(4D,3D,4x),5D,5D,5D
1280 PRINT USING 1310:1,76(1),73,73,76(1),75(1)
1300 PRINT USING 1310:1,76(1),73,73,76(1),75(1)
1301 IMAGE 3D,4x,4D,3D,4x,2(4D,3D,4x),13x,4D,5D
1300 PRINT "J(2) Interval velocity calculated from Dix" ending 1300 PRINT "J(2) Interval velocity calculated from Dix" ending 1300 IF GS,700 THEN 1360
1300 IF GS,700 THEN 1360
1300 REM INITIALIZING PLOTTING VALUES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PRINT "X-AXIS INTERVAL, Y-AXIS INTERVAL:
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             VIFWPORT R.95,128.21,8.46,100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   PRINT "WINDOW: X1.X2.Y1.Y2;
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         XT="KILOMFTERS - SOUARED"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      YE "SECONDS ! SQUARED"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       FOR IRX1 TO XZ STEP X3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              MOVE X1+(X7-X1)/10,Y2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF 0$="N" THEN 1580
IF 0$<>"THEN 1490
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               FOVE (X1+X2)/2,Y1
FOR I=1 TO LEN(X$)/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         FOR 1=1 TO LEN(YE)/2
                                                                                                                                                                                                                                                                                                                                                                                                         X2=(INT(E1/5)+1)+5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           WINDOW X1.X2.Y1.Y2
                                                                                                                                                                                                                                                                                                                                                                                                                                            Y2=(INT(E2/5)+1)+5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    INPUT X10X20Y10Y2
                                                                                                                                                                                                                                                                                                                                                                                                                           Y1=1NT (12(1)/5)+5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          MOVF X10(Y2+Y1)/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     PRINT "JJJ"; X4;
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          PRINT "HHHHH";
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              PRINT "J"; AS;
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      PRINT "HJ":1;
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      INPUT X3,Y3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              G0SUR 1590
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            AXIS X 3.Y 3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      G0SUB 1590
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           1790 PRINT "K";
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       60 TO 2140
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PRINT "H";
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       MOVE I.Y1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 INPUT 05
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           NFX1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      NEXT I
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          PAGE
                                                                                                                                                                                                                                                                                                                                                                                       1420
1430
1450
1450
1470
1490
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1500
1510
1520
1530
1540
1560
1560
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1600
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1620
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1590
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            640
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1650
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1660
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               0291
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1680
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 0691
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   1700
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1710
```

```
1800 NEXT I
1820 Z$=56(Y$-1.7)
1830 PRINT Z$:"HJ";
1840 NEXT I
1850 NOW X$1.I
1860 NOVE X$1.I
1870 PRINT "HHH"; I;
1870 NEXT I
1870 PRINT "HHH"; I;
1870 NEXT I
1870 NEXT I
1870 NEXT I
1870 PRINT "HHH"; I;
1870 NEXT I
1870 NEXT I
1870 NEXT I
1870 NEXT I
1970 IF NCI)<
1970 IF NCI)<
1970 IF NCI)<
1970 IF P2-XY THEN 2070
1970 II P2-XY THEN 2070
```

```
CULTOR PERFORMS THE FOLLOWING FUNCTION CALLED RY THE USER DEFINANCE KFYS:"

1 OF PRINT REPOYES OR REINSERTS AN ENTIRE LAYER"

1 OF PRINT REPOYES OR REINSERTS AN ENTIRE TRACE"

1 OF DRINT REPOYES OR REINSERTS AN ENTIRE TRACE"

1 OF DRINT REPOYES OR REINSERTS AN ENTIRE TRACE"

1 OF DRINT REPOYES OR REINSERTS AN ENTIRE TRACE"

1 OF DRINT REPOYES OR REINSERTS OUTPUT ON THE SCREEN'

1 OF DRINT REPOYER FOLITING FUNCTIONS, PRESS THE DESIRED U.D."

2 OF DRINT REPOYER FOLITING FUNCTIONS, PRESS THE DESIRED U.D."

2 OF DRINT REPOYER FOLITING FUNCTIONS, PRESS THE DESIRED U.D."

2 OF STORE DRINT REPOYER FOR FOLITING

2 OF STORE DRINT REPOYER OF POINTS PER LAYER FOR EDITING

2 OF STORE DRINT REPOYER TO FOLICE TOWN S."

2 OF STORE DRINT REPOYER TO FOLICE TOWN S."

2 OF STORE DRINT REPOYER TO FOLICE TOWN S."

2 OF STORE DRINT REPOYER TOWN S."

2 OF STORE DRINT REPOYER TO FOLICE TOWN S."

2 OF STORE DRINT REPOYER TOWN S."

3 OF STORE DRIVE STORE S."

3 OF STORE DRIVE STORE S."

3 OF STORE DRIVE STORE S."

3 OF STORE S. THE STORE S."

4 OF STORE S. THE STORE S. THE STORE S. THE STORE S."

4 OF STORE S. THE STORE S. THE STORE S."

4 OF S
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               310 NCI)=SGH(H(I))+K
320 NEXT I
330 PETHPN
340 PRINT "LHHMDER OF POINTS PER LAYFR:__"
350 PRINT "LA NEGATIVE NUMBER DELFTFS THAT LAYER FROM THE CALCULATION"
350 PRINT "_A NEGATIVE NUMBER DELFTFS THAT LAYER FROM THE SALCHLATION"
350 PRINT "_WHICH LAYFR DO YOU WISH TO DELFTF OR INSERT"
350 H(I)=-N(I)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     REM RETURN TO HYDROPHONE DELAY RELEASE CORRECTION FIND 3
CALL "LINK",1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    REM LIST OF SLOWI FORMATTED OUTPUT TO SCREEN
                                                                                                                                                                                                                                                                                                                                                                                                                         REP PRINT OUT TABLE OF RESIDUAL VALUES
   SUBROUTINE EDIT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       REM SLOWI FORMATTED DUTPUT TO TAPE
                                                                   24 REM DELETE/REINSFRT A LAYER
25 GOSUB 340
                                                                                                                                                                                     REM DELETF/RFINSFRT A TRACE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    -ANNTHER LAYERT"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  44 RFM RFTURN TO X7-T7
45 FIND 4
1 REM SLODIGIT
2 GO TO 100
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 CALL "LINK",130
                                                                                                                                                                                                                                                                                                           REF EDIT POINTS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               G05UB 1150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    00SUB 560
                                                                                                                                                                                                                                   605UR 46N
                                                                                                                                                                                                                                                                                                                                              G05UR 800
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       RETURK
                                                                                                                                                            RETURN
                                                                                                                                                                                                                                                                       RF TURN
                                                                                                                                                                                                                                                                                                                                                                                  RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           RFIURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          PE TURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        20
20
20
80
80
                                                                                                                                                                                                                                                                                                                                                                                                                                                         37
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           07
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  ۲,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      42
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    4.6
```

```
2.00 PRINT 10 PRINT 10 PRINT 10 PRINTS FOR FACH TRACE ""LLIANTED"."
2.00 PRINT 10 PRINT 10 PRINT 10 PRINTS FOR FACH TRACE ""LLIANTED TO THE FEB OF PRINTS FOR FACE TO THE FEB OF PRINTS FO
```

```
1340 PRINT "____DO YOU WISH TO WRITE THIS DATA SET ONTO A TAPE FILE?"
1350 INPUT Q$
1360 IF OS="N" THEN 1880
1370 IF Q$<"N" THEN 1340
                                                                                                                                                                                                                         REM SECTION TO WRITE SLOWI FORMATTED OUTPUT TO TAPE AND SCREFN PRINT USING "P40A/40A/":85.48
PPINT USING 1180:86.87.P1.84.82
IMAGE 70.,2(30.40)," 1.0000",40.30,70,
PRINT " 0 0 1 1 1 1 1
                                                                                                                                                          PRINT "___THIS OPTION HAS NOT BEEN MADE AVAILABLE YETIGGG"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             PRINT " WHICH FILE DO YOU WISH TO WRITE TO?"
PRINT " (IF YOU ARE IN BOURT AS TO WHICH FILE IS FREE,"
PRINT " TYPE 999 TO BO A TLIST, WHICH WILL INDICATE"
PPINT " THE FIRST AVAILABLE FILE)"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IS THE FILE YOU ARE WRITING TO ALREADY MARKED?"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |F |<>999 THEN 1550
|F |<=255 THEN 1470
|PRINT "FILF NUMBER IS 100 LARGE !!GGGGGGGGGGG"
                                                                                     PRINT "_NO PICK WAS EVER MADE FOR THAT POINT!GG"
                                                                                                                       PRINT "THAT POINT HAS NEVER BEEN DELETFOIGG"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   PRINT "FILE NUMBER IS TOO LARGE !! GGGGGGGGG"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1530 PRINT "WHICH FILE BO YOU WISH TO WRITE TO?"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                IF R(I.J)<=0 THEN 1320
PRINT USING "2(40,30)5":0(J) PR(I.J)
                                                                                                                                                                                                                                                                                                                                                  PRINT USING "46S":N(I)
             1050 IF R(1,J)>N THEN 1090
1060 IF R(1,J)=N THEN 1070
1050 R(1,J)=R(1,J)
1060 RETURN
1060 PRINT "_NO PICK WAS EV
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1610 IF 0$<>"N" THEN 1580
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF 05="Y" THFN 1640
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1550 IF IC=255 THEN 1580
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1F 0(J)<0 THEN 1320
                                                                                                                                                                                                                                                                                                                                                                                                                         IF N(1)>0 THEN 1270
                                                                                                                                                                                                                                                                                                                                             1210 PRINT USING "40
1220 NEXT 1
1230 PRINT 1
1240 FOR INT 1
1250 IE N(1)>0 THEN
1260 FOR JET TO N3
1290 IF R(1, J)<0 THEN
1300 IF R(1, J)<0 THEN
1310 PRINT USING "2(
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1480 FOR 1=1 TO 200
                                                                                                                                                                                                                                                                                                                             FOR 1=1 TO N1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           INPUT A1,9:H$
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      FIND 01,27:1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  GO TO 1380
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      1570 GO TO 1530
                                                                                                                                                                                                  G0SUB 230
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              PRINT HE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             1590 INPUT 0$
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1540 1MPUT 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1580 PPINT "
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           INPUT
                                                                                                        PETURN
                                                                                                                                                                                 RETURN
                                                                                                                                            RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NFXT I
                                                                                                                                                                                                                     PETURN
RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PAGE
                                                                                                                                                            11120
11140
11150
11150
11160
11180
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1410
1420
1430
1460
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1460
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1490
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1500
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              1510
                                                                                                        1080
```

```
1620 FIND 81,27:1
1630 FARK 81,28:1,7000
1640 FIND 81,27:1
1650 PRINT 81,17: USING "40A/40A ":8%A$
1660 PRINT 81,17: USING "40A/40A ":8%A$
1670 PRINT 81,17: USING "40S.81.81.8
1500 PRINT 81,17: USING "40S":N(I)
1700 PRINT 81,17: USING "40S":N(I)
1710 NEXT I TO NI
1720 PRINT 81,17: USING "40S":N(I)
1730 FOR I=1 TO NI
1730 FOR I=1 TO NI
1740 IF N(I)<11 THEN 1860
1750 PRINT 81,12:
1760 K=1
1760 FRINT 81,12: USING "2(40,30)S":D(J),R(I,J)
1860 PRINT 81,12: USING "2(40,30)S":D(J),R(I,J)
1860 NEXT I
1860 NEXT I
1860 NEXT I
1860 NEXT I
1860 PRINT 81,12: USING "2(40,30)S":D(J),R(I,J)
1860 NEXT I
1860 NEXT I
```

16 FEW SLODIGIT SUPROUTINE DUPP/RECOVEP FROW TAPF

4. GET SOC (ALC "LINK", 100

4. SETUR "LINK", 100

4. SETUR "LINK", 100

4. SETUR "LINK", 100

5. CALL "LINK", 100

5. SETUR "LINK", 100

5. SETUR "LINK", 100

5. CALL
Appendix K

Listings of reduction programs

This appendix contains line numbered listings of SLOWI and LINFT. The absolute pathnames for these programs are:

>udd>Marine>JChilds>sonobuoy>slowi.fortran
>udd>Marine>JChilds>sonobuoy>linft.fortran

The introductory comments prefacing the program listings describe the input required. All input is from file05 and all output is targeted for file06. Therefore, file attaches must be made to these files before executing the programs. Both programs have been modified to run on Honeywell 60 series computer under Multics., and are compiled with Honeywell Multics fortran (release 4). The pathnames of the object segments are:

>udd>Marine>JChilds>sonobuoy>slowi
>udd>Marine>JChilds>sonobuoy>linft

Program SLOWI consists of a main program and three subroutines. The main program and subroutines are numbered sequentially, but the subroutines are set off on separate pages.

FORMAT(10A4) FORMAT(3F8.4.F8.3) FORMAT(10F8.3) FORMAT (10F7.3) FORMAT (1514) FORMAT(F7.4) FORMAT (10A4) FORMAT(414) Slope downward in the direction of travel is SQUARED PLOT OF OBLIQUE REFLECTION ARRIVALS, OR RANGE - TPAVEL C LINT - PROGRAM FOR FITTING LINE TO RANGE SQUARED - TRAVEL TIME HANDLES AS MANY AS FIFTEFN TRACES DELINEATED BY UP 10 SEVFNIY-AVELO - average velocity above shallowest refractor whether the option is desired or not. The following distances are true ranges (in kilometers) distance is direct water wave travel time OF SEAFLOOR INCIDENCE COMPUTATION ASSUMES FIRST TRAVEL ISSW2 - specifies input units for XDATA(1) (range). SLOP(1) - incremental slopes of layers in degrees. 1.0000 if all input values are in seconds) the ISSM variables allow for various options to be Slope of layer with respect to the layer will cause the program to skip that layer. specified within the program. The value of each variable is set to either 0 or 1, depending upon above. (e.g. if two successive layers have equal absolute slope, alpha, than SLOP(1) = alpha, SLOP(2) = 0.0 N(1) - number of points per layer. If negative, VM - horizontal sound velocity in water SCALE - scale factor in inches/second. (SCALE = CRUISE - label of cruise, sonobuoy number, etc. REVISED FOR USGS (MENLO PARK, OFFICE OF MARINE GEOLOGY) BY J. CHILDS AND A COOPER Data: XDATA(1),YDATA(1) - pairs of ranges (in (included for refraction data sets only) VLINT - mean vertical sound velocity in water IANOT - date and time of run or sonobuoy ISSWO - specifies type of data initially DELTA - time zero correction in seconds skips slope corrections Card 6 (and 7, if more than 10 (ayers) omits data listing O lists input data O corrects for slope TIME PLOT OF REFRACTION ARRIVALS TIME VALUE IS NORMAL INCIDENCE. 1 SSW0 - 1 SSW1 - 1 SSW2 - 1 SSW3 options are available: is negative. refractions reflections DATE 27 JANUARY 1976 FIVE POINTS EACH. 1 SSW3 = 1 ISSW1 = 1 Card 9 - end INPUT REGUIRED: C AUTH: HOSKINS Card 8 Card S C. rd Card Card Card ANGLE

193

(

```
7.390
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          7.695
                           FORMAT(14)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               10.020
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             xxva((75) • yyval(75) • xdata(75) • ydata(75) • vlave(16) • ortis(15) •
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         depth(16), angle (75), slop(15), alph(15), beta(15), reslo(15),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               8.363
7.138
6.840
7.150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            dimension ianot(10).n(18).xval(75).yval(75).res(75).
                                                                                                                                                                                                                                                                                                                                       FERENT RECORD. ARRANGE THE DATA SETS SO THAT THE REFRACTION WOULD COME FIRST, OR WOULD FOLLOW THE REFRACTION DATA FROM ANOTHER RECORD. WITH REFLECTIONS AND REFRACTIONS FROM THE SAME RECORD, ALWAYS PUT THE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            7.215
7.215
8.000
                                                                                                                                              PROFILES. AFTER EACH DATA SET, A CHECK CARD (ICHECK) MUST BE INSERTED. THE VALUE OF ICHECK SHOULD BE CONTAINED IN THE FIRST TEN COLUMNS OF THE CARD, AND
                                                                                                                                                                                                                                    ICHECK SHOULD BE NEGATIVE; AND IF THE FOLLOWING DATA
1S OF A REFRACTION, ICHECK SHOULD BE POSITIVE.
EACH DATA SET REQUIRES ALL INPUT DATA (DATE.
CRUISE, PARAMETERS, ETC) UNLESS IT IS A REFRACTION FOLLOWING A REFLECTION SET FROM THE SAME RECORD.
 seconds or kilometers; see ISSW2 below)
                                                                                                                                                                                                                                                                                                                           FOLLOWED IMMEDIATELY BY REFRACTION DATA FROM A DIF-
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       hight(15).cruise(10)
FORTRAN STATEMENT FUNCTION NECESSARY FOR MULTICS.
arsin(x) = atan(x/sqrt(1-x++2))
                                                                                                                                                                                          WILL DEPEND UPON WHAT DATA FOLLOWS. IF THERE IS NO SUBSEQUENT DATA, ICHECK SHOULD BE ZERO OR NULL;
                                        - card signalling end of data set
                                                                                                                                 WITH ANY COMBINATION OF REFLECTION AND REFRACTION
                                                                                                                                                                                                                                                                                                             (WE ASSUME THAT THERE WILL BE NO REFLECTION DATA
                                                                                                                                                                                                                         IF THE FOLLOWING DATA IS ANOTHER REFLECTION SET.
                                                                                                                    THIS PROGRAM WILL DO ANY NUMBER OF DATA SETS,
                                                                      m -1 reflection data set follows
                                                                                    m +1 refraction data set follows
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            6.830
6.580
7.020
               and travel times (in seconds).
                                                                                                                                                                                                                                                                                                                                                                                                                                               Example input refraction data set
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               4.638
6.126
5.998
6.826
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 0.100 -0.100 0.000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             5.617
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          5.617
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               4.020
                                                                                                                                                                                                                                                                                                                                                                                                 REFLECTIONS FIRST)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                ioutz6
angle(1)=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SONOBUOY TEST
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1.490
                                         ICHECK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            5.612
5.568
6.619
7.494
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          1 APRIL 1978
                             Final card
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     iines
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              2.020
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             4.790
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                00000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  1.500
0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               0.8
```

194

٠,

```
write(fout.901) issw0.issw1.issw2.issw3
format(" ISSW0=",i2," ISSW1=",i2." ISSW2=",i2." ISSW3=",i2)
write(fout.1005)
format(" NUMBER OF POINTS EACH LAYER")
read(iin,1021) (n(i),is1,15)
                                                                                                                                                                                                                       write(fout,1020) vlint.vh.scale.delta
format(" MEAN VERT SOUND VEL=".f7.4,3x,"HOR120NTAL SOUND ",
"VEL=".f7.4,/" INCH/SEC=",f7.4,3x,"TIME ZERO CORR=",
                                        format("1"," PROGRAM LINEAR FIT", /8x," 2 DECEMBER 1976", /)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       slop(i)=slop(i)/57.29578
INCREMENTAL SLOPES TO ABSOLUTE SLOPES
do 67 i=2,nref
                                                                                                                                                                                                                                                                                                                                                                                 read(iin,900) issu0,issu1,issu2,issu3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   format(" INCREMENTAL LAYER SLOPES") read(iin,1024) (slop(f),i=1,nref) write(iout,1024) (slop(i),i=1,nref)
                                                                                                                                                                                        format(" ",10m4,55m,10m4)
read(iin,2001) vlintovhymomle,deltm
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       write(ioutx1021) (n(i),i=1,nref)
                                                                                                                                                                     urite(iout,1004) cruise,cruise
                                                                                                               write(iout,2007) isnot
                                                                                                                          format(" ",10a4)
write(iout,1003) ianot
format(" ",95x,10a4)
                                                                                                                                                          read(iin,2008) cruise
                                                                                            read(fin,1002) fanot
                                                                                                                                                                                                             lormat(3f8.4, f8.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             do 44 i=1,15
if(n(i)) 45,44,45
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          urite(fout, 1023)
                              write(iout,1000)
                                                                       write(iout,1001)
                                                                                                                                                                                                                                                                                                                                                                                                                                                        nrefec
NUMBER OF LAYERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    Jormat(1017.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               do 61 imlunref
                                                                                                                                                                               ormat (10a4)
                                                                                                                                                                                                                                                                 scall=scale
scal2=scale
do 15 i=1,15
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   format (1514)
                                                                                                       ormat (10s4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  nrefanref+1
                                                                                 format (" ")
                                                                                                                                                                                                                                                                                              depth(i)=0.
                                                                                                                                                                                                                                                                                                         v(ave(i)=0.
                                                                                                                                                                                                                                                                                                                  ortim(i)#0.
                                                                                                                                                                                                                                                                                                                                                                                            format (414)
                                                                                                                                                                                                                                                                                                                             stop(i)=0
1actr=1.0
          scale=1.
                   deltaro.
                                                              C ENTER PARAMETERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               continue
                                                                                                                                                                                                                                                                                                                                                            n(11)*0
                                                                                                                                                                                                                                                                                                                                                  n(16)=0
                                                                                                                                                                                                                                                                                                                                                                       n(18)=0
                                                                                                                                                                                                                                                                                                                                        n(;)=0
                                                                                                                                                                                                                                                      17.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   C CONVERT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    C COUNT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1023
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1024
                                                                                 1001
                                                                                                     1002
                                                                                                                                                                             2008
                                                                                                                                                                                                                                 1020
                                                                                                                                                                                                                                                                                                                                                                                                                                   1005
                                                                                                                                              1003
                                                                                                                                                                                                             2001
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1021
                                                                                                                           2002
                                                                                                                                                                                                                                                                                                                                                                                                              106
                                                                                                                                                                                                                                                                                                                                                                                           006
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             7 7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  4.5
                                                                                                                                                                                                                                                                                                                                       2
                                                                                                                                                                                                            160
161
162
165
165
165
175
175
175
175
176
177
178
178
179
```

```
write(fout.1011) avelo
format(/" Average velocity above shallowest refraction=",17.4)
                                                                                                                                                                                                                                                                                                                                                                                              DVAL",
67 slod(i)=slod(i)+slod(i-1)
c CHECK IF INPUTS ARE REASONABLE OR WITHIN DIMENSIONFD ARRAYS
                                                          if(vlint.gt.1.6.or.vlint.lt.1.4) write(iout.1030)
if(vh.gt.1.6.or.vh.lt.1.4) write(iout.1030)
if(abs/scale).gt.6.) write(iout.1030)
if(abs/delta).gt.5.) write(iout.1030)
format(" INPUT VALUE OFF SCALE")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                       xxval(i)=(xdata(i)+delta)+factr/scal1
yyval(i)=(ydata(i)+delta)/scal2
to use ranges rather than birect water than
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               xxval(i) xxxval(i) - yyval(1) +vlint+sin(slop(j))
                                                                                                                                                                                                                                                                                                                                                                                                                                   format(" LAYER "-12)
read(iin,2003) (xdata(i),ydata(i),im1,layer)
                                                                                                                                                                                                                                                                               read(iin,2003) (mdata(i),ydata(i),im1,ikj)
                                   if(n(i),gt,75) write(iout,1030)
if(abs(slop(i)),gt,0,35) write(iout,1030)
                                                                                                                                                                                                                                                                                                                                                                                               SEC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            if(issw2.ne.0) go to 5
xxval(i)=xxval(i)*vh
TO OMIT SLOPE CORRECTION
if(issw3.ne.0 .or. issw0.ne.0) go to 55
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              if (issw0.ne.0) go to 10 c SQUARE VALUES FOR OBLIQUE REFLECTION TRACES
                                                                                                                                                                if (aveloalt, 1.4) avelomylint
                                                                                                                                                                                                                                                                                                                                                                                                         ANG INC")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   if(xval(i).lt.0.) xval(i)=0.
                                                                                                                                                                                                                                                                                                                                                                                              DDATA TDATA
                                                                                                                           if(issw0.eq.0) go to 19
read(iin,2002) avelo
                                                                                                                                                                                                                                                                                                                                                                     if(issul.ne.0) go to 42
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       HVAL (i) HXVBL(i) *XVAL(i)
                                                                                                                                                                                                                                                       OVER SPECIFIFD DATA POINTS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    yval(i)=yval(i)*yval(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    C SET NEGATIVE RANGES TO ZERO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         sumt2=sumt2+yval(i)
                                                                                                                                                                                                                                                                                                                                                                                                          " TVAL RES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             xva((i)exxxa(i)
                                                                                                                                                                                                                                           if(layer) 80,2,3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        yval(i) myyval(i)
                                                                                                                                                                                                                                                                                                                                                                                   write(iout,1006)
                                                                                                                                                                                                                                                                                                                                                                                                                                                             do 10 imlalayer
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             do 20 imlalayer
                                                                                                                                                                                                                                                                                            format(10f8.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        C FIT LEAST SQUARFS LINE
                                                                                                                                                                                                                                                                                                                     do 82 imj.ikj
                                                                                                                                                   format(f7.4)
                                                                                                                                                                                                                                                                    ikj=(-layer)
                       do 86 im1,15
                                                                                                                                                                                                                                                                                                         ikj=(nref+3)
                                                                                                                                                                                                                                                                                                                                             nrefanref-1
                                                                                                                                                                                                                                                                                                                                 n(1) mu(1+1)
                                                                                                                                                                                                                                                                                                                                                                                               format (/"
                                                                                                                                                                                                                               (ayeren(j)
                                                                                                                                                                                                     C READ DATA POINTS
                                                                                                                                                                                                                                                                                                                                                           go to 84
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 continue
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 sumt2=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     SOUARES
                                                                                                                                                                                                                    ) = j + 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     SUM T
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 COPTION
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     C 0P110N
                                                                                                                                                                                                                                                        SKIP
                                                                                                                                                                                                                                                                                                                                                                                   1006
                                                                                                               1030
                                                                                                                                                    2002
                                                                                                                                                                                         101
                                                                                                                                                                                                                                                                                            2003
                                                                                                                                                                                                                                                                                                                                                                                                                                   1007
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                2
                                                 86
                                                                                                                                                                                                                                                                                                                                 82
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            8.2
                                                                       187
188
190
191
192
193
195
```

```
c FIND DEVIATIONS FROM BEST FITTING LINE
c POSITIVE RESIDUE MEANS DATA POINT GREATER (DEEPER) THAN FITTED LINE
26 do 33 i#1,layer
                                                                                                                                                                                                                                                                                                                               if (kkk-1) 26,12,26
BECAUSE DIRECT WATER WAVE MAY BE DIFFICULT TO DETERMINE AT RANGE
CORRECTION IS APPLIED TO RANGES SO TO MAKE MEAN VERTICAL VFLOCITY
AGREE WITH MATTHEWS TABLES.
                                                                                                                                                                                                       bx(float(layer)*sd2t2-sumd2*sumt2)/(float(layer)*sumd4%
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 depth(j) = (0.75+b+sqrt(1.-(1.5+a)++2.))/(1.-7.25+a++2.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      C MINIMUM DEPTH FOR REFRACTING SURFACE - ASSUMES FLATNESS AND
                                                                                                                                                                                                                                                                                                                                                                                                                                           write(iout,1009) factrowthowh format(" FACTORH", f7.3,3x,"VH APPARENTH", f7.4,3x,"VH SUPPLIEDH", f7.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               C DETERMINE ANGLE OF INCIDENCE ON SEAFLOOR FOR FIRST TRACE
                                                                                                                                                                                                                                      b=(sumd4*sumt2-sumd2*sd2t2)/(float(layer)*sumd4%
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       if(issw0.ne.0.or.i.eq.1.or.j.gt.1) go to 54
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             if(j.ne.1.or.issw0.ne.0) go to 52
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             angle(i) = arcos(cosag) + 57,29578
                                                                                                                                                                                                                                                                                                                 denth(j) #vlave(j) tortim(j)/2.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                res(i)=yval(i)-(a+xval(i)+b)
                                                                                                           sund4#sund4+xval(i)*xval(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          xval(i) = xval(i) + factr+ factr
                                                                                                                                                                         sd2t2#sd2t2+xval(i)+yval(i)
                                                                                                                                                                                                                                                                    if(issw0_ne_0) go to 9
vlave(j)=sqrt(abs(1_/a))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        if (issul.ne.0) go to 47
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          xxval(1) =xxval(1) ofactr
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              cosageyyval(1)/yyval(i)
                                                                                                                                                                                                                                                                                                   ortim(j)msqrt(abs(b))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   OVERBURDEN TO BE ALL WATER.
if(1.5.a-1.) 31,32,32
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C LIST DATA AND COMPUTED POINTS
                                                                                                                                                                                                                                                                                                                                                                                                factr=vlint/vlave(1)
SUM D SQUARES

SUMD2m0.

do 21 im1/layer

sumd2msumd2*xval(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              do SZ im2.layer
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         do 49 imlelayer
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           do 24 imlalayer
                                                                                              do 22 iminiaver
                                                                                                                                                           do 23 iminiayer
                                                                                                                                                                                                                       -sumd2+sumd2)
                                                                                                                                                                                                                                                      -sumd2+sumd2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        vlave(j)=1./a
                                                                                                                                                                                                                                                                                                                                                                                                               vhhevhefactr
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    depth(j)=0.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       ortim(j)*b
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    90 to 26
                                                                                                                                          $ d212=0.
                                                                              .0=1bmus
                                                               D2 SQUARES
                                                                                                                          c SUM 0212
                                                               C SUM
                                                                                                                                                                                                                                                                                                                                                                                                                                                            1009
                                                                                                                                                                           23
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  32
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                3.1
                                                5
                                                                                                             25
                                                                                                                                                                                                                                                                                    Ξ
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          7 %
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           288
289
290
                                                                                                                                         273
274
275
276
276
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   278
279
281
281
282
284
285
286
286
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          295
```

```
if(res(i).lt.-0.3) write(iout.1025) xdata(i).ydata(i).xxval(i).
                                                                                                                                                                                                                                                       if(res(i), it.-0.015. and. issw0.ne.0) write(iout, 1025) xdata(i),
                                                               if(res(i).gt.O.3) write(iout+1026) xdata(i).ydata(i).xxval(i).
yyval(i).xxval(i).yval(i).res(i).angle(i)
                                                                                                                                                                                                                                                                        ydata(i).xxva(i).xyva(i).xxva(i).yval(i).res(i)
if(res(i).gt.0.015.and.issx0.ne.0) xrite(iout.1026) xdata(i).
                                                                                                                                                                                                                                                                                                                                                                                                                                          write(iout,1015) a,b,j,v(lave(j),j,ortim(j),j,depth(j)
format("E Am",f6,4,2x,"Bm",f7,3,2x,"VLAVE(",i1,")m",f7,3,2x,
"ORTIM(",i1,")m",f7,3,2x,"DEPTH(",i1,")m",f6,3)
                                                                                                                                                                   if (res(i), lt.-0.3. and. issw0.eq.0) write (iout, 1025) xdata(i),
FOR REFLECTIONS, FLAG DEVIATIONS > 0.3 SEC2. FOR REFRACTIONS, FLAG
                                                                                                                                                                                                      if(res(i).gt.0.3.and.issw0.eq.0) write(iout.1026) xdata(i).
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              format(/" LAYER DEPTH THICK VELOCITY IT INC REFL TT")
write(iout,1018) depth(1),vlave(1),ortim(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                write(iout,1012) i,depth(i),thick,vint,deltt,ortim(i)
                                                                                                if(abs(res(i)).gt.O.O15.and.isswO.ne.O) go to 49
write(iout.1008) xdata(i).ydata(i).xxval(i).yyval(i).
                                                                                                                                                                                                                                                                                                          ydata(i) exxva((i) eyyva((i) exva((i) eyva((i) es(i)
                                                                                                                                                                                      ydata(i),xxva((i),ryval(i),xval(i),rval(i),res(i)
                                                                                                                                                                                                                       ydata(1),xxval(1),yyval(1),xval(1),yval(1),res(1)
                                                                                                                                                                                                                                         if(abs(res(i)).gt.O.3.and.isswO.eq.O) go to 49
                                                 yyval(i),xval(i),yval(i),res(i),angle(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                lormat (4x,"1", 18.3,9x, 16.3,9x,19.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              INTERVAL VELOCITIES AND THICKNESSES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 EOJ - REFLECTIONS"//)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        if(ortim(F)-ortim(i)) 71,71,70
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         BY DEPTH
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              format(i5,f8,3,f6,3,3f9,3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                thick=depth(i)-depth(i-1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                delttrortim(i)-ortim(i-1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         if (nref.eq.1) go to 87
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           if (issud.ne.0) go to 29
                                                                                                                                                                                                                                                                                                                                                           xval(i),yval(i),res(i)
                                                                                                                                                                                                                                                                                                                                                                                       ormat(7f8.3,"<",f6.1)
                                                                                                                                                                                                                                                                                                                                                                                                      Jormat (718.3, ">" + 16.1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    ifficheck) 1,700n,2004
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              vint=(thick-2.)/deltt
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 read(iin,2000) icheck
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        REFRACTION INTERCEPTS
                                                                                                                                                                                                                                                                                                                                                                                                                            ormat(718.3,17.1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   arite(iout, 1016)
              DEVIATIONS > 0.015 SEC.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               write(iout,1017)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         do 70 kmjenref
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         do 70 izl,nn
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                30 41 i=2,1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  format(i10)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  format (/"
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         nnsnret-1
                                                                                                                                                     90 to 49
                                                                                                                                                                                                                                                                                                                                                                           continue
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              90 to 19
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     90 to 14
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1 S S WO =- 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              COMPUTE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SORT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                41
1012
                                                                                                                                                                                                                                                                                                                                                                                       1025
1026
1008
47
                                                                                                                                                                                                                                                                                                                                                                                                                                                           1015
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1017
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                1018
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1016
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 2000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   2004
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      59
                                                                                                                                                                    25
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               2625
```

```
write(fout,1013)
format(/" LAYER INTCPT DEPTH THICK VELOCITY TT INC SLOPE")
do 90 j#1,nref
heit=0.
                                                                                                                                                                                                                                          c SLOPE CORRECTED VELOCITY AND THICKNESS COMPUTATION AFTER C.OFFICER C. TRAVEL TIME INCREMENTS DETERMINED FROM VELOCITY OF LAYER AROVE 87 do 88 illalinna
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         angbasin(beta(k)+reslo(k))+vlave(k-1)/vlave(k)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      hight(j)=0.5*vlave(j)+rtime/cos(albh(j))
deltt=2.0*hight(j)/vlave(j)
                                                                                                                                                                                                                                                                                                                                                                                                                                                alph(1)=arsin(avelo/vlave(j+1))+reslo(1)
if(j.eq.1) go to 92
do 91 k=2.j
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   angazsin(alph(k-1)) *vlave(k)/vlave(k-1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                heitzheitt(angc+hight(k)/vlave(k))
rtimezortim(j)-heit
                                                                                                                                                           if(vlave(j)-vlave(j-1)) 75,75,74
nrefmnref-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           vlave(j+1)=vlave(j)/sin(alph(j))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      angc=cos(alph(k))+cos(beta(k))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                alph(k) zarsin(anga) +reslo(k)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     beta(k-1) marsin(angb)
                                                                                                                                                                                                                                                                                                                                                                      resto(i) = slop(i) - slop(1-1)
                                                                                                                                                                                                                                                                                                              v(ave(j+1)=v(ave(j)
                                                                                                                                                                                                                                                                                                                                                                                          write(iout,1011) avelo
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     if (j.eq.1) go to 95
beta(j)=alph(j)
                                                                                                                                                                                            vlave(k)=vlave(k+1)
                                                                                                                                                                                                        ortim(k)=ortim(k+1)
                                                                                                               c DELETE VELOCITY INVERSIONS
                                            ortim(i)mortim(k)
                                                                                                                                                                                                                    slop(k) =slop(k+1)
          vlave(i)=vlave(k)
                                                                                                                                                                                                                                                                                                                                              resto(1) = stop(1)
                                                                                                                                                                                                                                                                                                   ienre f-1kj
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       do 93 ijk=1,jki
                                                                             slop(i) # slop(k)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     ik jzijk-1
                                                                                                                                                                                                                                                                                                                       viave(1) mavelo
                                rotimmortim(i)
                                                                                                                                                                                                                                                                                       ik j= 1 jk-1
                                                       ortim(k)=rotim
                                                                                                                                                                                                                                                                                                                                                          do 89 i=2,nref
                       v(ave(k)=v(av
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            do 94 k=1, iki
 viaveviave(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                k= j-ik j
                                                                                                                                                                                    do 76 kmjenn
                                                                                                                                                do 74 i = 2, nn
                                                                   dip=slop(i)
                                                                                                                                                                                                                                                                                                                                   depth(1)=0.
                                                                                         s(op(k) edip
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |ki=(j-1)
                                                                                                     continue
                                                                                                                                      nnanref
                                                                                                                                                                                                                                1-1-1
                                                                                                                                                                                                                                                                                                                                                                                                                 1013
                                                                                                                                                                      7
                                                                                                                                                                                                                    9 2
                                                                                                                                                                                                                                                                                                                                                                     83
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    93
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                94
                                                                                                     2
                                                                                                                                                                                                                                                                                                             88
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                92
7
                                                     380
                                                                                                                                                                                                                                          382
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  410
```

```
FORMAT (F8.0.3F8.4.F8.3.F8.0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     FORMAT (1514)
                                                                                                                                                                                                                                                                                                     FORMAT(10A4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 FORMAT(514)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        omits subroutine MAIND listing of reduced
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            allows correction to echo sounding ddepth
                                                                                                                                                                                                                                                                                                                                                                                                                                                                1.0000 if all input values are in seconds.)
DELTA - time zero correction in seconds
DEPLOY - hydrophone deployment depth, in feet.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         omits correction to echo sounding depth
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  card 5
N(1) - number of points per layer. If negative,
will cause the program to skip that layer.
                                          THIS PROGRAM HAS BEEN MODIFIED TO RUN ON THE MULTICS
SYSTEM AT USGS, MENLO PARK,
PROGRAM TO SOLVE SLOPING WIDE ANGLE REFLECTION PROFILES BY
                                                                                                                                                                                                                                                                                                                                                                                     VV - mean vertical sound velocity from Matthew's
                                                                                                                                                                                                                                                                                                                                                                                                                                                   SCALE - scale factor in inches/second, (SCALE =
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           punches out ranges, travel times and
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            desired or not. The following options are available:
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              the program. The value of each variable is set to either \theta or 1, depending upon whether the option is
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          prints out ranges, travel times and
                                                                                                                                                                                                                                                                                                                      CRUISE - label of cruise, sonobuoy number, etc.
                                                                                                                                                                                                                                                                                                                                                  DPWTR - water depth in uncorrected meters from
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             The ISSW variables allow for various options within
                                                                                                                                                                                                                                                                                                                                                                                                                   VH - horizontal sound velocity measured from
                                                                                           REDUCING EACH LAYER TO INDIVIDUAL FLAT LAYER AND THEN
                                                                                                         FITTING DATA USING X2-17. FINDS RAY EMERGENCE ANGLE BY DERIVATION OF FOURTH ORDER POLYNOMIAL FITTED TO DATA. USFS EMERGENCE ANGLE TO COMPUTE THEORETICAL TRAVEL TIME.
                                                                                                                                                                        HANDLES AS MANY AS FIFTEEN LAYERS AND SEVENTY-FIVE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               (generally, 60, 120 or 240 feet)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           lists subroutine MAIND results
                                                                                                                                                                                                                                                                                        DATE - date and time of run or sonobuoy
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               ISSUD, ISSUT, ISSUZ, ISSUTZ, ISSUT3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            ranges and travel times
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            ISSMO = 0 omits input data lists and a lists input data
                                                                                                                                                                                                                     XAVIER LE PICHON REVISED MARCH 17 1967
                                                                                                                                                                                       POINTS PER LAYER.
USES SUBROUTINES MAIND, KAUS AND CRNGE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        suppresses printout
                                                                                                                                                                                                                                                                                                                                                                                                                                  velocimeter, in km/sec
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          emergence angles
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         emergence angles
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         suppresses punch
                                                                                                                                                                                                                                                                                                                                                                                                      Tables, in km/sec
                                                                                                                                                                                                                                                                                                                                                                      echo sounder
                              AUTH: LE PICHON / HOSKINS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        155W13 = 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        155W12 = 0
                                                                                                                                                                                                                                                          INPUT REQUIRED:
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           ISSMI # 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         -
PROGRAM SLOWI
DATE: JANUARY 1976
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          155W2 . 0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   Card 4
                                                                                                                                                                                                                                                                            Card 1
                                                                                                                                                                                                                                                                                                                                        Card 3
                                                                                                                                                                                                                                                                                                          card 2
```

```
5.619
6.737
6.070
6.248
                                                                                                                                                                                                                                                                               7.603
                                                                                                                                                                                                                                                                                               8.169
                                                                                                                                                                                                                                                        6.592
                                                                FORMAT( 1008.3)
FORMAT (1008,3)
                                                                                                FORMAT(14)
                                                                                                                                                                                                                      2.573
                                                                                                                                                                                                                                                                2.009
                                                                                                                                                                                                                                                                               3.260
0.869
1.994
3.225
1.608
3.724
6.135
                                                                                                                                                                                                                               4.547
0.770
1.774
2.884
                                                                                                                                                                                                                                                                                                                                                                                                                                                        scalZysvnyswythickytivtittootryttytuvuvvyvykyby
vhhyvvywytywuvxyzmysvypercydatanydsinydabsydsgrtydcosydarsin
                                                                                                                                                                                                                       5.480
6.442
6.052
6.201
6.508
                                                                                                                                                                                                                                                                       7.2427.5258.059
                                                                                                                                                                                                                                                                                                                     9.995
                                                                                                                                                                                                                                                                7.105
                                                                                                                                                                                                                                                                                                               9.909
                                                                                                                                                                                                                                                                                                                                                                                                       tt(15,75),date(10),crufse(10),numb(15),uu(15),sv(15),
                                                                                                                                                                                                                                                                                                                                                                                                                                        double precision coconocuododeltaodepthodiiodirodmino
                                                                                                                                                                                                                                                                                                                                                                                                                         CORMON tookhoveretredreswetsetsederezmepetesvneeke
       in degrees.
                              have equal absolute slope, alpha, than SLOP(1) = alpha, SLOP(2) = 0.0 Slope downward in the direction of travel
               Slope of layer with respect to the layer
                                                                                                                                                                                                                                                                                                                                                                                                u(75), s(75), thick(15), dii(75), rii(75), dir(15,75),
                                                                                                                                                                                                                                                                                                                                                                               dimension to(15).hh(15).v(15).w(15).su(15).cu(15).
                                                                       Date: DIR(I.J.);II(I.J.) - Dairs Of direct and reflected tto tay travel times, in seconds.
                     above (e.g. if two successive layers
                                                                                                                                                                                                                                                                                                                                                                                                                                                dridrefifactoribhipiperceipercZiririissiscalei
                                                                                                                                                                                                               0.800
2.249
4.090
0.576
1.567
                                                                                                                                                                                                                                                        5.649
                                                                                                                                                                                                                                                                0.654
                                                                                                                                                                                                                                                                                       0.650
                                                                                                                                                                                                                                                                                                      2.966
1.203
3.285
5.616
                                                                                                                                                                                                                                                                                                                                                                                        tw(15) od(75) or (75) ozm(75) op (506) ox (5) ot i (75) o
                                                                                                       ICHECK - card signalling end of data set in the set in the set of set in the set of set in 0 additional data set follows
Card 6 (and 7, if more than 10 (ayers)
SLOP(1) - incremental slopes of layers
                                                                                                                                                                                                                                                              7.093
7.204
7.204
8.052
8.119
8.271
9.901
                                                                                                                                                                                                               5.034
5.363
6.189
6.039
6.159
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         Jarsin(x) = datan(x/dsqrt(1.0d0-x+x))
                                                                                                                                                                                                                    1.939
                                                                                                                                                                                                                              3.669
0.384
1.364
                                                                                                                                                                                                                                                       2.422
0.435
1.545
2.739
                                                                                                                                                                                                                                                                                               1.536
2.714
0.800
2.855
5.118
                                                                                                                                                                                                                                                                                       0.433
                                                                                                                                                                                -0.000
                                                                                                                                                                                                       0.000
                                                                                        for each horizon traced.
                                                                                                                                                                                                                                                                                                                                                                                                                                 titemeindekoelethickeisswl
                                                                                                                                                                                                                       5.264
5.970
6.031
6.124
6.363
                                                                                                                                                                                1.0000
                                                                                                                                                                                                                                                                       7.172
7.392
8.047
8.099
                                                                                                                                                                                                       0.000
                                                                                                                                                                                                                                                                                                      8.233
9.897
9.950
10.091
                                                        is negative.
                                                                                                                                                                                                                                                                                                                                                (end of sample set)
                                                                                                                                                Example data set:
                                                                                                                                                                                1.4870
                                                                                                                                                                                                                       1.641
                                                                                                                                                                                                                                        0.192
                                                                                                                                                                                                                                                        2.200
                                                                                                                                                                                                                                                                       1.319
                                                                                                                                                                                                                                                                                               1.311
2.469
0.400
2.434
4.639
                                                                                                                                                                                                                                3.280
                                                                                                                                                                                                                                                                                        0.216
                                                                                                                                                                                                                                                                0.217
                                                                                                                                                                                                       0.000
                                                                                                                                                                                                                                                                                                                                                                                                                 inam(3)
                                                                Card 8 - end
                                                                                                                                                                                                       5.007
5.007
5.183
5.781
6.028
6.094
6.302
7.083
                                                                                                                                                                                                                                                                       7.144
                                                                                                                                                                                                                                                                                       8.046
8.083
                                                                                                                                                                                                                                                                                                        8.199
9.895
                                                                                                                                                                                                                                                                                                                       9.933
                                                                                                                                                                               1.5000
                                                                                                                                                                1 APRIL 1978
SONOBUOY TEST
                                                                                                final card
                                                                                                                                                                                                                      1.353
2.916
0.000
0.966
1.985
0.000
                                                                                                                                                                                                                                                                                               1.089
2.229
0.000
2.018
4.175
                                                                                                                                                                                                                                                                               2.247
                                                                                                                                                                                                       0.000
                                                                                                                                                                                                               0.000
                                                                                                                                                                                3755.
```

```
155W13=",12)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                urite(iout.108) issu0.issu1.issu2.issu12.issu13
108 format(" ISSU0.m.i2." ISSU2.m.i2." ISSU2.m.i2." ISSU2.m.i2."
c CLEAR POINTS PER TRACE AND SLOPE BUFFERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        tormat(1" E/S WATER DEPTH=",16.0,3x,"#EAN VERTICAL SOUND VELOCITY=",17.4,1," HORIZ SOUND VELOCITY=",17.4,2,1," HORIZ SOUND VELOCITY=",17.4,3x,"HYDRO DEPTH=",15.0)
UNICORR METERS TO TI AND CORRECT TO SB DATUM
dephy = (deptoy-30.0)/5000.
                                                                                          FURTHER REFERENCE, SEE KNOTT & HOSKINS, P., 52
DEPHY - TRAVEL TIME DIFFERENCE RETWEEN SONORUOY DATUM AND
                            DREF - ALGEBRAIC ADDITIVE CONSTANT APPLIED TO REFLECTED TRAVEL TIMES TO SHIFT THE REFLECTION TRACES WITH RESPECT TO THE DIRECT TRACE.
                                                                           FILTR - FILTER HISE TIME CORRECTION (IN SECONDS). FOR
                                                                                                                                                                                                                     format("1"," PROGRAM SLOWI",10x," DECEMBER 1976")
write(iout,191)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              format ("E NUMBER OF DATA POINTS FOR EACH LAYER")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     read(iin,198) issu0,issu1,issu2,issu12,issu13
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            urite(iout,106) doutr,vv,vh,scale,delta,deploy
                                                                                                                         AND ECHO SOUNDING DATUM (IN SECONDS)
                                                                                                                                         = (HYDROPHONE DEPTH-SOURCE DEPTH) +2/VV
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              C IN EDITS, FOR LAYERS BEING SKIPPED, PREFIX NUMBER OF
                                                                                                                                                                                                                                                                                                                                                                                               read(iin, 10) doutrovovovoscaleodeltaodeploy
                VALUES REMOVED FROM ORIGINAL INPUT LIST
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        if(iabs(numb(i)).gt.0) nrefunref+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        write(iout,219) (numb(i),i=1,nref)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           read(iin,20) (numb(i), i=1,15)
                                                                                                                                                                                                                                                                                                                                                                                                           format(f8.0,3f8.4,f8.3,f8.0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        doutr=doutr+0.54681
doutr=doutr/400.-dephy+filtr
                                                                                                                                                                                                                                                                                                                                                 read(iin,192) cruise
write(iout,193) cruise
                                                                                                                                                                                                                                                                                                                                                                                urite(iout,194) cruise
                                                                                                                                                                                                                                                                                                    write(iout,194) date
                                                                                                                                                                                                                                                                                                                   format(" ",95x,10a4)
format(" ",10a4)
                                                                                                                                                                                                                                                                     read(iin, 192) date
                                                                                                                                                                                                      write(iout,190)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               write(iout,197)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       write(iout,195)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              C DATA POINTS BY MINUS.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     READ SWITCH OPTIONS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           do 199 im1,15
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 do 206 i=1,15
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            format (1514)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       format(15;4)
                                                                                                                                                                        dref = 0.040
                                                                                                                                                                                                                                                                                       format (10a4)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       format(Si4)
                                                                                                                                                                                        # 11 tr = 0.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                             perc2=delta
                                                                                                                                                                                                                                                                                                                                                                                                                                              percessale
                                                                                                                                                                                                                                                                                                                                                                                                                                                                            scal2=delta
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                numb(i)*0
                                                                                                                                                                                                                                                        format ("
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            nref=0
                                                                                                                                                                                                                                                                                                                                                                                                                               くわわまくな
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C CONVERT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       219
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           106
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 204
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               206
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              197
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          199
                                                                                                                                                                                                                        190
                                                                                                                                                                                                                                                       191
                                                                                                                                                                                                                                                                                                                  193
                                                                                                                                                                                                                                                                                    192
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            20
                                                                                                                                                                                                                                                                                                                                                                                                               0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  161
162
163
164
                                                                                                                                                                                                                                                                                                                                                                             145
146
147
148
150
151
152
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       168
99
                                                                                                                                                                                                                                                                                                                   141
                                                                                                                                                                                                                                                                                                                                 142
                                                                                                                                                                                                                                                                                                                                                                771
```

```
format(/3x,"DIR (IN)",2x,"REf (IN)",2x,"DIR (SEC)",2x,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  format(/"E VERIFICATION OF DATA PICKS IN LAYER "+13) read(iin.201) (dir(k.)).tt(k.)).tln)
write(iout.205) (dir(k.)).tt(k.)).jml.n)
format(10dR.3)
                                                                                                                                          write(fout,730) (x(m),mssl,5)
format(/" FINAL COEFFICIENT X(1) VALUES",5d11.3)
do 228 jek,nref
                                                                                                                                                                                                                                                                           if(numb(i),le.6.and.numb(i).gt.0) go to 6007 if (u(i),gt.20..or.u(i),lt.-20.) go to 6007 uraut+daba(u(i))
                                                            C WHEN DELETING INTERFACES. COMBINE INCREMENTAL SLOPES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     203 if(numb(i).le.-2) nref=nref-1
c NEGATIVE VALUES FOR NUMB(1) CAUSE READER TO SPACE
c OVFR OMITTED LAYER DATA POINTS.
format("E INCREMENTAL SLOPES OF LAYERS") read(tin.30) (W(i).iml.nref) format(10d8.3)
                                                                                                                                                                                                                                                                  if (iabs (numb(i)).gt.75) go to 6007
                                      write(iout,196) (w(i),im1,nref)
format(10/8,3,/5/8,3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               C K IS USED TO REMOVE ZERO DATA VALUES
                                                                                                                                                                                                            wt=0.d0
1F INPUT VALUES ARE REASONABLE
                                                                                                                                                                                                                                                                                                                                    if(ut-1.d-10)6001,6001,6002
                                                                                                       if(numb(i).ge.2) kmk+1
if(numb(i).ge.2) go to 229
                                                                                                                                                                                                                                              C SET TRIAL VELOCITIES TO 1.5 KM/SEC
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            C SCALE DATA TO SCIENTIFIC UNITS
                                                                                                                                                                                                                                                                                                                                                                                u(i)=u(i)+0.017453293d0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         if(numb(i).gt.2) kmk+1
                                                                                                                                                                                                                                                                                                                                                C CONVERT ANGLES TO RADIANS 6002
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            C MAIN LOOP FOR NREF LAYERS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        write(iout,202) i
                                                                                                                                                                                                                                                                                                                                                                                                       C INTRODUCE DATA PICKS HERE
                                                                                                                               u(k)=u(k)+u(k+1)
                                                                                                                                                                                                                                  do 117 imponref
                                                                                                                                                                                                                                                                                                                                                                                                                                       do 203 intemref
                                                                                              do 229 1=2,nret
                                                                                                                                                                                                                                                                                                                                                                                                                                                  nmiabs(numb(i))
                                                                                                                                                                                                                                                                                                                                                                                                                                                              numb(k) snumb(t)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   write(iout,101)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                ormat(1018.3)
                                                                                                                                                                          w(j+1)=w(j+5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       "REF (SEC)")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        depth=0.d0
                                                                                                                                                                                                                                                        v(i)=1.5d0
                                                                                                                                                                                                                                                                                                                                                                                                                  nreferref
                                                                                                                                                                                      continue
                                                                                                                                                                                                                                                                                                                                                                                            v(1)=v
                                                                                                                                                                                                                                                                                                               v(1)=vv
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        1 = 1 + 1
                                                                        c ACCORDINGLY.
                                                                                                                                                                                                                                                                                                                                               F 12 H
                                                                                                                                                                                                                                                                                                                          k u = 2
                                                                                                                                                                                                                                                                                                                                                                                1300
                                                                                                                                                                                                                                                                                                                                               6001
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                101
                                                                                                                                                                           228
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    201
205
624
                                                                                                                                                                                                                                                                                                    117
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   202
                          30
```

```
urite(iout,111) vh,vhh
1 format(/," vH CORRECTED=",f?,4,3x,"vH SUPPLIED=",f?,4)
COMPUTE COEFFICIENTS DERIVATIVE FOR EMERGENCE ANGLE
                                                                                                                                                                                                                                                                                                                                       C IS FIRST DATA POINT CLOSE ENOUGH TO ORDINATE TO APPROXIMATE
                                                                                                                                                                                                         C FIT CURVE TO DATA TO OBTAIN TO AND LATER DIFFERENTIATE FOR
                                                                                                            if (n.eq.1.or.issw0.eq.1) write(iout,102) dii(n),
                                                                                                                                                                                c END OF DATA LOADING AND SCALING TO SCIENTIFIC UNITS
                                                                                                                                                                                                                                     C IND IS AN INDEX USED IN MAIND TO CONTROL PRINTOUT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          c IF FIRST LAYER COMPUTE THICKNESS AND VH BY X2-T2
                                                                                                                                      C IF NOT FIRST LAYER CONVERT U TO DISTANCE
                                                                                           s(n) = (rii(n)+scal2)/scale+dref
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               c BRING BACK TO FLAT LAYER CASE
r(i)=s(i)++2+con+u(i)+vh/v(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C OPTION TO COMPUTE EMERGENCE ANGLES
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         if (issw13.eq.1) go to 32
do 92 k=1.ko
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     con=2.0d0+to(1)+dsin(w(1))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    if (u(1)-dmin) 921,921,922
                                                                                 u(n) = (dii(n)+perc2)/perce
                                                                                                                                                     if(l.ne.1) u(n) Eu(n) +vh
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    hh(1)=v(1)*to(1)/2,0d0
do 200 i=1,ko
                                                                                                                                                                                                                                                                                                                                                                 11(u(1)-dmin) 3,3,923
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         x(3) xx(3) +2.0 d0 +v(1)
x(4) xx(4) +3.0 d0 +v(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      ((5) #x(5) *4.0d0 *v(1)
                                                                                                                                                                                                                                                   if(1-1) 930,931,930
dmin=0.45d0*vh
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   vh=dsqrt(x(2))+v(1)
C MOVE DATA TO WORKING ARRAYS
                                                                                                                                                                                                                                                                                                                                                                                                                       d(k)=(u(k)+xb)++2
                                                                                                                           rii(n),u(n),s(n)
                                                                                                                                                                                                                                                                                                                                                                                                                                                 to(1) = dsqrt(x(1))
                                                                                                                                                                                                                                                                                                                                                                                                                                     call maind(1,1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      coll maind(1,1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                call maind(4,1)
                                       dii(i)=dir(l.i)
                          do 4003 im1.ko
                                                    rii(i)=(((/))
                                                                  do 5010 n=1.ko
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              x(2)=x(2) +v(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   d(k) = n(k) + xb
                                                                                                                                                                                                                                                                                                                                                                                             do 90 k=1,ko
                                                                                                                                                                                                                                                                                                                                                                                                          r(k)=8(k)++2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             11(1-1)4,4,3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            d(i)=u(i)++2
                                                                                                                                                                                                                                                                             xb#1.0d0
go to 932
dmin#0.3d0
                                                                                                                                                                                                                          ANGLE OF EMERGENCE
             ()) quonao
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                (1)=x(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      r(k)=s(k)
                                                                                                                                                                     continue
                                                                                                                                                                                                                                                                                                                                                                                f-mput
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         indal
                                                                                                                                                                                                                                                                                                                          X D H C Y
                                                                                                                                                                                                                                                                                                                                                                                                                                                                  Indai
                                                                                                                                                                                                                                                                                                                                                    INTERCEPT
                                                                                                                                                                  5010
                                                    4003
                                                                                                                                                                                                                                                                   930
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              921
                                                                                                                                                     03
                                                                                                                                                                                                                                                                                                          931
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            200
                                                                                                                                                                                                                                                                                                                                                                                                                       06
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             281
281
282
283
284
285
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              287
288
289
291
291
294
295
                                                                                              672
549
                                                                                                                                      269
271
271
272
273
274
275
276
276
```

```
write(iouty104) [vv(l)vto(l)vthfck(l)vdepthysvnyww(l)
format(" LAYER "si2," VELOCITY#"sf6.3," REFLECTION TIMF#",
f6.3," THICKNESS#"sf6.3s/" DEPTH#"sf6.3,3x,"SV#"sf7.3,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            if(1.gt.1) thick(1) #(to(1)-to(1-1)) *v(1)/2.0d0
                                     do 300 im2,ko
zm(i)=K(2)+K(3)+u(i)+K(4)+u(i)++2+K(5)+u(i)++3
                                                                                          if (issw13.eq.0) write(fout.102) u(i).s(i).zmd
if(issw12.eq.0) write(7.102) u(i).s(i).zmd
c find angle emergence 2m for each point except last 922
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            if(dabs(to(1)-dpwtr).lt.0.005) go to 209
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             if(1.eq.1) thick(1) mto(1) +v(1) /2.040
                                                                                                                                                                                                                                                                                                                                                                         r(i)=r(i)++2+con+d(i)+ti(i)-ti(i)++2
                                                                                                                                                                                                                                                                                                                                   c ELIMINATE POINTS WITH NEGATIVE REDUCED D if(d(i))350,3601,3601
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      RESET ANGLE ACCORDING TO NEW VELOCITY tw(1)*tw(1)*v(1)/vv
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   if(l.ne.1) go to 207
TO SKIP CORRECTING TO E/S DEPTH
if(issw2.eq.0) go to 209
                                                                                                                                                                                                 con=2.0d0*dsin(w(l))/v(l)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           c If IND NEGATIVE RESTART PROCESS if (ind)31,31,32
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        ww(1) = w(1) /0.017453293d0
                                                                              zmdmzm(1)+57.29577951d0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         v(1)=dsqrt(1,0d0/x(2))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             if(x(2))3100,3100,3101
                                                                                                                                                                                                                                       call kaus(l,zm(1),1k)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                               C CHECK FOR IMAGINARY VELOCITY
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            depth=depth+thick(1)
                                                                (())=darsin(zm(i))
                                                                                                                                 if (t.eq.1) komko+1
                                                                                                                                             if ((.eq.1) go to 4
                                                                                                                                                                                                                                                                                                                                                            REDUCE TO FLAT LAYER CASE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              w(l) #datan(tw(l))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        Stope", 16.2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        drefadbutr-to(1)
                                                                                                                                                                                                                                                                                                                                                                                                                            go to (5,6), kw
                                                                                                                                                                                                                                                                                                                                                                                                                                                       call maind(1,1)
                                                                                                                    ormat(4f10.3)
                                                                                                                                                                                                                                                                  THAT D IS IN KM
                                                                                                                                                                                                                           350 i=2,ko
                                                                                                                                                                                                                                                                                d(1)*u(1)-dr
                                                                                                                                                                                                                                                                                            r(i)#$(i)-tr
                                                                                                                                                                                                                                                                                                                                                                                      d(i)=d(i)++2
                                                                                                                                                                                                                                                                                                                                                                                                                c SOLVE FOR VELOCITY
                                                                                                                                                                                                                                                                                                                      d(i) ad(i)/c
                                                                                                                                                            d(1)=-1.d-4
                                                                                                                                                                       i (1)=0.40
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      Sv(1)=Svn
                                                                                                                                                                                                                                                                                                          ti(i)=tit
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SOLUTION LISTING
                                                                                                                                                                                      nd=-ind
                                                                                                                                                                                                                                                                                                                                                                                                     continue
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    (1) ^= ^ ^
                                                                                                                                                                                                                                                                                                                                                                                                                                           indal
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   c 0P110N
                                                                                                                                                                                                                                                                  NO TE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        3101
                                                                                                                                                                                                                                                                                                                                                                         3601
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         210
                                                                                                        300
                                                                                                                                                                                                                                                                                                                                                                                                  350
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             104
                                                                                                                                                                                     2
                                                                                                     343
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       344
345
346
347
349
350
351
```

```
urite(iout, 3205) date, cruise
format(///1x,10a4,/1x,10a4,/5x,"VELOCITY REFL TIME THICKNESS
DEVIATION SLOPE"/)
deltamto(1)
do 3201 fmf, nref
if(i_gt_1) deltamto(i)-to(i-1)
urite(iout, 3202) i_v(i), to(i), thick(i), delta, sv(i), uu(i)
format(i3,6f10,3)
read(iin, 7000) icheck
                                                     write(iout.107) factor
format(" DIRECT WATER WAVE VELOCITY CORRECTION ".17.4)
depth=0.d0
                                                                                                                                                                                                                            format(i10)
if (icheck) 1,70n1,1
write(iout,2200) l
format(" VELOCITY NEGATIVE, REMOVE LAYER ",i2,//)
if(l,[t,nref) go to 2
write(iout,1010) dref
format(" NORMAL INCIDENCE IT CORRECTION=",f8,1)
                             if(dabs(vhh-vh),lt.0,003) go to 207
                                                                                                                                                                                                                                                                              go to 259
write(iout-6008)
format(" IMPOSSIRLE VALUE")
go to 204
continue
                                                                                        207 if(Lgt.1) call crnge if(Lgt.1) call crnge if(Llt.nref) go to 2 c make Tabulation of Results
                                         percesperce•vhh/vh
                                                  factor*vh/vhh
                                                                                                                                                        ELTA TT
                                                                                                                                              3205
                                                                                                                                                                                                                            7 000
          1010
                                                                                                                                                                                                3201
                                                                                                                                                                                                                                                3100
                                                                                                                                                                                                                                                                                         6007
6008
                                                                                                                                                                                                                                                                                                                       7001
                                                                                                                                     259
                             509
                                                                      107
```

```
double precision a(5.5).b(5).weight(5).covmat(5.5).resnrm.u(5)
                                                                       common torbhevewetredressecueturderezmepecesuneuhexetite
                                                                                          double precision assalsa2.c.curdsddo.dk.dr.d11.d2.d21.
d211.bhsoksperstrestdssenssatsktitsto.tretwetxsesub.
                                                   dimension to(15), hh(15), v(15), u(15), su(15), cu(15),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          D(kkenm) = D(kkenm) - (D(ienm) + D(kkei)/D(iel))
                                                             tu(15).d(75).r(75).zm(75).p(5.6).x(5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     if(a1-1.e-30) 1002,1002,1210
                                                                                                                                                                                                       if(d(i)) 1001,9001,9001
if(m+n-2) 6000,6000,6001
                                                                                                                                                                                                                                                                                                                                                                                                                                                            a2=dabs(p(kk,i))
if(a1-a2) 1020,1021,1021
                                                                                  m.ind.ko.l.thick.issw1
                                                                                                                                                                                                                                                                                           i ( (d(i)) 1000,9002,9002
STORED AS FILE MAINS ON DISC
DATE: 29 JAN 73
                                                                                                                                                                                                                                                                                                        if(m-1) 6003,6003,6004
                                                                                                                                                                                                                                                                                                                                      (+) -+ ( H-1 ) ++ (+)
                                                                                                               w.x.zm.dabs.dsqrt
                                                                                                                                                                                                                                                                                                                                              p(ming) #p(ming)+tx
                                                                                                                                                                                                                                                                                                                                                                 E MATRIX SYMETRIC
do 1010 nal.ino
do 1010 nal.in
b(m.) b(n.m.)
do 1002 kal.in
do 1002 kal.in
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   p(kkeiin) =p(feifn)
                                          AUTH: LE PICHON / HOSKINS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                               do 1200 iinmi,ng
                                                                                                                                                                                                                                               (H#Q(1)++(#+U-5)
                                                                                                                                                                                                                                                         D(B.1) #D(B.1) +tx
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 do 1201 nmmiting
                                                                                                                                                               do 1000 mm1,ino
do 1001 nm1,m
                                                                                                                                                                                                                                                                                                                                                                                                                                                  almdabs(p(i,1))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        do 1005 kml, ino
                                                                                                                                                                                                                                                                                    do 1000 i=1.ko
                                                                                                                                                                                              do 1001 iminko
                                                                                                                                                                                                                                                                           0 (m.nq) = 0. d0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           aasp(kk.iin)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     x(i)=p(i,nq)
                                                                                                                                                                                    0p.0=(u/w)d
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              D(i.iin) maa
                                                                                                                                                                                                                                    90 to 6002
                                                                                                                                                                                                                                                                                                                             go to 6005
                                NUMB: UNASSIGNED
                                                                                                                                                                                                                                                                                                                                                          continue
                                                                                                                                            fno=in+1
                                                                                                                                                       ng* ino+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     continue
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               SOLVE MATRIX
                                                                                                                                                                                                                            t x = 1.0 d0
                                                                                                                                                                                                                                                                   continue
                                                                                                                                                                                                                                                                                                                   ( * x = L ( 1 )
                                                                                                                                     out=6
                                                                                                                                                                                                                                                                                                                                                                                                                               isit
                                                                                                                                                                                                                                                                                                                                                                                                                                        kk=k+1
                                                                                                                                                                                                                                                                                                        9002
                                                                                                                                                                                                                                                                                                                                    6004
6005
1000
                                                                                                                                                                                                                                                                                                                                                                                                 1010
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1200
1021
1201
1201
                                                                                                                                                                                                                                             6001
```

```
write(iouts1900) x(1)sx(2)sx(3)sx(4)sx(5)
tormat(" COEFFICIENTS OF FITTED POLYNOMIAL: INTERCEPT="sf?.4s"
n x2="sf?.4s/s" x3="sf?.4s" x4="sf?.4s" x5="sf7.4s"
                                                                                                                                                                                                                                                                                                                                                                                                                                                         if(k,ne.1,and,1ssw1,eq.0) go to 1061
if(dk,lt,-0.3) write(iout,1904) d(k),rr(k),rr,dk
format(lk,f9,3,2210,3,2k,f9,3,~~")
if(dk,qe,-0.3,and,dk,le.0.3) write(iout,1903) d(k),rr(k),rr,dk
format(lk,f9,3,2710,3,2k,f9,3)
if(dk,qt,0.3) write(iout,1905) d(k),rr,dk
format(lk,f9,3,2710,3,2k,f9,3,~~")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  write(fout,1802)ddo,k1,ko
format(/," STANDARD DEVIATION=",f7.3,5x,"NEGATIVE D ",
"VALUES DISCARDED ",12," / ",12)
if(fino-ge.ok) write(fout,1803)
format(1x," STANDARD DEVIATION NOT SIGNIFICANT, TOO FEW",
"DATA POIHTS")
                                                                                                                                                                                 format (//3xv"bs0(KM)",3x,"R2(SEC)",2x,"R2 COMPUTED",1x,
"Difference")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        SIGNIFICANCE CHECK FOR STANDARD DEVIATION
                                                                                                                                                                                                                                                                                                                                                                                                                                              c SENSE SWITCH OPTION TO OMIT LISTING VALUES
                                                           if (a1-1.e-30) 1500-1500-1005
x(i)=x(i)/p(i.t)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       if(ino.ge.ok) ddozok-ino
ddozdsgrt (ddo/(ok-in-1))
           do 1060 kmmti.fno
x(i)mx(i)-(p(1.kx)*x(kx))
1f(1-ino) 1006,1050,1050
                                                                                                                                                                                                                                                     if (d(k)) 9003,9004,9004
                                                                                                                                                                                                                                                                                                                                 if(i-1) 6006,6006,6007
                                                                                                                                                                                                                                                                                                   PREDICTED TRAVEL TIME
do 1062 i=1, ino
                                                                                                                                                                                                                                                                                                                                                                               tx=x(i)+(d(k)++(i-1))
                                                                                        c FOR PRINTOUT INET AND INDET
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             if(d(m))6,9010,9010
                                                                                                                                                                        urite(fout, 1902)
                                            al *dabs(b(i.t))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              COMPUTE UNCERTAINTY
                                                                                                                                                                                                                        do 1061 k=1,ko
                                                                                                                          11(ind) 4,4,21
                                                                                                                                                                                                                                                                                                                                                                                                                                ddo=ddo+dk ++2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         d11=d(m)+d11
                                                                                                                                                                                                                                                                      ok = ok - 1 . 0d0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                std=ddo+ddo
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              do 6 m=1,ko
                                                                                                                                                                                                                                                                                      go to 1061
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             Q2=d(m)++2
                                                                                                                                                                                                                                                                                                                                                                   90 to 1062
                                                                                                                                                                                                                                                                                                                                                                                                                 dker(k)-rr
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           421=42+421
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           continue
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               d11=0.d0
                                                                                                                                                                                                                                                                                                                                                                                                  FFEFFFE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      k1=k0-0k
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        continue
                                                                                                                                                                                                                                      rr # 0. d0
                                                                                                                                                                                                                                                                                                                                                   tx=x(i)
                                                                                                                                            ddo*0.
                                                                                                                                                            okzko
                                                                                                                                                                                                                                                                                                      C COMPUTE
                                                                                                                                                                                                                                                                                                               9006
              1006
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1803
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1900
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          9010
                                                                            1005
                                                                                                                          1701
                                                                                                                                                                                         1902
                                                                                                                                                                                                                                                                      9003
                                                                                                                                                                                                                                                                                                                                                   9009
                                                                                                                                                                                                                                                                                                                                                                                  6007
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1904
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          1903
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1905
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     1061
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1802
                                                                                                                                                                                                                                                                                                                                                                                                1062
                                                                                                                                                        465
                                                                                                                                                                                                                                                                                                                  673
677
673
673
680
                                                                                                                                                                                                                                                                                                                                                                                                                                                            787
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           9 N B B B B
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     267
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  5 67
                                                                                                          163
                                                                                                                                                                                      195
                                                                                                                                                                                                         897
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      063
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      163
```

```
dimension to(15).hh(15).v(15).w(15).sw(15).cw(15).tw(15).d(75).
                                                                                                                                                            double precision cacoxacuadadrahcahbahkapapagararrasixa
                                                                                                                                                                              Sixee Seneske tietketos trettetkeuseescherekexexexexeyezse
                                                                                                                                  common torbhovewetredresmetwederezmepecesunecheyetie
        STORED AS FILE KAUSS ON DISC
SUBROUTINE TO COMPUTE REFLECTIONS FOR X2-T2 METHOD.
L IS NUMBER OF LAYER, ZZ IS EMERGENCE ANGLE, IK IS INDEX
TO INDICATE FIRST POINT OF LAYER,
PARAMETERS TRANSMITTED BY COMMON. TR.DR.TI ARE RETURNED.
VERSION MAY 1967
                                                                                                                                                                                                                                                                                                                                                                                                                                 FIND ANGLE CORRESPONDING VERTICAL REFLECTION
                                                                                                                 r(75),zm(75),p(5,6),x(15), xx(15),y(5)
                                                                                                                                                                                            zzzzozdsgrtzdsinzdcoszdatanzdarsin
                                                                                                                                                                                                         darsin(x)#datan(x/dsqrt(1,0d0-x*x))
if(ik)9990,9990,9991
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   C FIND ANGLES INCIDENCE FROM EMERGENCE ANGLE
                                                                                                                                                                                                                                      FIND THICKNESSES, COMPUTE SIN COS TAN ON FIRST CALL TO KAUS FOR EACH LAYER
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          sixm(v(i-1)/v(i))*dsin (q)
cox=dsqrt (1.0d0-six*six)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        q=datan (six/cox)+w(i-1)
subroutine kaus(lezzeik)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        hc=(to(i)/2.0d0-tt)+v(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         hc=hh(i)-u+dsin (w(i))
                                                                                                                                                                                                                                                                                                                                      11c(-1)1003,1003,1002
[1=(-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  UFU+CH(i)+HC+Six/COX
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 Sixuev(1+1)+s1x/v(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  tt=tt+hc/(v(1)+cox)
                                                                                                                                                                                                                                                                                sw(i)=dsin(w(i))
cw(i)=dcos (w(i))
tw(i)=sw(i)/cw(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      hh (i) =hc+u+sw(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               xwedarsin(sixw)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          if (1-1) 11,11,10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     11(1-1)11,11,10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            11(1-1)13,14,14
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     COMPUTE REFLECTIONS
                                                                                                                                                                                                                                                                                                                                                                                    do 1001 imiril
                                                                                                                                                                                                                                                                  do 1000 i=1,1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                XX (1) = 2 2 + 4 (1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       six=dsin (q)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     coxedcos (q)
                                                                                                                                                                                                                                                                                                                                                                                                                    (mm) soopas
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              Q=xu-u(i+1)
                                                                                                                                                                                                                                                                                                                                                                                                    VERNETE(1)
                                                                                                                                                   me indeko
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           COMPUTE HH(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   Q=Q-W(i)
                                                                                                                                                                                                                                                                                                                               c=1.0d0
                                                                                                                                                                                                                                                                                                                                                                         0P.0=44
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              0F0.0m
                                                                                                                                                                                                                                                                                                                                                                                                                                                               (+) A=D
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       1=1=1
                                                                                                                                                                                                                                                                   0666
                                                                                                                                                                                                                                                                                                              1000
                                                                                                                                                                                                                                                                                                                                                                                                                                               1003
                                                                                                                                                                                                                                                                                                                                                        1002
                                                                                                                                                                                                                                                                                                                                                                                                    1001
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            12
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   =
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 561
563
563
564
565
565
                                                                                                                                 532
534
535
535
535
                                                                                                                                                                                                          556
557
558
558
559
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    568
569
570
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     260
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           555
```

```
sixedsin(k(1)+w(1))+v(1-1)/v(1)

x(1-1)=dersin(six)

go to 926

MAIN COMPUTATION
    if(L-i) 9252,9252,9250
sixedsin(xx(i))
if(six-v(i)/v(i+1))9253,30,30
sixw=v(i+1)*six/v(i)
                                                                                                                                                                                                                                                 tk=(rr+cu(i))/(cox+v(i))
                                                                                                                                                                                                                                    hkerr+dain(xx(1))/cox
ppepp/cw(1)+hk
                                                                                                                                                                                                                              COXECCOS (xx(i)-u(i))
                                                                                                                                                                                                    ti =(hc/v(1))+2.0d0
                                                                                                                                                                                                                                                             11(1-1)262,261,261
                                    як(i+1) вки+и(i+1)
go to 924
                                                                                                                          hcmh(i)-uesu(i)
simmdsin(m(i))
commdcos(m(i))
                                                                                                                                                                                                                        rrabh(i)-ppetu(i)
                                                                                                                                                                      11(1-1)252,252,24
                                                                                                                                                                                   hkehk/dcos (u(1))
                                                                   11(1-1)21,21,928
                                                                                                                                              hkmhc+(min/cox)
umu+cw(i) +hk
tkmhc/(v(i)+cdx)
                                                                                                                                                                                                                                                                   drædrthk
trætrttk
if(i-1)27,27,26
                               xwedarsin(sixu)
                                                                                                                                                                                                                                                                                             dr*pp-dr*c
                                                        x(1) *xx(1)
                                                                                                                                                                                                                                                                                                         dr=-1. d-4
                                                                                                                                                                 ttstt+tk
                                                                                                                                                                                                                                                       ttstt+tk
                                                                                                                                                                                                                                                                                      tratt-tr
                                                                                                                                                                                                                                                                                                              tr=0.d0
ti=0.d0
return
                                                                                                                                                                                                                                                                                                   return
                                                                                                                     ( = i + 1
                                                                                                                                                                                                            nadd
                                                              1-12
                                                                                                                                                                             1=1+1
                                                                                                                                                                                         tratk
                                                                                                                                                                                                drahk
           0526
                                                                         926
                                                                                                                                                                                                                                                                              262
                                                             956
                                                                                                                                                                             282
                                                                                                                                                                                                                  92
                                                                                                                                                                                                                                                                                                        30
```

```
common dummy(30),c.dumny(326),idumy(3),nlayryh
dimension c(15), h(15), sincr(15)
double precision c.cr.dir.dummy.dumny.hvsincr.xxxxdsgrt.dcos,
                                                                                                                                                                                                                                                                                                      format(2x,"V(",12,") OR THICK(",12,") VALUE UNREASONABLE,",
" COMPUTATION SKIPPED")
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 write(iout.1001) xx.dir.nlayr
format(1x.ef7.2," HINIMUM CRITICAL RANGE, ",f7.2," WATER ",
"TRAVEL TIME FOR LAYER ",i2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 :`
                                                                                                                                                                                                                                                                                                                                                                                                                                                   if(sincr(1-1).gt.1.0d() write(iout.1000) nlayr
if(sincr(1-1).gt.1.0d() return
format(2x,"VELOCITY INVERSION IN UNDERLYING LAYER, NO
"CRITICAL ANGLE FOR LAYER ",i2)
credarsin(sincr(i-1))
            PROGRAM STORED ON DISC AS CRNGS
CRANGE PROGRAM FOR COMPUTING MINUMUM RANGE OF REFRACTED WAVE
                                                                                                                                                                                                                    if(c(nlayr),lt.8.0.and.c(nlayr),gt.0.8) go to
write(iout.1002) nlayr.nlayr
                                                                                                                                                                                                                                                                90 to
                                                                                                                                                                                                                                                               if(h(nlayr).lt.9.0.and.h(nlayr).gt.0.0)
                                                                                                                                                        darsin(x) =datan(x/dsqrt(1,0d0-x+x))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           xxxxx+h(i-1)+sincr(i-1)/dcos(cr)
                                                                                                                                                                                                                                                                                                                                                                                                                                    sincr (i-1) #c(i-1)/c(i) *sincr(i)
                                                                                                                                                                                                                                                                            write(iout,1002) nlayr,nlayr
                                        22 DEC 72
                                                       ASSUMES FLAT-LYING LAYERS
                                                                                                                                                                                                                                                                                                                                                                 sincr(nlayr)=1.0d0
                                                                                                                                                                                                                                                                                                                                                                                              ijkmlayr-1
do 10 ijklmlrijkel
imij-ijkl
subroutine crnge
                                                                                                                                datan,darsin
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         direxx/c(1)
                                                                                                                                                                                                                                                                                                                                                                                ijznlayr+1
                                        SCOUL VERSION
                                                                                                                                                                                                                                                 return
                                                                                                                                                                                                                                                                                             return
                                                                                                                                                                          iout =6
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  return
                                                                                                                                                                                                    C DATA CHECKER
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1000
                                                                                                                                                                                                                                                                                                        1002
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1001
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          0
                                                                                                                                                                                                                                                               5
```

Appendix L

Listing of interpretation program SONOMODEL

This appendix contains a line numbered listing of the sono-buoy modelling program entitled sonomodel. The pathname of the program listing is:

>udd>Marine>JChilds>sonobuoy>sonomodel.fortran

The introductory comments prefacing the program describe the input required. All input is from file05 and all printer output goes to file06. Therefore, file attaches must be made to these files before executing the program. The fortran program has been compiled with Honeywell Multics fortran (release 4). The object segment has a pathname:

>udd>Marine>JChilds>sonobuoy>sonomodel

An example of the program, using the example input data contained in the comments, is contained in Appendix I.

```
calculate x and t values from the ray barameter pasin(phi(i))/\mathbf{v}(i) for values of phi in 30 increments from 0 to critical phi.
                                                                                                                                                                                                                                                                                                                                        format (10f8.3)
                                                                                                                                                                                                                                                                                                                                                                 format(1018.3)
                                                                                                                                                                                                                                                      format(f10.3)
format(f10.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  records at a firing rate of 50 meters and a recorder feed of 40 lines per finch. In line 4, the first factor scales the distance autis, while the second factor scales the time axis. For both axes increasing the factor factor "stretches" the axis, while decreasing the factor
                                                                                                                                                                                            format(f10.4)
                                                                                                                                                                     format (410.4)
                                                                                                                                                                                                                                                                                                      format ( f 10, 3)
                                                                                                                                                                                                                                                                                                                format(f10.3)
                       sodel employs ray tracing theory (a la brune). sethod is to
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         This data set is designed to match an eight second
                                                                                                                                 format (784)
                                                                                                          format(7a4)
                                                                                                                                                         format(i3)
 ********
                                                                                                                                                                  vh - horizontal water velocity of sound
v(n1+1) - velocity of material beneath
                                                                                                                                                                                                                                            axis to desired length. scales
                                                                                                                                                                                                                                                                                                                                       vi(i) - velocity of layers (in km/sec)
                                                                                                                                                                                                                                                                                                                                                                          note: if there are more than 10 layers in the model, than the velocities and
                                                                                                                                                                                                                                                                                                                                                                                                  thicknesses go on cards after 5 in
format(1018.3)
                                                                                                                                                                                                                                                       stl x values.
yscal - tbid for y axis
ylen - length of the y axis (effect-
                                                                                                                                                                                                                                                                                        ively the length of the time
                                                                                                                                                                                                                                                                                                                deltat - initial time offest of plot
                                                                                                                                                                                                                               xscal - constant to scale horizontal
                                                                                                                                                                                                                                                                                                                                                               2(i) - thickness of layers (in km)
sonobuoy modelling program
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   -0.100
6.712
6.207
                                                                                                                                                        - number of layers in model
                                                                                                        1d - tabet for model
                                                                                                                                                                                                                                                                                                      axis of the plot)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              3.761
                                                                                                                                                                                             deepest layer
                                                                                  input parameters required:
                                                                                                                                                                                                                                                                                                                                                                                                                                                  SAMPLE INPUT DATA SET
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    20.000
                                                                                                                                                                                                                    plotting parameters
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 "shrinks" the axis.
                                                                                                                                  1d - date
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              2.411
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 2.364
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SONOBUOY TEST A
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1 APRIL 1978
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               2.040
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           1.042
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    1.487
 *********
                                                                                                                                                                                                      b bres
                                                                                                                      card 2
                                                                                                                                            card 3
                                                                                                                                                                                                                                                                                                                                                      card 6
                                                                                               card 1
                                                                                                                                                                                                                                                                                                                              Card 5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   0.500
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               1.500
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           3.755
```

```
format(/" horizontal velocity of sound=">17.4)
format(" blot barameters are:">5x,"xscal=">f7.4>
5x,"ylen=">f7.2./" ">26x," initial time offset="/f7.4)
                                                                                                                                                                                                                                                                                                                                                                       we have interchanged the x and y axes in the plotting routines and consequently, the variable labels may appear a little funny.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             offset plot by deltate an initial time offset. sign of deltat
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          main loop for layers. calculates hyperbolas, critical angle
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        cell axis(0.0.0.0.0.*kilometers",10.xlen,90.0.0.0.5.0)
                                                                                                                                                                                                                                              km/sec) thickness(km)",/
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        must be replaced with a blank and the program recompiled.
                                                                                                                                                                                                                                                                                                                                                                                                                       call plot(0.0.7.0.-3)
call plot(50.0.28.0.+60)
call plot(-2.0.-2.0.-60)
The commands in lines 100,105,106,109 & 187 will
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 call plot(yscal,2,0,+20)
call plot(yscal,0,5,+20)
call axis(0,0,0,0,0,0,0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           reduce the entire plot to page size. The initial c
                                                                                                                                                                                                       ".784./" model: ".784./)
                                                                                                                                                                                                                                               velocity(km/sec)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          is the same as lint or slowi convention.
                                                                                                                urite(6,17) xscal,yscal,ylen,deltat
                                              read(Sol4) mscaloyscaloylenodeltat
read(Sol1) (v(i)oimlon()
read(Sol1) (z(i)oimlon()
write(6o9) idateoid
 arsin(x) satan(x/sqrt(1-x++2))
                                                                                                                                                                                                                                                                   format (13,9x, 15, 3, 15x, 16, 3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         call plot(yscal,xscal,+20)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   call plot (-deltat.0.0.-3)
                                     read(5,10) nlovhov(n(+1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    call plot(2.0.xscal.+20)
call plot(0.5.xscal.+20)
                                                                                                                                                      write(6,13) i.v(1),2(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            wscalmyscal+5.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        xtenaxten/xscat
                                                                                                                                                                                                                                                                                                                                                set up the plot routine
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       xscalmuscal/5.
                                                                                                                                                                                write(6,13) i.v(1)
                                                                                                                                                                                                       format(/," date:
format(i3,2f10,4)
                                                                                                                                                                                                                                             ormat(//" layer
                                                                                                                                                                                                                                                                                                                                                                                                              x tensyheyten
                       read(5,8) idate
                                                                                                write(6,16) vh
                                                                                                                                                                                                                                 ormat(10f8.3)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      ylensylen+1.00
             read(5,8) id
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    xscalexscal/4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  do 15 istant
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             x enexten/4
                                                                                                                            urite(6,12)
                                                                                                                                                                                             ormat (784)
                                                                                                                                                                    inn(+1
                                                                                                                                                     5
                                                                                                                                                                                             21000
                                                                                                                                                                                                                                                                  13 4 7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          ں ں
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   U U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      116
117
118
119
```

and distance and plots both.

for each layer calculate the critical shooting angle, the point
at which the solution blows up (x and t go to infinity).

subtract a nominal sum (here .2 degrees) from this and divide
by an incremental number to determine a delta. plot the hyperbola and critical refraction line for each layer calculate the critical point from the critical angle, and den=sqrt(1-(p+p+v(k)+v(k))) den=sqrt(1-(p+p+v(k)+v(k))) SUBBRUBAR(K) + V(K) / GET)
SUBBBRUBBAR(K) / (V(K) + GET)
KC(+) R2+D+SUBB
(C(+) R2+D+SUBB summasumm+z(k)/(v(k)+den) call spot (te(i) . xc(i) . 0.15.66.0.0) call line(yyexxondps1000)
if((ylen-tc(i)).le.0.0) go to 35
xend=xc(i)+(ylen-tc(i))*v(i+1) summaum+z(k)+v(k)/den yend=tc(i)+(xend-xc(i))/v(1+1) if (i.ne.1) cphi=arsin(v(1)/v(i)) if(xend.gt.xtest) go to 34 delta=(cphi-0.000003490658)/30 calculate direct arrival and plot. call plot (te(1),xe(1),3) critical refraction at xexten. call plot(ylen.xend.2) call plot (yend, xend, 2) cphi2=arsin(v(1)/v(i+1)) p=sin(ph1)/v(1) x(i,j)=2.p.sum 92=dpu t (1. j)=245umm do 20 k=1,1 do 30 k=1.1 xtest#28.0/xscal 0.0=##08 phi=phi+delta yy(j)=+t(i,j) SUMM #0.0 Sum=0.0 xx(j)=x(ioj) 0.0 =mns do 25 j=1,30 if(i.eq.1) D=Sin(phi)/v(1) mend=xtest cphi=1.570796 go to 35 do 35 imini ph 1 = 0.0 ndp=30 phi=cphi2 cont inue 20 30 3.4 25 178

```
tc",90,0,44)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                ×
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                critical distance
                                                                                                                                                                                      ŏ
                                                                                                                                                                                                                                                                                                 ff(i.eq.1) call symbol (noum.16.30.2.5."km/sec",90.0.6)
call number(knum.18.7.0.25.thick.90.0.2)
ff(i.eq.1) call symbol (noum.20.0.6.25."km",90.0.2)
call number(knum.22.0.0.25.critd.90.0.2)
call number(knum.24.5.0.25.critt.90.0.2)
call number(knum.24.5.0.25.critt.90.0.2)
if (i.eq.1) call symbol (xnum.25.75.0.25."km",90.0.2)
if (i.eq.1) call symbol (xnum.25.75.0.25."km",90.0.2)
                                                                                                                                                                                      thickness
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          construct and write an output data set compatible with slowi
                                                                                                                           write out a table on the plot with the model parameters
                                                                                                                                                                                      velocity
                                                                                                                                                                                                                                                                              call number(xnum,12.6,0.25,anl,90.0,-1)
                                                                                                                                                                                                                                                                                      call number(knum, 15.0,0.25,vel, 90.0,2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                t(sec)
                                                                                                                                                  call symbol(9.0,19.0,0,4,"mode(",90,0,5)
                                                                                                                                                                                                                                                                                                                                                                                                                              call number(xnum,12.6,0,25,an1,90,0,-1)
call number(xnum,15.0,0,25,vet,90,0,2)
                                                                           call plot(0.25,0.25,+20)
call symbol(4.0,12,0,0.5,id,90.0,2R)
call symbol(5.5,13,0,0,3,idate,90.0,2R)
                                                                                                                                                                                  call symbol(10.0,12.0,0.3,"layer
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                x (km)
                                             write a tabel and date on the plot
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              construct table of output values
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       write(6,52) jox((,1),et((,1))
do 45 j=3,30,3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               write(6,52) jox(ioj)ot(ioj)
do 50 jml,30
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       call plot(0.0,0.0,999)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           write(6,51) faxe(i)ate(i)
           call plot (ylenedire3)
                      call plot (0.0,0,0,2)
                                                                   call plot(1.0.1.0.+20)
                                                                                                                                                             call plot (9.1,21,0,2)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                Ę
                                                                                                                                                                                                                                                                                                                                                                                  xnum=xnum+0.5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     x(ivj)=x(ivj)/vh
                                                                                                                                                                                                                                            critdesc(i)
                                                                                                                                                                                                                                                        crittate(1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               format(" layer
                                                                                                                                                                                                                                 thick=2(i)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           critical travel time")
                                                                                                                                                                                                          do 60 imini
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        do 50 iminul
                                                                                                                                                                                                                      ve(=v(i)
                                                                                                                                                                                                                                                                                                                                                                                              cont inve
 diravhaylen
                                                                                                                                                                                                                                                                                                                                                                                                         an( **n(+1.0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     write(6,40)
                                                                                                                                                                                                                                                                                                                                                                                                                    ve(=v(n(+1)
                                                                                                                                                                                                                                                                   anlai
                                                                                                                                                                                                 xnum=10.5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                  end plot
                                                                                                                                                                                                                                                                                                                                                                                              9
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                9
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               42
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  50
                                   . . . .
```

urite(6,53)
urite(6,54) ((x(i,j),t(i,j),jxl,15,1),ixl,n()
format(i3,t45,f6,2,t6,2)
format(8x,i3,4x,f6,3,4x,f6,3)
format(10,7 slowi formatted output",/)
stop
end